



# **Powerful Suction**

Smart Inverter Motor® P9



### **Dual PowerPack**

Up to 80 minutes run time<sup>1</sup> with two interchangable batteries



# **One Touch Start**

Simple power control.



# **Self-Standing Kit**

Dock without wall mounting.





www.lg.com/au V1-01/18



DESIGN & CONVENIENCE			
Colour	Red		
Vacuum Type	Cordless Handstick		
Convenience			
Control Type	Button		
Telescopic Pipe	✓ (4 Lengths)		
Dust Bin Capacity	0.44L		
Convert to Handheld	✓		
Charging			
Charging Dock	✓		
Wall Mount Option	✓		
Self-Standing Kit	✓		

PERFORMANCE	
Aeroscience®	
Motor Technology	Smart Inverter Motor® P9
Cyclone Technology	Axial Turbo Cyclone®
Suction	
Power Modes	3 Modes
	(Turbo, Power, Normal)
Max Suction Power	Up to 140W
	(In Turbo Mode)
Battery	
Batteries Included	2
Battery Type	Lithium-lon
Battery Indicator	✓ (3 Step)
Charging Time	3.5 Hours
Simultaneous Charging	✓
Max Running Time	
Normal Mode Without Power Drive Nozzle®	Up to 40 minutes per battery
Normal Mode With Power Drive Nozzle®	Up to 30 minutes per battery
Power Mode	Up to 9 minutes per battery
Turbo Mode	Up to 6 minutes per battery
Filtration	
Technology	5 Step
Washable Filters	3
	(Pre-Filter, Mesh, Fine Dust Exhaust)
Noise (Turbo Mode)	86db

ATTACHMENTS	
Motorised Nozzles	
Carpet	✓ (Power Drive Nozzle <sup>®</sup> )
Hard Floor	√ (Power Drive Nozzle <sup>®</sup> )
Bedding Punch	-
Non-Motorised Nozzles	
Crevice Tool	✓
Combination Tool	✓

DIMENSIONS	
Packaging (W x D x H)	720mm x 295mm x 240mm
Weight (Hand Unit Only)	1.6kg
Weight (With Carpet Nozzle)	2.7kg

WARRANTY	
Handstick	2 Years Parts & Labour
Battery	12 Months Warranty
Smart Inverter Motor®	10 Years Warranty*
* 2 years parts and lahour +	8 years on motor (parts only)

COMPLIANCE	
EAN	8806098061853

# If you have any inquiries about our products, please feel free to contact our friendly customer service representatives on 1300 LG CARE.

Our Website www.lg.com/au
Customer Care 1300 LG CARE

(1300 54 2273)

#### **DISCLAIMERS**

**LG AUSTRALIA** 

<sup>1</sup> Up to 80 minutes run time when using 2 batteries in starting 'normal' mode without Power Drive Nozzle. Battery life may vary depending on settings and with use.

All product specifications are correct at time of printing. Specifications may change without prior notice. Customers

www.lg.com/au V1-01/18