
PORTABLE POWER **STATION**

便携式储能电源 150C



感谢您购买及使用本产品!

为确保能为您的手机或电子产品提供更好操作体验,在阅读本说明书的同时也请参阅您的手机或电子产品的说明书。首次充电对产品电池性能至关重要,首次充电时, 将产品连接电源插座,直到充满电为止。

名称	羽博便携式储能电源
型号	YB-150C
电池能量	153Wh(TYP)
电池容量	48Ah/3.2V
产品规格	149x142x113mm(约)
产品重量	1620g(約)
总输入功率	30W
输入Type-C	DC 20V=1.5A/15V=2A/12V=2.5A/9V=3A/5V=3A
USB总输出功率	30W
输出Type-C	DC 20V=1.5A/15V=2A/12V=2.5A/9V=3A/5V=3A
输出USB-A1	DC 12V=1.5A/9V=2A/5V=2.4A
输出USB-A2/A3	DC 5V=2A
输出Out-12V	DC 12V=10A (Max) (车充口)
输出Out-EC5	DC 12V=200A (Max) (汽车启动)
照明灯功率	5W
LED色温	4000K
执行标准	GB/T 35590-2017


配件清单:

150C便携式储能电源	x1	电源适配器	x1
汽车应急打火智能夹	x1	充电线	x1
说明书	x1		

由于每个地区对配件需求不同,所以以上配件会有不同。若有疑问请联系羽博客服。

操作说明

发下按键开关,显示屏数字标识显示剩余电量。长按按键进入灯光模式,单击一次进入 二级灯光模式,再按按键进入SOS模式,再按按键进入循环模式,任何档位长按按键退 出灯光模式。



如何利用储能电源为其它设备充电:

USB端口:智能手机、智能手表、数码相机、电子阅读器、平板电脑等。 Type-C端口:智能手机、手提电脑等。

12V车充端口: 灯具、汽车适配器等。 EC5端口: 汽车应急启动。

车充输出

_		
=	Mini冰箱 (40W)	4
	MILLINGOLD (LOAK)	-
	约3~4小时	
~		







USB输出

32寸TV (60W) 约2.5小时



EC5输出



小汽车 (200A)

充电状态:

给其他设备充电时

- 接入其他设备时,屏幕亮起并显示电量
- 电量指示灯熄灭,设备已充满电;

给150C杂电时:

- 显示屏数字显示当前电量,并在显示屏数字闪烁表示正在充电;
- 显示屏数字显示电量100,闪烁停止,150C已充满。

注 意:1.150C容量较大,使用适配器充满电需12小时左右,具体以实际为准。 2.若使用150C给设备充电时发现不能充电,请检查接线是否正常,牢固或充 电接口配件是否合适。建议选用羽博或正规品牌电源适配器为其充电。3. 储能 电源存在转化效率,故储能电源容量不等同于可充容量。4.储能电源适合大部 分手机充电,会出现不支持个别型号手机充电,这种情况本产品不在更换和保

安全性信息:

警告:不遵循这些安全说明可能会导致起火、触电、损坏或其他伤害。

切勿摔碰、切勿自行拆开或刺穿150C;切勿将150C暴露在火中、高温中或水中; 如果发现150C有鼓胀等其他不良现象或被充电设备有鼓胀等其他不良现象,请用户

停止使用1901。 此设备不适用于生理、感知和心智能力低下的人士(包括小孩),也不适用于缺乏相 关经验和知识的人士,除非有专门负责他们人身安全的人士监督或指导他们使用此 设备。应当看管好小孩,以确保他们不将此设备当作玩具来玩。

保修卡 ____ 联系电话: ____

訓博

东莞市羽博通讯设备有限公司 地址:广东省东莞市黄江镇长龙华裕街7号 网址:www.yoobao.com 邮箱:Sales@yoobao.cn

1.保修条件:本公司向羽博用户提供自产品购买之日起六个月的保修期。需要保修 服务时,请出示本保修卡,并请详尽填写相关内容。

2.保修范围:a、在正常使用的状态下出现的质量问题,非外力破坏造成的产品损坏; b、原则上不对尚在保修期内的产品收取维修费用,送修产品若遭人力损坏将酌情 收取检测或零配件费用。送修产品超出保修期的一律收取维修费。 c、产品维修期间,因无法使用该产品而造成的不便或损失,本公司均不承担任何责任。

3.以下情况不能享受保修服务:a、人为损坏。因使用不当造成的破坏、外观不正常磨

损, 摔伤, 电路烧毁, 挤压变形, 异物进入, 受潮, 产品上的密封标签被涂改或撕毁, 用户擅自拆装产品结构、使用不慎、操作不当、进水以及其他任何可见的人为损坏; b、因不可抗力因素造成的损坏。如地震、水灾、火灾、飓风或战争等。

产品中有毒有害物质或元素的名称及含量

	有毒有害物质或元素					
产品名称	铅(Pb)	汞 (Hg)	镉(Cd)	六价路 (Cr(VI))	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
YB-150C	0	0	0	0	0	0
O:表示该有害物质在该部件所有均质材料中的含量均在GB/T 35590-2017标准规定的限量要求以下。						
X:表示该有害物质至少在该部件的某一均质材料中的含量超出GB/T 35590-2017标准标准规定的限量要求。						

Yoobao

PORTABLE POWER STATION



Thank you for purchasing and using this product!

To ensure the best usage experience of your phones and devices, please carefully read this manual and the manual of your phones. The first charging is very important for the battery performance. Please charge this product to full in the first charging.

Technical Specifications:


Product Name	Yoobao Portable Power Station
Model	YB-150C
Battery Power	153Wh(TYP)
Battery Capacity	48Ah/3.2V
Size	about 149*142*113mm
Weight	about 1620g
Total Input Power	30W
Type-C Input	DC 20V=1.5A/15V=2A/12V=2.5A/9V=3A/5V=3A
Total USB Output	30W
Type-C Output	DC 20V=1.5A/15V=2A/12V=2.5A/9V=3A/5V=3A
USB-A1 Output	DC 12V=1.5A/9V=2A/5V=2.4A
USB-A2/A3 Output	DC 5V == 2A
Out-12V Output	DC 12V=10A (Max) (Car charger socket)
EC5 Output	DC 12V=200A (Max) (Car-jump-starting)
Power of Light	5W
LED Color Temperature	4000K
Standard	GB/T 35590-2017

ackage List:			
150C Portable Power Station	x1	Power Adapter	x1
Clamps	x1	Charging Cable	×1
Manual	x1		

Different countries may have different requirements for accessories. Please take actualproduct as the standard. Final interpretation is owned by YOOBAO company

Operations:

Press the power button and the LED display will shows the remaning power level. Long press the power button to turn on the light. Short press the power button another time for the second gear light, and press again to enter SOS mode, and press again to enter loop mode. Long press the button at any gear/mode to turn off the light.



How to charge other devices with Yoobao Power Station:

USB Output: Smart Phones, Smart Watches, Digital Cameras, E-Readers, Pads. Type-C Output: Smart Phones, Laptops.

12VC ar Charger Interface Output: Lamps, Car Adapters.

ECS Output: Vehicles(Emergency starting).

Car Charger Interface Output

-	ii ciiaigei iiite
	 Power for
٠	Mini-Fridge(40V
	about 3.4 hour



- 12V/5W LED Light about 26 hours



Ш	Mac Book12 about twice
FC5 O	utput

USB Output



- Charging Status:

Emergency Car Starting(200A)

Charging other devices:

The screen is on and shows the battery level.

The battery indicator light is off, the device is fully charged.

- Charging 150C:
 The digital display indicator displays the current power level and flashing, 150C is
- When the digital display indicator shows 100 and stops flashing, 150C is fully charged

Notice: 1. It will take about 12 hours to fully charge the 150C with adapter, and it shall subjec Notice: I, if will take about 12 hours to fully charge the JSO. With adapter, and it shall subject to the actual situation. 2. If JSOE is not working during rhanging, please check the abile and make sure it is firmly connected or the correct charging connector is used. We recommend using YOOBAO or other reputable adapters to charge the power bank. 3. Power station has its own conversion rate, so capacity in the power station does not equal to the total power when it charges other devices. A. The power station is compatible with most mobile phones, but it might not fit for some mobile phones, while not included in warranty and exchange conditions

Safety Information:

Warning: Not following the safety usage may cause fire, electric shock, damage to devices and injury to users.

uo not nit, open, install backwards, puncture, or expose it to fire, high temperature environments or any liquids. If you find a bulge or other abnormal phenomena on 150C, please stop. This device is not applicable to people who have physical or mental issues, children and those who are lack of the relavant knowledge and experience unless they are guided professionally. Children should be taken care of to make sure they don't use this device as a toy. Do not hit, open, install backwards, puncture, or expose it to fire, high temperature

Warranty –

Customer Name: ____ — Phone Number: —— ____ Date of Purchaes: ___

Dongguan YOOBAO Communication Devices Co. LTD Address: Building 7, Huayu Street, Changlong Village, Huangjiang Town, Dongguan, Guangdong, China Website:www.yoobao.com Email:Sales@yoobao.cn

1.Warranty condition: We provide 6 months warranty for YOOBAO users from the date when the product is purchased. When applying for the warranty service, please show this warranty card and fill in the blank.

2.Warranty scope: a. Quality problems appeared on normally use or damages caused not by external force. b. In principle, we do not charge if products are under warranty period, but human damage will be charge accordingly. Products beyond warranty period will be repaired at customers' expense. c. We are not responsible for the in convenience or loss caused by not being able to use the product during the repairing time.

3.The following circumstances are not under warranty conditions: a.Artificial damages: In the oriusing cutinosalities are in control warranty oriusions, aranical canages, improper use; product appearance worn abnormally, dropping; circuitry burned; squeeze; foreign matter enter into product; got damp; the seal label on the product has been changed or damaged; other obvious artificial damages. Other problems caused by customers such as dismounting the device, improper use and operation or products get wet, d.Damages caused by force majeure such as earthquake, flood, fire, hurricane

Toxic materials and content:

	Toxic materials and conten					
Material Name	Pb	Hg	Cd	Cr (VI)	PBB	PBDE
YB-150C	0	0	0	0	0	0
O: means this toxic material meets the requirements in standard GB/T 35590-2017						

X: means this toxic material does not meet the requirements in standard GB/T 35590-2017