

Panasonic®

Operating Instructions Blu-ray Disc™ Recorder Model No. **DMR-BWT835**

DIGA
Blu-ray



Thank you for purchasing this product.

Please read these instructions carefully before using this product, and save this manual for future use.

- **This Blu-ray Disc Recorder is for viewing and recording free to view channels only. It does not receive pay TV or encrypted channels.**

Region management information

BD-Video: This unit can play BD-Video discs supporting the region code “B”.

e.g.,



DVD-Video: This unit can play DVD-Video discs supporting the region number “4” or “ALL”.

e.g.,



Safety precautions

WARNING

Unit

- To reduce the risk of fire, electric shock or product damage,
 - Do not expose this unit to rain, moisture, dripping or splashing.
 - Do not place objects filled with liquids, such as vases, on this unit.
 - Use only the recommended accessories.
 - Do not remove covers.
 - Do not repair this unit by yourself. Refer servicing to qualified service personnel.
 - Do not let metal objects fall inside this unit.
 - Do not place heavy items on this unit.

AC mains lead

- To reduce the risk of fire, electric shock or product damage,
 - Ensure that the power supply voltage corresponds to the voltage printed on this unit.
 - Insert the mains plug fully into the socket outlet.
 - Do not pull, bend, or place heavy items on the lead.
 - Do not handle the plug with wet hands.
 - Hold onto the mains plug body when disconnecting the plug.
 - Do not use a damaged mains plug or socket outlet.
- The mains plug is the disconnecting device. Install this unit so that the mains plug can be unplugged from the socket outlet immediately.

Small object

- Keep the Memory Card out of reach of children to prevent swallowing.

CAUTION

Unit

- This unit utilizes a laser. Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation exposure.
- Do not place sources of naked flames, such as lighted candles, on this unit.
- This unit may receive radio interference caused by mobile telephones during use. If such interference occurs, please increase separation between this unit and the mobile telephone.
- This unit is intended for use in moderate climates.

Placement

- Place this unit on an even surface.
- To reduce the risk of fire, electric shock or product damage,
 - Do not install or place this unit in a bookcase, built-in cabinet or in another confined space. Ensure this unit is well ventilated.
 - Do not obstruct this unit's ventilation openings with newspapers, tablecloths, curtains, and similar items.
 - Do not expose this unit to direct sunlight, high temperatures, high humidity, and excessive vibration.

Batteries

- Danger of explosion if battery is incorrectly replaced. Replace only with the type recommended by the manufacturer.
- Mishandling of batteries can cause electrolyte leakage and may cause a fire.
 - Do not mix old and new batteries or different types at the same time.
 - Do not heat or expose to flame.
 - Do not leave the battery(ies) in a car exposed to direct sunlight for a long period of time with doors and windows closed.
 - Do not take apart or short circuit.
 - Do not recharge alkaline or manganese batteries.
 - Do not use batteries if the covering has been peeled off.
 - Remove batteries if you do not intend to use the remote control for a long period of time. Store in a cool, dark place.
- When disposing the batteries, please contact your local authorities or dealer and ask for the correct method of disposal.



DANGER - VISIBLE AND INVISIBLE LASER RADIATION WHEN OPEN. AVOID DIRECT EXPOSURE TO BEAM.	
FDA21 CFR/CLASS IIIb	
CAUTION - CLASS 3B VISIBLE AND INVISIBLE LASER RADIATION WHEN OPEN. AVOID EXPOSURE TO THE BEAM. IEC60825-1/CLASS 3B	
ATTENTION - RAYONNEMENT LASER VISIBLE ET INVISIBLE CLASSE 3B, EN CAS D'OUVERTURE, EVITER UNE EXPOSITION AU FAISCEAU.	
FORSIGTIG - SYNLIG OG USYNLIG LASERSTRÅLING KLASSE 3B, NÅR LÅGET ER ÅBENT, UNDGÅ AT BLIVE UDSAT FOR STRÅLEN.	
VARO - AVATTAESSA OLET ALTTIINA LUOKAN 3B NÄKYVÄÄ JA NÄKYMÄTÖNTÄ LASERSÄTELYÄ. VARO ALTISTUMISTA SÄTEELLE.	
WARNING - KLASSE 3B SYNLIG OCH OSYNLIG LASERSTRÅLING NÄR DENNA DEL ÄR ÖPPNAD. UNDVIK EXPONERING FÖR STRÅLEN.	
VORSICHT - SICHTBARE UND UNSICHTBARE LASERSTRAHLUNG KLASSE 3B, WENN ABDECKUNG GEOFFNET. NICHT DEM STRAHL AUSSETZEN.	
注意 - 打开时有可见及不可见激光辐射。避免光束照射。	
注意 - ここを開くとクラス3Bの可視及び不可視レーザー放射が出る。ビームの目又は皮膚への被ばくは危険! 見たり触れたりしないこと。	
VQL2Q40	

(Inside of product)

Supplied accessories

Please check and identify the supplied accessories.

(Product numbers correct as of February 2013. These may be subject to change.)

Remote control (N2QAYB000755):	1 pc.
Batteries for remote control:	2 pcs.
AC mains lead:	1 pc.
RF coaxial cable:	1 pc.
HDMI cable:	1 pc.

- Do not use AC mains lead with other equipment.

Indemnity concerning recorded content

Panasonic does not accept any responsibility for damages directly or indirectly due to any type of problems that result in loss of recording or edited content (data), and does not guarantee any content if recording or editing does not work properly. Likewise, the above also applies in a case where any type of repair is made to the unit (including any other non-HDD related component).

Restriction on use of unauthorized copied content

This unit adopts the following technology for copyright protection.

Cinavia Notice

This product uses Cinavia technology to limit the use of unauthorized copies of some commercially-produced film and videos and their soundtracks. When a prohibited use of an unauthorized copy is detected, a message will be displayed and playback or copying will be interrupted. More information about Cinavia technology is provided at the Cinavia Online Consumer Information Center at <http://www.cinavia.com>. To request additional information about Cinavia by mail, send a postcard with your mailing address to: Cinavia Consumer Information Center, P.O. Box 86851, San Diego, CA, 92138, USA.

Table of contents

Safety precautions	2
Supplied accessories	3
Getting started	
HDD and media information	6
- Recordable/playable contents	6
- Recording mode	8
- Notes	9
Unit care	11
Control reference guide	12
Connection	14
- Basic connections	14
- Amplifier/receiver connections	15
- Network connection	17
Settings	18
- TV operation buttons	18
- Easy Setting	19
- Easy Network Setting	20
FUNCTION MENU screen	22
Watching broadcasts	
Watching broadcasts	23
- Using Channel List	23
- Using TV Guide system	24
- Using channel information	24
- Operations while watching broadcast	25
- REWIND LIVE TV/PAUSE LIVE TV	25
Recording	
Recording TV programmes	27
- Operation during Recording	28
Timer recording	29
- Manually programming timer recording	30
- Timer recording options	30
- Timer recording from channel information	31
- Remote recording from outside	31
- Notes on timer recording	31
- To confirm and edit a timer programme	32
Playing back video	
Playing titles on the HDD	33
- DIRECT NAVIGATOR (VIDEO) screen	33
Playing titles on the media	36
- Notes for BD-Live discs	37
Operation during play	38
- General operations	38
- 3D video playback	40
Editing video	
Deleting recorded titles	41
Editing recorded titles	42

Copying video

Copying titles	46
- Copying from media other than HDD with DIRECT NAVIGATOR	48
- Copying titles with copying list	48
- Notes for copying	51
- Copying a finalised disc	52
- Copying Title Playing	53
- Copying HD Video (AVCHD) to the DVD-R in High Definition	53

Photo

Playing photos	54
- DIRECT NAVIGATOR (PHOTO) screen	54
- Photo play option	55
- Slideshow settings	55
Editing photos	56
Copying photos	57
- Selecting and copying the photos	57
- Copying automatically	57

Music

Playing music	58
- Copying music (MP3) to HDD	58
- Playing music recorded on HDD	59
- Operations during music play	60
Editing music/playlist	61

With Other Equipment

Recording from external equipment	62
- Manual Recording	62
- Flexible Recording via AV input	62
Copying the HD Video or the SD Video	63
- Copying HD Video (AVCHD)	63
- Copying SD Video (MPEG2)	64
Smart Home Networking (DLNA)	65
- Using this unit as Server	65
- Using this unit as Client	66
- Using this unit as Media Renderer	67

Convenient functions

VIERA Connect (Enjoying Internet Service)	68
- To enjoy video communication (e.g., Skype™)	68
Media management	69
Registering the external HDD (USB HDD)	71
- Connecting the USB HDD	71
- Disconnecting the USB HDD	71
- Registering the USB HDD	72
VIERA Link functions	73
Playback menu	74

Changing the unit's settings	77
- Common procedures	77
- Digital TV Tuning	79
- HDD / Disc / USB HDD	81
- Picture	83
- Sound	84
- Display	85
- Connection	85
- Network	87
- Others	90
- Language code list	93
Software (Firmware) Update	94
Other operations	95
- Entering text	95
- Switching the aspect ratio of the screen	95
- HOLD function	95

About descriptions in these operating instructions

- Pages to be referred to are indicated as "⇒ ○○".

Troubleshooting

Troubleshooting guide	96
- General operation	96
- Displays	97
- TV screen and video	97
- Sound	99
- Recording, timer recording and copying	99
- Play	100
- Edit	101
- Photo	101
- Music	102
- USB	102
- TV Guide	102
- Broadcast	102
- VIERA Link	103
- Network	103
- Reset	104
- Messages on the unit's display	104
- When you experience problems with Easy Network Setting	106

Reference

Specifications	108
Licenses	114
Limited Warranty	116
Index	117

Getting started

Watching broadcasts

Recording

Playing back video

Editing video

Copying video

Photo

Music

With Other Equipment

Convenient functions














Troubleshooting

Reference








HDD and media information

Recordable/playable contents

(-: Impossible)

Media type	Standard symbol		Recordable contents	Playable contents
Built-in hard disk drive (HDD)*¹		HDD	<ul style="list-style-type: none"> • Video • AVCHD/AVCHD 3D • JPEG • MPO (3D photo) • MP3 	
External hard disk drive (USB HDD)*¹ (⇒ 9)		USB HDD	<ul style="list-style-type: none"> • Video*² 	<ul style="list-style-type: none"> • AVCHD/AVCHD 3D*^{3, 4} • SD Video (MPEG2)*⁵ • MP4 • MPEG2 • Xvid • MKV • JPEG • MPO (3D photo) • MP3
BD-Video 		BD-V	—	<ul style="list-style-type: none"> • Video
BD-RE*¹ 		BD-RE	<ul style="list-style-type: none"> • Video • AVCHD/AVCHD 3D • JPEG • MPO (3D photo) 	
BD-R 		BD-R	<ul style="list-style-type: none"> • Video • AVCHD/AVCHD 3D*³ 	<ul style="list-style-type: none"> • Xvid • MKV
DVD-Video*⁶ 		DVD-V	—	<ul style="list-style-type: none"> • Video
DVD-RAM*¹ 		RAM	<ul style="list-style-type: none"> • Video • JPEG • MPO (3D photo) 	
DVD-R DVD-R DL  		DVD-R	<ul style="list-style-type: none"> • Video • AVCHD*³ 	<ul style="list-style-type: none"> • Xvid • MKV • JPEG • MPO (3D photo) • MP3

(–: Impossible)

Media type	Standard symbol	Recordable contents	Playable contents
DVD-RW^{※1} 		DVD-RW • Video –	• AVCHD ^{※3}
+R/+R DL		+R • Video –	• AVCHD ^{※3}
+RW^{※1}		+RW • Video –	• AVCHD ^{※3}
Audio CD (CD-DA) 		CD –	• Music
CD (including CD-R/RW)		–	• Xvid • JPEG • MPO (3D photo)
SD Cards^{※1} 		SD • JPEG • MPO (3D photo)	• AVCHD/AVCHD 3D ^{※3, 4} • SD Video (MPEG2) ^{※5} • MP4 • JPEG • MPO (3D photo)
USB memory		USB –	• AVCHD/AVCHD 3D ^{※3, 4} • SD Video (MPEG2) ^{※5} • MP4 • Xvid • JPEG • MPO (3D photo) • MP3

※1 Rewritable media

※2 It cannot be recorded directly. (Only compatible with copying from the built-in HDD)

※3 Recorded with AVCHD format compatible devices (Panasonic video camera, etc.). It may not be able to play back, add, or edit depending on the device.

※4 It cannot be played back directly from the USB HDD or USB memory. Playback is possible by copying to the HDD. (⇒ 63)

※5 Recorded with SD-Video format compatible devices (Panasonic video camera, etc.). It can be played back only after copying to HDD. (⇒ 64)

※6 Includes finalised DVD-R, DVD-R DL, DVD-RW, +R and +R DL.



- **+RW** This unit cannot record to 8X Speed +RW disc.
- The producer of the disc can control how discs are played. So you may not always be able to control play as described in these operating instructions. Read the disc's instructions carefully.
- With certain recording states and folder structures, the play order may differ or playback may not be possible.

HDD and media information

Playable contents on a DLNA server

When this unit works as a DLNA client (⇒ 66), following contents are playable.

- Recorded video*
- AVCHD*
- MP4
- MPEG2
- JPEG
- MPO (3D photo)
- MP3
- FLAC

* Only when the server is another DIGA. (⇒ 65)

• Depending on the server, the contents other than stated above can be played back.








About extension of files

File format	Extension							
MP4	“.MP4”	“.mp4”	“.MOV”	“.mov”				
MPEG2	“.MPG”	“.mpg”	“.MPEG”	“.mpeg”	“.M2TS”	“.m2ts”	“.MTS”	
	“.mts”	“.TS”	“.ts”					
Xvid	“.AVI”	“.avi”						
Subtitle text files*	“.SRT”	“.srt”	“.SUB”	“.sub”	“.TXT”	“.txt”		
MKV	“.MKV”	“.mkv”						
	“.SRT”	“.srt”	“.SSA”	“.ssa”	“.ASS”	“.ass”	“.SUB”	
	“.sub”	“.TXT”	“.txt”					
JPEG	“.JPG”	“.jpg”						
MPO (3D photo)	“.MPO”	“.mpo”						
MP3	“.MP3”	“.mp3”						

* The video file and subtitle text files are inside the same folder, and the file names are the same except for the file extensions.

• Some files may not be played back even if they have these extensions.

Recording mode

Recording Mode	DR	HG/HX/HE/HL/HM	XP/SP/LP/EP/FR
Feature	Programmes can be recorded in a nearly perfect broadcasted state.	Recording can be done with reduced recording volume in HD quality.	Recording can be done with reduced recording volume in SD quality.
Quality	Quality as the broadcast	High definition* ¹	Standard definition
Recordable media	  		   
Multiple audio	Record all multiple audio	Record only one audio	
Subtitles	Can be recorded	Can be recorded (only one subtitle)* ²	
Surround audio	Surround audio as the broadcast	Surround audio produced by conversion of broadcast audio format	Stereo audio

*¹ The SD quality programme can not be converted to HD quality.

*² You cannot select during play whether it appears or disappears.

Approximate recording times

Refer to “Recording modes and approximate recording times”. (⇒ 112)

• FR (Flexible Recording Mode)

The unit automatically selects the best possible recording rate between XP and EP (8 hours).

Notes

Notes for an External HDD (USB HDD)

You can use an external HDD in the following two ways. (A single HDD cannot handle those two ways simultaneously.)

- **For recorded titles**

Moving titles in the built-in HDD to a USB HDD to save the capacity of the built-in HDD.

- The USB HDD must first be registered on this unit. (⇒ 71)

- **For data files**

Playing back MP4, JPEG, MP3, etc. (data files) in a USB HDD with this unit.

- The USB HDD must be formatted in FAT12, FAT16, FAT32 and NTFS file system.
- The USB HDD over 2 TB is not usable.



- This unit supports USB 2.0 High Speed.
- Although this unit can use USB 3.0 devices as USB 2.0 devices, in certain cases USB 3.0 devices cannot be used due to differing connector shape, larger current ratings, etc. (Use of USB 2.0 devices is recommended.)
- This unit does not recognize USB HDDs other than those in which the size of one sector is 512-bytes. (For details, consult the dealer of your USB HDD.)
- This unit does not guarantee connection with all USB devices.

Notes for the disc

- **Disc recorded on another device**

- It may be necessary to finalize the disc, create Top Menu or close the session on the equipment used for recording to play on this unit.
- **DVD-RW** Recorded in DVD Video Recording (DVD-VR) format
 - This unit can play back and copy to HDD.
 - This unit does not support editing or recording.
 - It is possible to record and edit with DVD-Video (DVD-V) format by formatting discs with this unit.
- Recording may not be possible to discs which were used for recording on other equipment.

- **Play on other players**

- **BD-RE** **BD-R** When these discs cannot be played back on other Blu-ray Disc players, etc. (e.g., title recorded with HE-AAC audio format), convert the recording mode to play them back. (⇒ 44, File Conversion)
- **DVD-R** **DVD-RW** **+R** Finalisation is needed. (⇒ 70)
- **+RW** If the disc failed to play on other equipment, we recommend you create a Top Menu (⇒ 70).

- **Regarding 8 cm Disc**

This unit cannot record or edit the 8 cm disc. Only playback or copy to the HDD is possible.

- **Discs that cannot be played**

- DVD-RAM that cannot be removed from their cartridges
- 2.6 and 5.2 GB DVD-RAM, 12 cm
- HD DVD
- CD-ROM, Photo CD, PD, etc.
- DVD-Audio
- Super Video CD, Super Audio CD, Video CD



- Operation and sound quality of CDs that do not conform to CD-DA specifications (copy control CDs, etc.) cannot be guaranteed.

HDD and media information

Notes for the SD cards

• Compatible SD card

- SD Memory Card
(from 8 MB to 2 GB, FAT12 and FAT16 formats)
- SDHC Memory Card
(from 4 GB to 32 GB, FAT32 format)
- SDXC Memory Card
(48 GB, 64 GB, exFAT format)

• Using miniSD card or microSD card

Mini-type and micro-type cards can also be used, but must be used with adaptor cards (optional).

To format an SD card

Refer to “Format Disc/Format Card”. (⇒ 69)



- Usable memory is slightly less than the card capacity.
- If the SD card is formatted on other equipment, the time necessary for recording may be longer or the card may not be able to be used on this unit. In these cases, format the card on this unit.
- SDHC Memory Cards and SDXC Memory Cards can be used in equipment that is compatible with the appropriate cards. (SDHC Memory Cards can also be used in equipment compatible with SDXC Memory Cards.)

Notes for the USB memories

USB memories support FAT12, FAT16, FAT32 and NTFS file systems.



- The USB memory over 2 TB is not usable.
- This unit supports USB 2.0 High Speed.
- This unit does not guarantee connection with all USB devices.

Media handling


- Do not touch the recorded surface of the discs or the terminal surface of the SD cards.



- If there is dirt or condensation on the disc, wipe with a damp cloth and then wipe dry.



- Do not attach labels or stickers to discs.
- Do not use disc cleaning sprays, benzene, thinner, static electricity prevention liquids or any other solvent.
- Do not use ballpoint pens or other hard writing implements, when writing on the label side of the disc.
- Do not drop, stack, or impact discs.
- Do not place objects on discs.
- Do not use the following discs:
 - Discs with exposed adhesive from removed stickers or labels (rental discs, etc.).
 - Discs that are badly warped or cracked.
 - Irregularly shaped discs.



- Do not expose the terminals of the SD card to water, garbage or other strange things.
- Do not place in the following areas:
 - In hot places, such as under the direct sunlight.
 - In very dusty or humid areas.
 - Locations susceptible to significant difference in temperature (condensation can occur).
 - Where static electricity or electromagnetic waves occur.

Unit care

HDD/USB HDD handling care

• The HDD is a high precision device

The HDD is a high precision recording instrument and is easily susceptible to damage. Therefore, be careful of the following points while the unit is turned on, especially during operation, otherwise the HDD and the recorded content may be damaged:

- Do not subject the unit to any vibration and shock.
- Do not remove the AC mains lead from the household mains socket.

• The HDD is a temporary storage device

- The HDD is not an everlasting storage device. It is recommended to save the recorded content on a disc or to keep the original data or CDs that they were copied from.
- If you notice a problem with the HDD such as repetitive strange sounds, immediately save (backup) all content and request service. If you continue using the HDD with a problem, the unit or the recorded content will be damaged.

• If the HDD or USB HDD is damaged, the recorded content cannot be recovered.

Setup precautions

- **Place the unit on a surface that is flat and not subject to vibration or impact.**
- **Do not place on anything that generates heat like a Set Top Box, etc.**
- **Place in an area where condensation does not occur. Conditions where condensation may occur**
 - When there is an extreme change in temperature (e.g., when subjected to an air conditioner or when cooled air directly impacts the unit).
 - When there is high humidity or a lot of steam in the room.

In the above situation, **without turning the unit on**, let the unit adjust to the room temperature and wait 2–3 hours until condensation is gone.

- **Do not block the cooling fan on the rear of the unit.**
- **The unit may breakdown if cigarette smoke or bug spray/vapour, etc. gets inside the unit.**

When moving the unit

Before moving the unit, ensure the disc tray is empty.

- 1 Switch the unit to standby mode. (Wait until "BYE" disappears from the display.)
- 2 Remove the AC mains lead from the household mains socket.
- 3 Move only after the unit has come to a complete stop (approx. 3 minutes) in order to avoid subjecting to vibration and shock. (Even after the unit is switched to standby mode, the HDD continues operating for a short time.)

Cleaning

• This unit

- Wipe with a soft, dry cloth.
- Never use alcohol, paint thinner or benzine to clean this unit.
- Before using chemically treated cloth, carefully read the instructions that came with the cloth.

• This unit's lens

Use the **Lens cleaner** (optional) to clean the unit's lens.

Lens cleaner: RP-CL720AE

- This lens cleaner may not be for sale depending on the region.

When requesting this unit for repair

The registration of the USB HDD may be cancelled in the process of repairing this unit.

You can use the USB HDD again by re-registering, but all recorded content already on the USB HDD will be lost. In such cases, the recorded content (data) cannot be recovered.

To dispose or transfer this unit


This unit may contain private information. Before disposing of or transferring this unit, perform the following to delete the data, including personal or secret information:

- Format HDD (⇒ 77, 82)
- Perform "Shipping Condition" (⇒ 77, 93)

Control reference guide

Instructions for operations are generally described using the remote control.

Remote control




- ① Transmit the remote control signal
 - Point it at remote control signal sensor on this unit. (⇒ 13)
- ② Switch the unit from on to standby mode or vice versa
- ③ Select drive (HDD, BD, SD or USB)
- ④ Select channels and title numbers, etc./Enter numbers or characters
- ⑤ Switch to the previously watched channel (⇒ 23)
- ⑥ Basic operations for recording and play, REWIND LIVE TV/PAUSE LIVE TV (⇒ 25)
- ⑦ Show Information (⇒ 24, 34, 38)
- ⑧ Selection/OK, Frame-by-frame (⇒ 39)

- ⑨ Show DIRECT NAVIGATOR, Top Menu, Pop-up Menu (⇒ 33, 39)
- ⑩ Show OPTION menu (⇒ 42, 56, 61)
- ⑪ Colour buttons (Use in accordance with instruction on the screen.)
- ⑫ Start recording (⇒ 27, 62)
- ⑬ Select a conversion mode/recording mode (⇒ 27, 62)
- ⑭ Show the Timer Recording screen (⇒ 30)
- ⑮ Create chapter (⇒ 39)
- ⑯ Input select (⇒ 23, 62)
- ⑰ To delete unwanted recorded titles, timer programmes, photos or music (⇒ 41)
- ⑱ TV operation buttons (⇒ 18)
- ⑲ Channel select (⇒ 23)/Change pages in the DIRECT NAVIGATOR screen etc.
- ⑳ Show the VIERA Connect screen (⇒ 68)
- ㉑ Switching to the radio channel list (⇒ 23)
- ㉒ Start up a video communication (⇒ 68)
- ㉓ Exit the menu screen
- ㉔ Show the TV Guide screen (⇒ 24)
- ㉕ Show the FUNCTION MENU screen (⇒ 22)
- ㉖ Return to previous screen
- ㉗ Show subtitles (⇒ 25, 39)
- ㉘ Show Teletext (⇒ 25)
- ㉙ Select audio (⇒ 25, 39)
- ㉚ Skip the specified time (⇒ 39)
- ㉛ Skip approx. 1 minute forward (⇒ 39)
- ㉜ Skip approx. 10 seconds backward (⇒ 39)

Insert batteries


Insert so the poles (+ and -) match those in the remote control.



R6/LR6, AA

(Alkaline or manganese batteries)


Main unit



① Standby/on switch (⏻/⏻)

Press to switch the unit from on to standby mode or vice versa. In standby mode, the unit is still consuming a small amount of power.

② Open/close disc tray



③ Blue LED

- It is possible to set the LED to turn on/off. (⇒ 85, Blue LED)

④ Disc tray


⑤ USB port

⑥ SD card slot

- When removing the SD card, press on the centre of the card and pull it straight out.



- While writing to/reading from the media, do not switch the unit to standby mode or remove the media. Such action may result in loss of the media contents.
- When inserting the media, ensure that it is facing the right way up.



⑦ Recording indicator

- The indicator will light up while recording.
- The indicator will blink while recording is paused and before recording starts.

⑧ CALL LED

- The LED will light up when this unit receives incoming call etc. of the video communication. (⇒ 68)

⑨ Remote control signal sensor

- Angle: Approx. 20° up and down, 30° left and right
- Distance: Within approx. 7 m in front of the unit


⑩ Channel select (⇒ 23)

⑪ Start recording (⇒ 27)

⑫ Stop

⑬ Start play

Display



1 SD card slot indicator

2 Copying indicator

3 Disc indicator

4 Drive (HDD, BD or SD) indicator

5 Remote control signal indicator

6 Main display section indicator

- Current time
- Playback counter
- Various messages (⇒ 104)

7 Playback indicator

8 USB port indicator

9 Timer recording indicator


- This indicator lights up when the timer recording standby is activated.

Connection

Basic connections

3D programmes can be played back when this unit is connected to a 3D compatible TV.

- Before connection, turn off all equipment and read the appropriate operating instructions.



To connect and register the USB HDD (optional)

Refer to "Registering the external HDD (USB HDD)". (⇒ 71)

To connect the Communication Camera (optional)

Refer to "VIERA Connect (Enjoying Internet Service)". (⇒ 68)

About HDMI cable

If you use an optional HDMI cable, use the High Speed HDMI cables. Non-HDMI-compliant cables cannot be utilized.

It is recommended that you use Panasonic's HDMI cable.

When outputting 1080p signal, please use HDMI Cables 5.0 meters or less.

When the unit is not to be used for a long time

To save power, unplug it from the household mains socket. This unit consumes a small amount of power, even when the unit is in standby mode.


[approx. 0.2 W ("Quick Start" is not activated and "RF OUT (Aerial Signal)" is set to "Off")]



- This unit cannot connect the TV that does not have the HDMI terminal.
- The HDMI connection supports VIERA Link "HDAVI Control" (⇒ 73).
- You cannot connect this unit to DVI devices that are incompatible with HDCP.
Depending on the device, images may not display properly or at all when connecting with a DVI/HDMI switching cable. (Audio cannot be output.)
- If you are connecting to a TV that is only compatible with 2 channel audio output, audio with 3 channels or more will be down mixed and output as 2 channels, even if connecting with an HDMI cable. (Some discs cannot be down mixed.)

Connect the Set Top Box or video equipment

- Connect to terminals of the same colour.




Amplifier/receiver connections

HDMI terminal

3D programmes can be played back when this unit is connected to a 3D compatible amplifier/receiver and a 3D compatible TV.

- You will not be able to view 3D programmes with this connection if your amplifier/receiver is not 3D compatible.




- VIERA Link function is possible by connecting to a TV or amplifier/receiver compatible with VIERA Link.
- When using a TV or an amplifier/receiver that does not display "ARC compatible" on the HDMI terminal, it is necessary to connect the TV and the amplifier/receiver with a digital audio cable to enjoy the TV audio on the amplifier/receiver.

Connection

■ Amplifier/receiver not compatible with 3D

3D programmes can be played back when this unit is connected to a 3D compatible TV.


- This connection only supports up to 5.1ch.




- VIERA Link function is possible by connecting to a TV or amplifier/receiver compatible with VIERA Link.
- When using a TV or an amplifier/receiver that does not display "ARC compatible" on the HDMI terminal, it is necessary to connect the TV and the amplifier/receiver with a digital audio cable to enjoy the TV audio on the amplifier/receiver.

DIGITAL AUDIO OUT terminal

■ Using Optical digital audio cable




■ Using Coaxial cable



- When you do not want the audio to be output from the TV, set "HDMI Audio Output" to "Off" (⇒ 77, 87).

AUDIO OUT terminal

- Connect to terminals of the same colour.



Network connection

When this unit is connected to the network, you can enjoy network functions (DLNA function, VIERA Connect, etc.).

For details about connection method, refer to the instructions supplied with the connected equipment.

After you make the LAN cable/Wireless LAN connection, the network setting is needed.
(⇒ 20, Easy Network Setting)

■ Precautions of Wireless LAN connection

The following limits are in place regarding the usage of this unit. You must be aware of these limits before using this unit.


Panasonic will in no way be responsible for any incidental damage which may arise due to a failure to obey these limits, or to any condition of use or disuse of this unit.

- **Data transmitted and received over radio waves may be intercepted and monitored.**
- **This unit contains delicate electronic components.**

Please use this unit in the manner in which it was intended and follow the following points:


- Do not expose this unit to high temperatures or direct sunlight.
- Do not bend, or subject this unit to strong impacts.
- Keep this unit away from moisture.
- Do not disassemble or alter this unit in any way.

LAN cable connection




- Use category 5 or above straight LAN cables (STP) when connecting to peripheral devices.
- Inserting any cable other than a LAN cable in the LAN terminal can damage the unit.

Wireless LAN connection



- For up-to-date compatibility information on your Wireless router refer to <http://panasonic.jp/support/global/cs/> (This site is in English only.)
- The unit is not compatible with public wireless LAN services.

Settings



TV operation buttons
(⇒ right)

To exit the screen

Select and enter buttons

FUNCTION MENU (⇒ 22)

To return to the previous screen

TV operation buttons

The TV can be operated from the TV operation buttons of the remote control.

- Perform the setting if you cannot operate the TV with the TV operation buttons.

While pressing [TV ⏻], enter the code with the number buttons.

Manufacturer and Code No.

Brand	Code	Brand	Code
Panasonic	01/02/03/04	NEC	36
AIWA	35	NOBLEX	33
AKAI	27/30	NOKIA	25/26/27/60/61
BEKO	05/71/72/73/74	NORDMENDE	10
BENQ	58/59	OLEVIA	45
BRANDT	10/15	ONWA	30/39/70
BUSH	05	ORION	05
CENTREX	66	PEONY	49/69
CURTIS	05	PHILCO	41/48/64
DAEWOO	64/65	PHILIPS	05/06/46
DESMET	05	PHONOLA	05
DUAL	05	PIONEER	37/38
ELEMIS	05	PROVIEW	52
FERGUSON	10/34	PYE	05
FINLUX	61	RADIOLA	05
FISHER	21	SABA	10
FUJITSU	53	SALORA	26
FUNAI	63/67	SAMSUNG	32/42/43/65/68
GOLDSTAR	05/50/51	SANSUI	05
GOODMANS	05	SANYO	21/54/55/56
GRADIENTE	36	SCHNEIDER	05/29/30
GRUNDIG	09	SEG	05/69/75/76/77/78
HITACHI	05/22/23/40/41	SELECO	05/25
IRRADIO	30	SHARP	18
ITT	25	SIEMENS	09
JVC	17/30/39/70	SINUDYNE	05
KDS	52	SONY	08
KOLIN	45	TCL	31/33/66/67/69
KONKA	62	TELEFUNKEN	10/11/12/13/14
LG	05/50/51	TEVION	52
LOEWE	07/46	THOMSON	10/15/44
MAG	52	TOSHIBA	16/57
METZ	05/28/79	WHITE	05
MITSUBISHI	05/19/20/47	WESTINGHOUSE	
MIVAR	24	YAMAHA	18/41

- If the brand of your TV is not listed or the code number is invalid for the TV, this remote control is not compatible with your TV.



- If your TV brand has more than one code listed, select the one that allows correct operation.

Easy Setting

1 Turn on the TV, then select the appropriate AV input to suit the connections to this unit.

2 Press $\left[\text{⏻}\right]$ on the remote control or $\left[\text{⏻/I}\right]$ on this unit.

- The Easy Setting will start at the initial power on.

3 Follow the on-screen instructions and perform the settings.

- When the Download from TV screen appears, the setting information on the TV is acquired by this unit. (⇒ 73)

Auto Setup starts.

(This operation may take some time.)

e.g.,

Digital TV Auto Tuning			
Progress		CH 6	69
This will take about 3 minutes.			
RF Ch	Channel Name	Type	Quality
35	○○○○	Digital TV	10
35	○○○○	Digital TV	10
Digital TV: 2			
Searching			
RETURN			

After tuning has been completed, clock will be set automatically.

If the clock setting screen appears, set the time manually (⇒ 91, Clock).

4 Set “Quick Start” to “On”, “Off” or “Timer Setting for Quick Start”, then press [OK].

Quick Start	
On	
Off	
Timer Setting for Quick Start	6:00 AM — 11:00 PM

• **On**

It is possible to start quickly from standby mode.

• **Off**

Power consumption in standby mode is minimized. (⇒ 108)

However, startup time from standby mode will be longer.

• **Timer Setting for Quick Start**

“Quick Start” is activated when the set time comes. (If the clock has not been set, this function is not activated at all hours.)

Settings

- 5** If the TV aspect setting screen appears:
Select the item to match the type of TV connected.
For details, refer to "TV Aspect". (⇒ 86)

When "Easy Setting has been completed."
appears, Easy Setting is complete.

- Select "Yes" to proceed to "Easy Network Setting". (⇒ right)
- Select "No" to finish the Easy Setting.

To stop partway

Press [RETURN ⊕].

To restart setup

- 1 Press [FUNCTION MENU]. (⇒ 18)
- 2 Select "Setup" in "Others", then press [OK].
- 3 Select "Auto Setup" in "Digital TV Tuning", then press [OK].
- 4 Select "Yes", then press [OK].

To confirm that channels have been tuned correctly

Refer to "Using Channel List". (⇒ 23)




- If tuning is cancelled partway through, it may not be possible to receive the channels. Restart setup again.

Easy Network Setting

After completing "Easy Setting", you can continue with "Easy Network Setting".

- 1** Select "Wired" or "Wireless", then press [OK].



- 2** Follow the on-screen instructions and make the following confirmation and settings.

"Wired" connection:

- Home Network Connection Check
- Home Network function
- Internet Connection Test

"Wireless" connection:

- Before beginning wireless connection setup
Obtain your Network name (SSID).
An SSID (Service Set IDentification) is a name used by wireless LAN to identify a particular network. Transmission is possible if the SSID matches for both devices.
- Wireless Settings
- Home Network Connection Check
- Home Network function
- Internet Connection Test

- 3** When "Easy Network Setting is finished."
appears.
Press [OK].

Connection method to wireless access point

Search for wireless network:

- 1 Select "Search for wireless network", then press [OK].
- 2 The available wireless networks will be displayed. Select your network name and press [OK].
 - If your Network name is not displayed search again by pressing the red button on the remote control.
 - Stealth SSID will not be displayed. Enter manually by using "Wireless Settings". (⇒ 77, 87)
- If your wireless network is encrypted, Encryption Key Input Screen will be displayed. Input the encryption key of your network.


WPS (PUSH button):

If your Wireless router supports WPS (PUSH button), you can easily perform the settings by pressing WPS button on it.

WPS (Wi-Fi Protected Setup™) is a standard that facilitates settings relating to the connection and security of wireless LAN devices.

- 1 Select "WPS (PUSH button)", then press [OK].
- 2 Press WPS button or corresponding button of Wireless router until the lamp starts flashing.

e.g.,



- Wi-Fi Protected Setup™-compatible Wireless router may have the mark.
 - For details, refer to the operating instruction of Wireless router.
- 3 Press [OK].

When you experience problems

Refer to "When you experience problems with Easy Network Setting". (⇒ 106)

To restart Easy Network Setting

- 1 Press [FUNCTION MENU]. (⇒ 18)
- 2 Select "Setup" in "Others", then press [OK].
- 3 Select "Easy Network Setting" in "Network", then press [OK].

To redo settings individually

If "Easy Network Setting" did not work properly or when you change the settings individually, perform the following steps:

- 1 Press [FUNCTION MENU]. (⇒ 18)
- 2 Select "Setup" in "Others", then press [OK].
- 3 Select "Network Settings" in "Network", then press [OK].
- 4 Refer to "Network Settings". (⇒ 87)

Check security before using Home Network function

If you set "Home Network function" to "On", all connected devices on the same network can access this unit. Ensure that the router for your home network has adequate security system to prevent unauthorized access.




- Refer to the operating instructions of the hub or router.
- If you set "Home Network function" to "On", the setting for "Quick Start" is fixed to "On".
- Do not use this unit to connect to any wireless network for which you do not have usage rights. During automatic searches in a wireless network environment, wireless networks (SSID) for which you do not have usage rights may be displayed; however, using these networks may be regarded as illegal access.
- After performing network settings on this unit, the settings (encryption level, etc.) of the Wireless router might change. When you have trouble getting online on your PC, perform the network settings on your PC in accordance with the settings of Wireless router.
- Please be aware that connecting to a network without encryption may result in the content of the communication being illegitimately viewed by a third party, or the leaking of data such as personal or secret information.

FUNCTION MENU screen


You can easily access the desired functions, such as playback, timer recording, the unit's settings etc. via the FUNCTION MENU.

1 Press [FUNCTION MENU].



2 Select the item, then press [OK]

e.g.,



FUNCTION MENU list

FUNCTION MENU

- Playback Contents
 - Video (⇒ 33)
 - Video (AVCHD) (⇒ 36)
 - Video (MP4) (⇒ 36)
 - Photo (⇒ 54)
 - Music (⇒ 58)
 - Top Menu (⇒ 36)
 - Menu (⇒ 36)
- TV Guide (⇒ 24)
- Timer Recording (⇒ 29)
- Copy
 - Copy Video (⇒ 48)
 - Copy Video (AVCHD) to DVD-R (⇒ 53)
- Network
 - Home Network (DLNA Client) (⇒ 66)
 - Home Network (Media Renderer) (⇒ 67)
 - Network Service (⇒ 68)
 - Remote Recording (⇒ 31)
- Others
 - Playlists (⇒ 36)
 - Flexible Recording via AV input (⇒ 62)
 - Copy Video (AVCHD) (⇒ 63)
 - Copy Video (MPEG2) (⇒ 64)
 - Copy New Photos (⇒ 57)
 - Blu-ray Disc Management (⇒ 69)
 - DVD Management (⇒ 69)
 - SD Card Management (⇒ 69)
 - BD-Video Data Management (⇒ 37)
 - Setup (⇒ 77)
 - You can change the unit's settings of Digital TV Tuning, Sound, Display, Connection, Network etc. in the Setup menu.
- Drive Select
 - HDD
 - Blu-ray Disc / DVD
 - SD Card
 - USB Device
 - USB HDD



- Selectable items will change depending on the type and status of the media.

Watching broadcasts

Instructions for operations are generally described using the remote control. (⇒ 12)

1 Press [INPUT SELECT] and select “TV”, then press [OK].

2 Press [CH ^ v] to select the channel.

- You can also select the channel by the following operations
 - Using number buttons.
 - Using Channel List (⇒ right)
 - Using TV Guide system (⇒ 24)
 - Using channel information (⇒ 24)

To switch to the channel you have previously watched

Press [LAST VIEW .

- This function will work only for the channels you have watched for more than 10 seconds.

To switch to the radio channels or to the all channels

Press [RADIO/TV].



- When you are watching the 3D programme, subtitles and TV Guide, etc., may not display correctly depending on the settings. (⇒ 40, 3D Type, Signal Format)

About the PIN for parental control


If you have set a ratings level (⇒ 80, Child Lock (Parental Rating)), you may be asked to enter the PIN. In that case, enter the 4-digit PIN with the number buttons by following the on-screen instructions.

- **Make a note of the PIN you have decided on in case you forget it.**
- PIN can be changed via “PIN Entry”. (⇒ 92)

Using Channel List

You can select from the list of channel names.

1 Press [OK].



Channel names

2 Select the channel, then press [OK].


To edit the channel list

Refer to “Channel List”. (⇒ 80)

Watching broadcasts

Using TV Guide system

- 1 Press [GUIDE].
TV Guide screen appears.



- 2 Select the programme, then press [OK].
- 3 Select "View", then press [OK].

Page up/down

Press [CH \wedge v].

To view a programme list for another day

Press the green button (Previous) or the yellow button (Next).

To see programme information

Press [STATUS ①].

To retrieve the programme data for the area where data have not been acquired

Select the area, then press [STATUS ①].

- Some broadcasters may not send the programme data. You cannot retrieve the data from them.

To set a timer Recording using the TV Guide System

Refer to "Timer recording". (⇒ 29)




- Selection of channel is made easy by creating a Favourite of the channels you watch often. (⇒ 79, Favourites Edit)

Using channel information


While watching a programme

Press [STATUS ①].



Channel information appears.

e.g.,



- 1 Current Category
- 2 Set timer (⇒ 31)
- 3 Subtitle
- 4 Teletext
- 5 Multiple audio

To show detailed information

Press [STATUS ①] again.

To hide the information screen

Press [EXIT \otimes].

To change Category

Press the blue button.

• To register your favourite channels

- 1 Press [OPTION].
- 2 Select "Digital TV Menu", then press [OK].
- 3 Select "Favourites Edit", then press [OK].
- 4 Refer to "Favourites Edit". (⇒ 79)

To switch between the current programme and the next programme


Press [◀, ▶].

To switch to another channel

Press [▲, ▼], then press [OK].

Operations while watching broadcast

To show subtitle

When “” appears in channel information (⇒ 24)

Press [STTL ].


- Press again to hide subtitle.






Switching audio

Press [AUDIO].

- Audio will switch according to the contents of the programme every time it is pressed.

To show Teletext

When “” appears in channel information (⇒ 24)

- 1 Press [TEXT ].
- 2 Use [, , , , number buttons or colour buttons, etc. according to on-screen instructions.



- You can change the display mode. (⇒ 77, 85, Teletext)

Aspect

You can switch the screen mode.

Refer to “Switching the aspect ratio of the screen”. (⇒ 95)

REWIND LIVE TV/PAUSE LIVE TV

This unit temporarily saves a live TV programme you are watching with this unit's tuner on HDD.

REWIND LIVE TV

You can rewind live TV programme to the point where temporary save has started (up to 1.5 hours).

- REWIND LIVE TV does not work when watching a programme via external input.

PAUSE LIVE TV


You can pause live TV programme and restart watching from the paused position.

1 While watching TV

REWIND LIVE TV:

Press [SLOW/SEARCH ] to rewind.

PAUSE LIVE TV:

Press [PAUSE ] to pause.

- The maximum amount of the temporary save is 1.5 hours.

2 When you want to resume:

Press [PLAY/× 1.3 ].


- You can perform search or Quick View, etc.
- If temporary save stops, playback will be performed by that point.

Watching broadcasts


Display information

While pausing or rewinding a broadcast:

Press [STATUS ①].




- Press [STATUS ①] again.



While pausing a programme via external input:

Press [STATUS ①].



- ① The time that you can rewind the live programme.
- ② The amount of time temporarily saved on HDD.
- ③ The time of the current playback position.

To stop REWIND LIVE TV or PAUSE LIVE TV

- 1 Press [STOP ■].
- 2 Select "Yes", then press [OK].

To hide the display information

Press [EXIT ⊗].



- The unit cannot rewind and play more than 1.5 hours prior to the current time.
- Temporary save stops in the following cases:
 - When switching to other channels or other screen
 - When recording of the watching programme is started
 - When two programmes simultaneous recording is started
 - When performing PAUSE LIVE TV or REWIND LIVE TV for more than 8 hours (This may vary depending on the HDD free space.)
- These functions do not work in the following cases:
 - When the clock is not set
 - While recording two programmes simultaneously
 - While copying
 - While watching a programme being recorded
 - When a radio programme is selected
 - REWIND LIVE TV:
 - When "REWIND LIVE TV" is set to "Off" (⇒ 82)
 - PAUSE LIVE TV:
 - When a timer recording via external input is started while watching a programme via external input
- PAUSE LIVE TV:

You can operate this unit with the TV remote control by using VIERA Link (⇒ 73).
Refer to the TV operating instructions.

Recording TV programmes



- This operation will only record to built-in HDD.
- This unit can record two programmes being broadcasted at the same time.

1 Select the channel to record.

2 Press [REC MODE] and select the conversion mode, then press [OK].

- This unit will record the programmes in DR mode once, and then automatically convert to the selected recording mode while this unit is in standby.
- Recording mode (⇒ 8)

Conversion Mode Setting		
HDD Remain:	0 h 0 m (DR)	Data Size
	Off (DR)	
High Definition	HG	Large ↕ Small
	HX	
	HE	
	HL	
	HM	
Standard Definition	XP	Large ↕ Small
	SP	
	LP	
	EP	

- The conversion mode set here is used as an initial value for the next recording.

3 Press [REC ●].

Recording starts.

- "REC1" or "REC2" will light on the unit's display.

4 Select "Automatic Stop", then press [OK].

• One touch recording (OTR)

Recording stops automatically when the programme ends.

REC1/OTR	
○○○○	8:00 AM - 8:45 AM
Vacation	
Automatic Stop at 8:45 AM	
Recording Time	30 min
Continuous recording	

- You can also select "Recording Time" or "Continuous recording". (⇒ right)

To set the recording time

- 1 Select "Recording Time" or "Continuous recording" in step 4 (⇒ left).

Recording Time:

You can set the length of recording time from 30 minutes to 4 hours.

- You can select the recording time with [◀, ▶].

Continuous recording:

The recording is continued until you press [STOP ■].

- 2 Press [OK].

To convert the recording mode after recording in DR mode

Refer to "File Conversion". (⇒ 44)

To confirm whether the conversion is completed

Refer to "To confirm whether the conversion is completed". (⇒ 45)

To cancel a conversion

Refer to "To cancel a "During standby" conversion". (⇒ 45)



- One recording will terminate when simultaneous recording is being done and timer recording starts.
- Teletext will not be recorded.
- Following contents or media cannot be played back while recording.
 - Xvid and MKV file
 - photo
 - USB HDD (For data files) and USB memory
- Copying cannot be performed while recording.
- When "Automatic Standby after OTR" is set to "On" (⇒ 90), this unit is turned to standby mode if this unit is not operated for approximately 5 minutes after completing "Automatic Stop" or "Recording Time".
- The title before conversion (the title recorded in DR mode) will be deleted once the conversion is completed.
- Conversion will take about the same time as the recorded duration.
- When the HDD does not have enough remaining space, conversion will not start.
- Conversion is stopped when this unit is turned on. Conversion will start from the beginning again once the unit is switched to standby mode.
- The conversion will not start if the timer recording is scheduled within the time required for the conversion.
- When converted, audio content and subtitle will be converted with the same settings as at the start of recording.


Recording TV programmes

Operation during Recording

To check the recording programme

Press [STATUS .

e.g., While recording two programmes simultaneously




Recording programme not displayed on the TV

To stop recording

Press [STOP .

When recording one programme:


If the following screen appears



Select "Yes", then press [OK].


When recording two programmes:

If the following screen appears



- 1 Select the programme, then press [OK].
- 2 Select "Yes", then press [OK].

To pause recording

After displaying the recording programme, press [PAUSE .

- Press again to restart recording.
(A title is not split into separate titles.)



- Timer recording programme cannot be paused.

To record two programmes simultaneously

While recording, perform steps 1–4 on page 27.




- Channel or input can only be switched between the recording programmes.


Simultaneous rec and play

You can play the recording title from the beginning or the titles previously recorded to the HDD.

- 1 Press [DIRECT NAVIGATOR].

- If the DIRECT NAVIGATOR screen of music is displayed, press the red button, then select "VIDEO".



" " is displayed on the recording programme.

- 2 Select the title, then press [OK].

Timer recording



- This operation will only record to built-in HDD.
- This unit can record two programmes being broadcasted at the same time.

Preparation

If you want to change the recording mode:
Press [REC MODE] and select the recording mode, then press [OK].

1 Press [GUIDE].

TV Guide screen appears.

TV Guide										TUE 01.01.2013 8:05 AM		Category: All Digital Channels					
										8:00 AM - 9:45 AM		Shifted workman		Penguin		D	
TUE 01.01		8:00 AM		9:30 AM		9:30 AM		9:30 AM		10:00 AM		10:30 AM		11:00 AM			
1		○○○○		Shifted workman													
2		○○○○		Kitten		House dog						Will					
3		○○○○		Vacation		Hunting											
4		○○○○		Pampas grass				News		Top run							
5		○○○○		News		Corn Shopping				Area 91							
6		○○○○		Venus				Moon									
7		○○○○		Construction						Hippocampus							
8		○○○○		Great river		Mr. Otter		Dodge									
		OR				RETURN				Information				Page Up			
				<input type="checkbox"/>		Timer Rec.		<input type="checkbox"/>		24 hours		<input type="checkbox"/>		24 hours			
								<input type="checkbox"/>		Category							
																	

2 Select the programme, then press the red button.

The timer icon “⌚” (red) is displayed.

- If on-screen instructions are displayed, follow them.

To use TV Guide system

Refer to “Using TV Guide system”. (⇒ 24)

To edit the timer recording on the TV Guide screen

- 1 Select the programme to edit, then press the red button.
- 2 Select “Timer Rec Edit”, then press [OK].
- 3 Go to step 3 on page 30.

To cancel a timer recording on the TV Guide screen

- 1 Select the programme to cancel, then press the red button.
- 2 Select “Timer Rec Cancel”, then press [OK]. (“⌚” disappears)

Operation during Recording

Refer to “Operation during Recording”. (⇒ 28)



- Some broadcasters may not send programme information. When programme information is not displayed correctly, use manual timer recording. (⇒ 30)
- The receipt of the TV Guide data via Set Top Box is not possible.
- When timer recording from the external equipment, use manual timer recording. (⇒ 30)
- You can set the start and finish time to make the timer recording work successfully. (⇒ 77, 82, Timer Record Start Buffer, Timer Record Stop Buffer)

To select the programmes of a specific category

- 1 On the TV Guide screen:
Press the blue button.
- 2 Select the item, then press [OK].

To return to the previous TV Guide list

Select “All Digital Channels” in step 2.



- Category may not be assigned correctly depending on the programme information.

Timer recording

Manually programming timer recording

1 Press [PROG/CHECK].

2 Select "New Timer Programme", then press [OK].

3 Select the items and change the items. (⇒ right, Timer recording options)

4 Press [OK]. The timer programme is stored.

To confirm and edit the timer programme

Refer to "To confirm and edit a timer programme".
(⇒ 32)

Operation during Recording

Refer to "Operation during Recording". (⇒ 28)



- When recording from the external equipment, "Mode" (recording mode) is XP, SP, LP, EP or FR.

Timer recording options

Select the items and change the items.

e.g.,

Channel

- You can select Category/AV with the red button.

Day/Date

- You can select "Date" or "Weekly" by pressing the green button.

• Auto Renewal Recording

(Only daily/weekly timer recording)

The unit will record the new programme over the old one.

Press the yellow button.

"Renew : ON" is displayed.

Start/Stop

- Press and hold [▲, ▼] to alter in 15-minute increments.

Mode/Conv.

Refer to step 2 on page 27.

Subtitles

(Only when item other than "OFF" is selected in "Conv.")

Title Name

- Select "Title Name", then press [OK].
- Refer to "Entering text". (⇒ 95)

Timer recording from channel information

You can make timer recording of the current or next programme.

- 1 While watching a programme
Press [STATUS ].

e.g.,

1	NEWS	10:30 AM
0000	9:00 AM - 11:00 AM	All Digital Channels
◀ Now ▶	<input type="checkbox"/> Set timer	<input type="checkbox"/> Change category
Rating: G	Dolby D	  

- 2 Display the channel information of a programme to record.
• Switch the programme with [◀, ▶].
- 3 Press the yellow button.
- 4 Go to step 3 on page 30.

Remote recording from outside

You can make a timer recording from a smart phone or a PC, etc. away from home. (You must register to a service to use this function.)

For details, please check the following website.

<http://panasonic.jp/support/global/cs/>

(This site is in English only.)

- However, as of February 2013, the service has not yet been launched.


Preparation

- Network connection (⇒ 17, 20)
- Remote Recording Function Settings (⇒ 77, 88)



- This unit will be always connected to the internet, so we recommend that you subscribe to a flat-rate data plan with an always-on connection.
- Please note that a regular maintenance or unexpected trouble may interrupt the service, and that the service content may be changed or revoked and operation menu screens may be changed with or without a prior notice.

Notes on timer recording

- You can enter up to 32 programmes within a month in advance. (Each daily or weekly programme is counted as one programme.)
- When recording except in DR mode, the audio content will be selected according to the following settings:
 - Audio Type for Digital Broadcast (⇒ 77, 85)
 - Audio for HG / HX / HE / HL / HM Recording (⇒ 77, 85)
- Even if you switch the unit to standby mode during the timer recording, the recording is continued.
- When you programme successive timer recordings to start, about last 1 minute of earlier programme will not be recorded.
- Timer recording will not start while:
 - copying a title in high speed mode [with finalising or creating Top Menu (RW)]
 - copying a title in normal speed mode
 - converting a title in "File Conversion" (Only when "Now" is selected)
 - copying HD Video (AVCHD) from USB device or SD card
 - copying photos/music
 - formatting
 - finalising/creating Top Menu
- When "Pure Sound mode" is activated, timer recording does not start during playback of BD-Video, DVD-Video or music CD. (⇒ 81)

Timer recording

To confirm and edit a timer programme

1 Press [PROG/CHECK].

e.g.,

Channel Name	Schedule	Mode	Space
World news	TUE 08.01 11:00 AM - 11:45 AM	DR	OK
Football	TUE 08.01 10:00 AM - 11:50 AM	→HG	OK
Solar	TUE 08.01 11:50 AM - 1:00 AM	DR	☒ !
Dogs and cats	TUE 01.01 8:00 AM - 10:45 AM	DR	☒

New Timer Programme

Total 3/32 [DEL] Delete [i] Info Page Up [A] Page Down [V]

[OK] RETURN [Turn Off] [] [] [] []

2 Select the programme, then perform the operations.

To deactivate a timer programme

Press the red button.

- The timer icon “⊖” will change from red to grey.
- Press the red button again to activate timer recording standby. (The timer icon “⊖” will change to red.)

To delete a timer programme

Press [DEL].

To edit a timer programme

- 1 Press [OK].
- 2 Change the timer recording options.
 - Refer to “Timer recording options”. (⇒ 30)
- 3 Press [OK].

To show programme information

Press [STATUS i].

To exit the timer recording list

Press [EXIT ☒].

Screen icons

- ⊖ Red: Timer recording standby is activated.
Grey: Timer recording standby is deactivated.
- Currently recording programme
- ☐ A part or all of the programme will not be recorded since the programme is overlapping.
- 📀 The HDD is full.
- 🔒 Copy-protected programme
It was not recorded.
- ☒ The recording of the programme was not completed because of some reason.
- 🔄 Auto Renewal Recording (⇒ 30) is set.
- OK Displayed if the recording can fit in the remaining space
- > Daily or weekly timer programme is set.
- (Date)
- ! It may not be possible to record because:
 - there is not enough space left.
 - the number of possible titles has reached its maximum. (⇒ 110)
 - programmes are deactivated, etc.


Playing titles on the HDD



* "For recorded titles" only

- 1 Press **[DRIVE SELECT]** to select "HDD", then press **[DIRECT NAVIGATOR]**.
 - If the DIRECT NAVIGATOR screen of photo or music is displayed, press the red button, then select "VIDEO".

e.g.,




- 1 Tab (⇒ 34)

- 2 Programme type

- **[USB HDD]** When connecting registered USB HDD, "USB HDD" tab and registration number appears. Select "USB HDD" tab.


e.g.,



- 2 Select the title, then press **[OK]**. Playback starts.

Resume play function

If the following screen appears, select the point to start playback.



DIRECT NAVIGATOR (VIDEO) screen

Screen icons

- Currently recording programme
- 🔒 Protected title
- 📄 Title was not recorded due to recording protection
- ✕ Title cannot be played (When data is damaged etc.)
- 📁 Grouped titles
- 🚩 Title has not yet been played
- NTSC
PAL Title is recorded using a different encoding system from that of the unit.
Change the "TV System" (⇒ 77, 86).
- 📻 Radio programme
- 3D contents
 - This icon will not display even with 3D programmes when a broadcast programme is recorded.
- 1080 50p Recorded in 1080/50p contents
- 1080 60p Recorded in 1080/60p contents
- G Title is restricted by Child Lock (Parental Rating) (⇒ 80).
- 🔴! Recording did not complete as the timer recording has started.

Playing titles on the HDD

Tab

Titles will be categorised automatically.
You can quickly find the recorded titles by selecting the tab.

To select the tab

Press [◀, ▶].

To change the displayed programme type tab

- 1 Select the programme type, then press the green button.
- 2 Select the item, then press [OK].

To change the programme type of title

Refer to “Changing programme type of title”.
(⇒ 43)

Switching to the PHOTO or MUSIC screen

- 1 Press the red button.
- 2 Select “PHOTO” or “MUSIC”, then press [OK].

Showing Information

Select the title, then press [STATUS ⓘ].

Switching the appearance

- 1 Press [OPTION].
- 2 Select “Grouped Titles” or “All Titles”, then press [OK].


Grouped Titles:

Two or more titles recorded in the daily/weekly timer recording mode are bundled and displayed as one item.

All Titles:

Displays all titles.

Playing back grouped titles

- 1 On the Grouped Titles screen:
Select the item marked with .
- 2 **When playing all titles:**
Press [PLAY/× 1.3 ▶].

When playing the individual title:

Press [OK] and select the title, then press [OK].

Editing the grouped titles

- 1 Select the title or the group, then press the yellow button.
 - A check mark is displayed. Repeat this step.
 - Press the yellow button again to cancel.
 - If you perform "Remove", select the title in the group.
- 2 Press [OPTION].
- 3 Select the item, then press [OK].

Create Group:

Selected titles are bundled to form a group.
Select "Create", then press [OK].

Release Grouping:

All the titles in the group are released.
Select "Release", then press [OK].

Remove:

Selected titles are removed from the group.
Select "Remove", then press [OK].


Changing the group name

- 1 Select the group, then press [OPTION].
- 2 Select "Edit", then press [OK].
- 3 Select "Enter Title Name", then press [OK].
- 4 Refer to "Entering text". (⇒ 95)

Playback from Chapter View

Regarding chapters


You can divide a title into multiple chapters. Each section between the division points (Chapter Marks) becomes a chapter.



• Chapter Creation

This unit can create chapters automatically while recording broadcasting. (⇒ 82)

- 1 Select the title, then press [OPTION].
- 2 Select "Chapter View", then press [OK].
e.g., [HDD]











- 3 Select the chapter, then press [OK].

To edit the chapter in Chapter View

Refer to "Editing chapters". (⇒ 45)

Playing titles on the media

* "For data files" only

- 1 Insert the media.**
 Depending on the type of the media, play starts from the specified position, or the screen appears.
 - AVCHD: If the menu screen is not displayed
Press [PLAY/× 1.3 ▶].
- 2** When the DIRECT NAVIGATOR screen or menu screen etc., appears:
Select the item or title, then press [OK].
 - Repeat this step if necessary.
 Playback starts.

To play back the playlist created on other equipment

- 1 Press [FUNCTION MENU].
- 2 Select "Playlists" in "Others", then press [OK].
- 3 Select the playlist, then press [OK].




- **[BD-V]** You cannot play back while recording from external equipment. Also, playback stops when the timer recording starts from external equipment.
- Some files may not be played back, depending on the video resolution and frame rate condition.

Menu screen

Selecting screen for each operation is displayed when the media is inserted, and you can access the operation screen easily.

e.g., **[USB]**




- Display items differ depending on what is recorded in each media.

If the menu screen is not displayed, display it by performing the following operation.

- 1 While stopped
Press [OPTION].
- 2 Select "Drive Select", then press [OK].
- 3 Select the media, then press [OK].

Video list screen

e.g.,



Screen icons:



Folder




Titles



Move to the parent folder

DIRECT NAVIGATOR screen

e.g.,



Switching to the PHOTO screen

Press the red button.

The screen switches to "PHOTO".

Showing Information

Select the title, then press [STATUS].

Playback from Chapter View

- 1 Select the title, then press [OPTION].
- 2 Select "Chapter View", then press [OK].
- 3 Select the chapter, then press [OK].


• Regarding chapters

Refer to "Regarding chapters". (⇒ 35)

DIRECT NAVIGATOR (AVCHD) screen

SD

e.g.,



Showing Information

- 1 Select the title, then press [OPTION].
- 2 Select "Information", then press [OK].

About screen icons on the DIRECT NAVIGATOR

Refer to "Screen icons". (⇒ 33)

Notes for BD-Live discs

BD-V

BD-Live allows you to enjoy more functions such as subtitles, exclusive images and online games by connecting this unit to the Internet.

Preparation

- 1 Perform network connection and settings.
(⇒ 17, 20)
- 2 Insert a disc.

For the playback method, refer to the instructions for the disc.

Delete BD-Video data


If you no longer need BD-Live data recorded on the built-in HDD, you can delete data with the following operation.

- 1 Press [FUNCTION MENU].
- 2 Select "BD-Video Data Management" in "Others", then press [OK].
- 3 Select "Delete BD-Video data", then press [OK].
- 4 Select "Yes", then press [OK].
- 5 Select "Start", then press [OK].
- 6 Press [OK].



- The usable functions and the operating method may vary with each disc, please refer to the instructions on the disc.
- You can restrict Internet access when BD-Live functions are used (⇒ 77, 81, BD-Live).
- When "Pure Sound mode" is set to "On", this unit cannot use BD-Live functions. (⇒ 81)

Operation during play



- Depending on the media and the type of file, some operations may not be possible.
- Depending on the media, it may take time for the menu screen, pictures, sound, etc. to start.
- Discs continue to rotate while menus are displayed. Press [STOP ■] when you have finished playback to protect the unit's motor, your TV screen, etc.

General operations

Status messages

Press [STATUS ⓘ] twice.

e.g.,

8:05:50 AM	01.01.2013
■ Remain	HDD 45:53 DR
■ T1	0:05.14 DR

[0:30.00]

Stop

Press [STOP ■].

Resume play function

Press [PLAY/×1.3 ▶] to restart from the stopped position.



- The resume play function does not work depending on the media.
- Discs:** Only previous stopped position is memorized. The position may be cleared if the tray is opened or the unit is switched to standby mode.

Quick View

Press and hold [PLAY/×1.3 ▶].

- Press again to return to normal speed.



- Xvid, MKV, MP4 and MPEG2 ([USB HDD] [USB]):** Quick View is not effective.
- Quick View is not effective when playing back the DVD-RW disc.
- Quick View may not work when recording in XP or FR mode.

Search

Press [SLOW/SEARCH ◀◀] or [SLOW/SEARCH ▶▶].

- Press [PLAY/×1.3 ▶] to restart play.



- The speed increases up to 5 steps.
([+R] [+RW]): Up to 3 steps
- Xvid, MKV, MP4 and MPEG2 ([USB HDD] [USB]):** Audio is not heard during all levels search.

Pause

Press [PAUSE ■■].

- Press [PLAY/×1.3 ▶] to restart play.

Slow-motion

While paused, press [SLOW/SEARCH ◀◀] or [SLOW/SEARCH ▶▶].

- Press [PLAY/×1.3 ▶] to restart play.



- The speed increases up to 5 steps.
- Xvid, MKV, MP4 and MPEG2 ([USB HDD] [USB]):** Slow-motion is not effective.
- [BD-V], AVCHD ([DVD-R] [SD]):** Forward direction [SLOW/SEARCH ▶▶] only.

Frame-by-frame

While paused, press [◀] (◀▶) or [▶] (▶▶).

- Each press shows the next frame.
- Press and hold to change in succession forward or backward.
- Press [PLAY/× 1.3 ▶] to restart play.



- **Xvid, MKV, MP4 and MPEG2** (USB HDD USB): Frame-by-frame is not effective.
- **BD-V, AVCHD** (DVD-R SD): Forward direction [▶] (▶▶) only.

Manual Skip

Skip forward 1 minute:

Press [MANUAL SKIP +60s].

Skip backward 10 seconds:

Press [MANUAL SKIP -10s].



- **Xvid and MKV**: Manual Skip is not effective.

Skipping the specified time

- 1 Press [TIME SLIP].
- 2 Select the time with [▲, ▼].
 - Press and hold [▲, ▼] to change the time by 10-minute.
- 3 Press [OK].
 - Play skips the specified time.



- **BD-V, DVD-V, Xvid, MKV, AVCHD, MP4 and MPEG2** (USB HDD USB): [TIME SLIP] is not effective.

To display menu

BD-V DVD-V

- 1 Press [OPTION].
- 2 Select "Playback Menu", then press [OK].
- 3 Select "Top Menu", "Pop-up Menu" or "Menu", then press [OK].

Skipping the title or chapter

Press [SKIP ◀◀] or [SKIP ▶▶].



- **HDD USB HDD** (For recorded titles): It will not skip the title. But the title in the grouped titles will be skipped. (⇒ 34)

To create Chapter Marks

HDD USB HDD (For recorded titles) **BD-RE**

BD-R RAM

During the playback or pause

Press [CHAPTER].

To delete the Chapter Mark

HDD USB HDD (For recorded titles) **BD-RE**

BD-R RAM

- 1 While paused
 - Press [SKIP ◀◀] or [SKIP ▶▶] and skip to the location you want to delete.
- 2 Press [CHAPTER].
- 3 Select "Yes", then press [OK].

Changing audio

Press [AUDIO].

- It will switch depending on the contents recorded every time it is pressed.

Switching subtitles

HDD USB HDD (For recorded titles) **BD-RE**

BD-R:

- 1 Press [STTL ⚙️].
 - 2 Select "On" or "Off".
- If you want to switch the subtitle language, select it in the Disc menu (⇒ 74).

BD-V DVD-V, Xvid and MKV:

Display with "Subtitles" in the Disc menu (⇒ 74).

Aspect

You can switch the screen mode.

Refer to "Switching the aspect ratio of the screen". (⇒ 95)

Operation during play

3D video playback

Preparation

Connect 3D compatible TV to this unit. (⇒ 14)

- Perform the necessary preparations for the TV.

Play back following the instructions displayed on the screen.

Preparatory 3D settings

Perform the following settings as necessary.

3D BD-Video Playback

It is also possible to play back 3D discs in 2D (conventional video). (⇒ 77, 81)

3D Type

If 3D video cannot be played back in 3D, you may be able to play it in 3D by changing the setting. (⇒ 77, 85)

3D AVCHD Output

If 2D AVCHD video is recognised as 3D video and cannot be played back correctly, you may be able to play it by changing the setting. (⇒ 77, 85)

3D Playback Message

Hide the 3D viewing warning screen. (⇒ 77, 85)

Graphic Display Level

Adjust the 3D position for the playback menu or message screen etc. (⇒ 75)

3D settings during playback

Change this setting when the screen is not correctly displayed for 3D compatible programmes.

- 1 Press [OPTION].
- 2 Select "3D Settings", then press [OK].
- 3 Select the item, then press [OK].

Signal Format

Original

Keep original picture format.

Side by side

3D picture format comprising of left and right screens.

2D to 3D

Converts 2D pictures to 3D effect while playing.

3D Picture Mode

Normal

Normal 3D effects.

Soft

Soft 3D effects.

- This function cannot be enabled when "Signal Format" is set to "2D to 3D".

Manual Settings

Distance

Set the amount of depth perception.

Screen Type

Selects how the screen appears during 3D playback (flat or round).

Frame Width

Set the amount of feathering at the edge of screen.

Frame Colour

Set the colour of feathering at the edge of screen.



- Depending on the contents, displayed items are different.
- This unit only guarantees the playback of the Frame Sequential and the Side-by-Side (Half) programme types.
- Please refrain from viewing 3D images if you do not feel well or are experiencing visual fatigue.
In the event that you experience dizziness, nausea, or other discomfort while viewing 3D images, discontinue use and rest your eyes.
- Depending on the connected TV, the video being played back might switch to 2D video due to changes in resolution etc. Check the 3D setting on the TV.
- 3D video might not output the way it is set in "HDMI Video Format" (⇒ 86) and "24p Output" (⇒ 86).
- It may display as Side-by-Side when playback of the 3D video is started.

Deleting recorded titles

Once deleted, recorded content cannot be restored to its original state. Make certain before proceeding.




- If the disc is protected, release the protection. (⇒ 69, Disc Protection)



* "For recorded titles" only

- 1 On the DIRECT NAVIGATOR screen:
Select the title.



- 2 Press [DEL].

- 3 Select "Delete", then press [OK].

Deleting during play

- 1 Press [DEL] while playing.
- 2 Select "Delete", then press [OK].

Available disc space after deleting

- **HDD** **USB HDD** **BD-RE** **RAM**

The space deleted becomes available for recording.

- **BD-R** **DVD-R** **+R**


Available space does not increase even after the contents are deleted.

- **DVD-RW** **+RW**

Available recording space increases only when the last recorded title is deleted.

Multiple deleting

Select the title, then press the yellow button in step 1.



A check mark is displayed. Repeat this step.

- Press the yellow button again to cancel.

Editing recorded titles

Once deleted, divided or partially deleted, recorded content cannot be restored to its original state. Make certain before proceeding.




* "For recorded titles" only




- Depending on the media and the type of file, some operations may not be possible.
- PIN is required to edit the titles with **G** in some functions. (⇒ 33)

- On the DIRECT NAVIGATOR screen: Select the title.



- Press [OPTION].
- Select the item, then press [OK].
e.g.,



- "Edit" has several functions.

Multiple editing

Select the title, then press the yellow button in step 1.

A check mark is displayed. Repeat this step.

- Press the yellow button again to cancel.

Deleting

- Select "Delete Title", then press [OK].
- Select "Delete", then press [OK].

Entering title name

- Select "Enter Title Name" in "Edit", then press [OK].
- Refer to "Entering text". (⇒ 95)

Setting protection

HDD **USB HDD** **BD-RE** **BD-R** **RAM** **+R** **+RW**

Protection setting prevents the title from accidental deletion.

All	Not Viewed	Movies	Drama
Channel	Date	Title Name	
	04.10	Birds	
	04.10	World news	
	29.10	Football	
	29.10	Dogs and Cats	
	Start Time	9:00 AM	Rec time
	Prog.Type	Movies	

- Select "Set up Protection" or "Cancel Protection" in "Edit", then press [OK].
- Select "Yes", then press [OK].

appears when setting the protection.

Partial deleting

HDD USB HDD BD-RE BD-R RAM

- 1 Select "Partial Delete" in "Edit", then press [OK].
- 2 Press [OK] at the start point and end point to delete.
 - You can find the desired point by using play, search, etc. (⇒ 38)
- 3 Select "Continue", then press [OK].
 - Select "Next", then press [OK] to delete other sections. Up to 20 sections can be set. (⇒ go to step 2)
- 4 Select "Delete", then press [OK].
 - Chapter Mark is generated in the scene that was partially deleted.
- 5 Press [RETURN].

Dividing title

HDD USB HDD BD-RE BD-R RAM

- 1 Select "Divide Title" in "Edit", then press [OK].
- 2 Press [OK] at the point to divide the title.
 - You can find the desired point by using play, search, etc. (⇒ 38)
- 3 Select "Continue", then press [OK].
- 4 Select "Divide", then press [OK].

To confirm the division point

After performing step 2.

Select "Preview", then press [OK].

- The unit plays 10 seconds before and after the division point.

To change the division point

After performing step 2.

Restart play and select "Divide", then press [OK] at the division point.



- HDD USB HDD Divided titles will become a group of titles.

Changing thumbnail

HDD USB HDD RAM DVD-R DVD-RW +R +RW

- 1 Select "Change Thumbnail" in "Edit", then press [OK].
- 2 Press [OK] at the point to use as a thumbnail.
 - You can find the desired point by using play, search, etc. (⇒ 38)
- 3 Select "Finish", then press [OK].

To change the point

After performing step 2.

Restart play and select "Change", then press [OK] at the point to change.




- It is possible to change the image displayed on the Top Menu after finalising or creating Top Menu.

Changing programme type of title

HDD

Programme type information in the title can be edited.



- 1 Select "Change Prog.Type" in "Edit", then press [OK].
- 2 Select the item to change a programme type, then press [OK].
- 3 Select the programme type, then press [OK].
- 4 Select "Set", then press [OK].

Editing recorded titles


File Conversion

HDD **USB HDD**

File Conversion is a function to convert the recording mode of the title in DR mode and AVCHD contents. The size of the converted title will be small regularly. It will take about the same time as the recorded duration.

- 1 Select "File Conversion" in "Edit", then press [OK].

e.g.,



- 2 Set the conversion options, then press [OK].

Recording Mode (⇒ 8):

- **USB HDD** You cannot select XP, SP, LP and EP mode.

Subtitles:

- **Automatic**

Subtitles will be recorded if they are included in the title, and will not be recorded if they are not included.

- **Off**

Subtitle will not be recorded.

Timing:

- **Now**

Conversion begins immediately after step 4.

- Timer recording will not be performed during conversion.

- **During standby**

Conversion will be performed after the unit is switched to standby mode.

- 3 Select the item, then press [OK].

Convert & Delete:

The original title will be deleted to save HDD capacity after conversion.

Convert Only:

The original title remains after conversion.

- 4 **"Now" conversion:**

Select "Start", then press [OK].

"During standby" conversion:

Press [OK].

- Conversion will be performed after the unit is switched to standby mode.

"COPY" or "CONV" on the unit's display remains lighted during conversion.

To cancel a “Now” conversion

Press and hold [RETURN ⊕] for more than 3 seconds.

To confirm whether the conversion is completed

Press [DIRECT NAVIGATOR].

e.g.,

Channel	Date	Title Name	Titles
○○○○	04.10	Birds	1
○○○○	04.10	World news	1
○○○○	29.10	Football	1
○○○○	29.10	Dogs and Cats	1
Start Time 9:00 AM		Rec: 1.00(DR→HL)	①
Prog Type: Movies			

When “○○ → ○○ (Recording mode for conversion)” is displayed, the conversion has not finished.

To cancel a “During standby” conversion

After performing steps 1–3 (⇒ 42)

- 1 Select “File Conversion” in “Edit”, then press [OK].
- 2 Select “Yes”, then press [OK].



- To use “File Conversion”, the HDD needs enough storage capacity.
- The size of converted title might increase depending on the title.
- File Conversion is stopped when this unit is turned on during performing “During standby” conversion. Conversion will start from the beginning again once the unit is switched to standby mode.
- When converted, the audio content will be selected according to the following settings:
 - Audio Type for Digital Broadcast (⇒ 77, 85)
 - Audio for HG / HX / HE / HL / HM Recording (⇒ 77, 85)
- When converted, 3D information may not be retained.
- In titles with the Auto Renewal Recording function (⇒ 30) set, a programme may be unintentionally converted while in “During standby”.

Editing chapters

HDD **USB HDD** **BD-RE** **BD-R** **RAM**

- 1 Select “Chapter View”, then press [OK].
- 2 Perform the editing operations.

Edit Chapter Mark:

Select the point where you want to start a new chapter while viewing the title.

- 1 Press the green button.
- 2 Press [OK] at the point you want to divide.
 - Repeat this step.
- 3 Press [RETURN ⊕] to go to Chapter View screen.

To delete the chapter:

- 1 Select the chapter, then press [DEL].

Multiple editing

Select the chapter, then press the yellow button.

A check mark is displayed. Repeat this step.

- Press the yellow button again to cancel.
- 2 Select “Delete”, then press [OK].

To combine chapters (Delete chapter mark):

- 1 Select the chapter, then press [OPTION].
- 2 Select “Combine Chapters”, then press [OK].
- 3 Select “Combine”, then press [OK].
The selected chapter is combined to the next chapter.


Playback from Chapter View

Refer to “Playback from Chapter View”. (⇒ 35)



- The maximum number of chapters:
(Depends on the state of recording.)
HDD **USB HDD**: Approx. 1000 per title
BD-RE **BD-R** **RAM**: Approx. 1000 per disc
- **HDD** **USB HDD** When the title has the maximum number of chapters, you cannot perform the Resume play function (⇒ 33) or the “Changing thumbnail” (⇒ 43) with the title.

Copying titles



*1 “For recorded titles” only

*2 The title in the source media will be deleted.

*3 The recording mode cannot be changed.

1 Insert or connect the media.

2 Press [DRIVE SELECT] to select “HDD”, then press [DIRECT NAVIGATOR].

- If the DIRECT NAVIGATOR screen of photo or music is displayed, press the red button, then select “VIDEO”.

3 Select the title, then press the yellow button.

A check mark is displayed. Repeat this step.

Channel	Date	Title Name
	04:10	Birds
	04:10	World news
	29:10	Foot ball
	29:10	Dogs and Cats
	9:00 AM	Rac time
	Movies	

- Press the yellow button again to cancel.


4 Press the blue button.

5 Set the copy direction, then press [OK].

6 Select “Yes”, then press [OK].

- If you select “No”, you can change the selection. (⇒ 47)

7 Set other settings, then press [OK]. e.g.,



(⇒ 47, Setting the copying options)

8 Select “Yes”, then press [OK].

To register the external HDD (USB HDD)

Refer to “Registering the USB HDD”. (⇒ 72)

To copy HD Video (AVCHD) to the DVD-R in High Definition

Refer to “Copying HD Video (AVCHD) to the DVD-R in High Definition”. (⇒ 53)

Release the disc protection

Refer to “Disc Protection”. (⇒ 69)




- Simultaneous operation is not possible while copying with finalising or creating Top Menu. However, the titles on the HDD can be played back while high speed copying without finalising or creating Top Menu.

To change the selection

- 1 Select "No", then press [OK] in step 6 (⇒ 46).

e.g., **HDD** → **BD-RE**

The order of copying



- 2 To change the selected titles:

Select the title, then press the yellow button.

Repeat this step to select titles.

To change the picture quality:

HDD → **BD-RE** **BD-R** **RAM** **DVD-R** **DVD-RW**
+R **+RW**

- 1 Select the title, then press [OPTION].
- 2 Select "Conversion Select", then press [OK].
- 3 Select the picture quality, then press [OK].
Repeat steps if necessary.
- 3 Press the blue button.
- 4 Go to step 6 (⇒ 46).

Screen icons



Titles that will be copied to the disc
in normal speed



Titles that cannot be copied

About screen icons on the DIRECT NAVIGATOR

Refer to "Screen icons". (⇒ 33)

Setting the copying options

- 1 Select the item in step 7 (⇒ 46).
- 2 Press [◀, ▶] to change the settings.

• Automatic Standby after Copy

On:

This unit is turned to standby mode when it is not operated for approximately 5 minutes after completing copy.

• Subtitles

Automatic:

Subtitles will be recorded if they are included in the title.

• Finalise

On:

DVD-R **DVD-RW** **+R** The discs become play-only and you can also play them on other DVD equipment.

• Create Top Menu

On:

+RW You can play the disc on other DVD equipment.



- You can perform "Finalise" or "Create Top Menu" later. (⇒ 70)

Copying titles


Copying from media other than HDD with DIRECT NAVIGATOR

BD-RE BD-R RAM +RW → HDD

- 1** Insert a disc.
The menu screen appears. (⇒ 36)
- 2** Select "Play Video", then press [OK].
- 3** Select the title, then press the yellow button.
A check mark is displayed. Repeat this step.

Channel	Date	Title Name
○○○○	04.10	Birds
○○○○	04.10	World news
○○○○	28.10	Foot ball
○○○○	29.10	Dogs and Cats
Start Time	9:00 AM	Rec time 0:30 [C]

- 4** Press the blue button.



- To change the detailed settings for copy, refer to "Copying titles with copying list". (⇒ right)

- 5** Select "Start Copying", then press [OK].
- 6** Select "Yes", then press [OK].

Copying titles with copying list

HDD ↔ USB HDD ※1, 2, 3

HDD → BD-RE BD-R RAM DVD-R
DVD-RW +R +RW

USB HDD ※1 → BD-RE BD-R

BD-RE BD-R
RAM +RW → HDD

※1 "For recorded titles" only

※2 The title in the source media will be deleted.


※3 The recording mode cannot be changed.

- 1** HDD ↔ USB HDD:
 - 1 Press [FUNCTION MENU].
 - 2 Select "Copy Video" in "Copy", then press [OK].

Except "HDD ↔ USB HDD":

- 1 Insert a disc.
The menu screen appears. (⇒ 36)
- 2 Select "Copy", then press [OK].

- 2** Set the copy direction.
 - 1 Select "Copy Direction", then press [▶] (right).
 - 2 Set "Source" and "Destination".
 - 3 Press [◀].




- 3** Set the recording mode (⇒ 8).
 - 1 Select "Copy Mode", then press [▶] (right).
 - 2 Set "Recording Mode".
 - 3 Press [◀].

4 Register titles for copy.

- 1 Select "Create List", then press **[▶]** (right).
- 2 Select "New item", then press **[OK]**.
- 3 Select the title, then press the yellow button.

Repeat this step to select titles.

e.g., **HDD**



- To change the appearance of the list or show information of the title


- 1 Press [OPTION].
- 2 Select the item, then press [OK].



- The titles will be copied in the order of the copying list. If you want to specify the order, edit the copying list after the titles are selected.
(⇒ 50. Editing the copying list)

- 4 Press [OK].
- 5 Press [◀].

Data size of each registered title




Data size recorded to the copy destination

5 Make other settings.

- 1 Select "Other Settings", then press **[▶]** (right).

e.g.,



- This screen does not appear depending on the copying mode. (⇒ go to step 6)

- 2 Select the copying option, then press [OK].
(⇒ 47, Setting the copying options)

- 3 Press [◀].

6 Select “Start Copying”, then press [OK].

- 7** Select “Yes”, then press [OK].

To cancel all registered copying settings and lists

After performing step 1

- 1 Select "Cancel All", then press [OK].
- 2 Select "Yes", then press [OK].




- Titles in the grouped titles and other titles cannot be registered simultaneously.

Copying titles

Editing the copying list

- 1 Select the title after step 4-4 (⇒ 49).



- 2 Press [OPTION].
- 3 Select the item, then press [OK].

Delete All:

All titles that you registered to copy are deleted.

Select "Yes", then press [OK].

Add:

Add new items to the copying list.

- 1 Select the titles with the yellow button.
- 2 Press [OK].

Delete:

Selected titles are deleted.

- Select the title, then press the yellow button before step 2.

Repeat this step to select titles.

Select "Yes", then press [OK].

Move:

Change the order of items on the copying list.

- Select the title to move before step 2.

Select the destination, then press [OK].



- When copying at normal speed, the total data size will change according to the recording mode.
- The total data size shown may be larger than the sum of the data sizes for each registered item.

Screen icons



Titles that cannot be copied in high speed mode



Titles that cannot be copied



Title contains photos
• Photos cannot be copied.

[N] (NTSC)

Title recorded using a different encoding system from that of the unit.

[P] (PAL)

• Titles displaying these marks cannot be selected.

About other screen icons





Refer to "Screen icons". (⇒ 33)

Notes for copying

Notes for high speed copy

High Speed Copying is the process of copying a title to disc in high speed while maintaining the original record mode and recording length. If any conversion is required during the copy process, the copying will be done at normal speed.

- The following recording mode and media combinations support high speed copying.

Original title's recording mode	Media
DR	
HG	
HX	
HE	
HL	
HM	
XP	
SP	
LP	
EP	
FR	
	
	* DVD-RAM only

- Converting the recording mode will result in a normal speed copy.
- High speed copy is possible only when there is enough recording capacity on the destination media.



- It is impossible to copy at high speed in the following cases:

- **HDD** → **BD-RE** **BD-R** :
 - Copying radio programmes
- **HDD** → **DVD-R** **DVD-RW** **+R** **+RW** :
 - Copy including a title that was recorded to HDD with "Rec for High Speed Copy" set to "Off" (⇒ 82)
 - Titles that contain many deleted segments
 - Titles (SD Video) that have been copied to the HDD from an SD card or a Panasonic video camera, etc. (⇒ 64)
- **HDD** → **+R** **+RW** :
 - Titles recorded in "EP" mode and "FR (recordings 5 hours or longer)" mode
 - Titles recorded in 16:9 aspect
- **HDD** → **DVD-R** **DVD-RW** :
 - Titles recorded via AV input in 16:9 aspect using "EP" mode or "FR (recordings 5 hours or longer)" mode

Notes for normal speed copy

- **DVD-R** **DVD-RW** **+R** **+RW** You cannot copy to the disc in the following cases.
 - When there is not enough free space on the HDD.
 - When the number of titles recorded to the HDD and the number of titles to be copied to the disc is greater than 999 in total.
- **DVD-R** **DVD-RW** **+R** **+RW** If copy is cancelled during the step while temporarily copying to the HDD, then nothing will be copied.
- **BD-R** **DVD-R** **DVD-RW** **+R** **+RW** Even if the title was not copied to the disc, the amount of remaining writable disc space becomes less.
- When copying title recorded in 1080/50p or 1080/60p, it cannot copy in progressive.

Notes for copying to the USB HDD

You cannot copy the following titles.

- Protected titles
- HD Video (AVCHD)
- SD Video (MPEG2)

Notes for copying to the DVD-RAM

When copying to DVD-RAM using "8 hours" mode, play may not be possible on DVD players that are compatible with DVD-RAM. Use "6 hours" mode if playback may be on other equipment. (⇒ 82, Recording time in EP mode)

Notes for copying 3D programmes

- It may not display correctly in 3D when a copied 3D programme is played back. In such a case, change the "Signal Format" during the playback of the title. (⇒ 40)
- 3D information may not be copied.
- If you want to copy 3D AVCHD video to the disc in 3D, use BD-R or BD-RE and copying speed must be high speed.

Copying titles

About maintaining the chapter mark

- The position of the chapter might shift slightly.
- Maximum number of chapters on the disc is limited.
 - **BD-RE** **BD-R** **RAM** **DVD-R** **DVD-RW** :
Approx. 1000
 - **+R** **+RW** : Approx. 254
(Depends on the state of recording.)

Copying a finalised disc

DVD-V → **HDD**

While playing a disc, the content being played is copied to the HDD according to the set time.


- 1 Press [FUNCTION MENU].
- 2 Select "Copy Video" in "Copy", then press [OK].
- 3 Set "Copy Mode".
 - 1 Select "Copy Mode", then press [▶] (right).
 - 2 Press [OK], then select the recording mode (XP/SP/LP/EP).
 - 3 Press [◀].

- 4 Set "Copy Time".
 - 1 Select "Copy Time", then press [▶] (right).
 - 2 Select "Time Setting", then press [OK].
 - 3 Select "On" or "Off".

On:
Set the copying time.

 - Set a few minutes longer than the source title, in order to include the operation time before play begins.

Off:
Copying all the content on the disc.
- 4 Press [◀].
- 5 Select "Start Copying", then press [OK].
- 6 Select "Yes", then press [OK].
 - When the Top Menu is displayed:
Select the title you want to start copying, then press [OK].



After the last title on the disc has finished playing the Top Menu is recorded until the set time is reached.

To stop copying

Press [STOP ■].

- You can also press and hold [RETURN ☺] for 3 seconds.
- If stopped partway, copying will be up to that point.



- Operations and on-screen displays during copy are also recorded.
- Almost all DVD-Video on sale have been treated to prevent illegal copying, and cannot be copied.
- If play does not begin automatically press [PLAY/×1.3 ▶] to start.

Copying Title Playing

HDD → **BD-RE** **BD-R** **RAM** **DVD-R** **DVD-RW** **+R**
+RW

- 1** Play back the title to copy.
 - Multiple audio and subtitle displayed during playback will be copied.
 - Select the multiple audio with "Audio Selection" in the Disc menu (⇒ 74)
 - Select the subtitles with "Subtitles" in the Disc menu. (⇒ 74)
- 2** Press [OPTION].
- 3** Select "Copy Title Playing", then press [OK].
- 4** Select "Start", then press [OK].
Copying will start from the beginning of the title regardless of the playing position.

To stop copying

Press and hold [RETURN ⊞] for 3 seconds.



- You can record to or play HDD while high speed copying. Press [OK] to exit the screen display.
- Press [STATUS ⓘ] to confirm the current progress.

• Speed and recording mode when copying

The high speed copy is performed if available.
Refer to "Notes for copying". (⇒ 51)



- When copying the titles in DR, HG, HX, HE, HL or HM modes and the copy destination does not have enough space, one from HG, HX, HE, HL or HM modes will be selected to match the available space.
- **RAM** **DVD-R** **DVD-RW** **+R** **+RW** When copying the titles in DR, HG, HX, HE, HL or HM modes, copy will be performed at normal speed in FR mode.
- When copying the titles in XP, SP, LP, EP or FR modes and the copy destination does not have enough space, copy will be performed at normal speed in FR mode.

Copying HD Video (AVCHD) to the DVD-R in High Definition

You can copy HD Video (AVCHD) recorded on HDD to a DVD-R in High Definition quality.

HDD → **DVD-R**

- 1** Insert an unformatted DVD-R or DVD-R DL.
The menu screen appears. (⇒ 36)
- 2** Select "Copy Video (AVCHD) to Disc", then press [OK].
- 3** Go to step 4 on page 49, "Copying titles with copying list".


To copy HD Video (AVCHD) from other equipment

Refer to "Copying HD Video (AVCHD)". (⇒ 63)



- This function can only be used for unformatted disc.
- When a disc is named, formatting will be automatically performed. Therefore, do not name a disc before this operation. (⇒ 69, Disc Name)
- Discs will be automatically finalised after copy.
- You can choose the thumbnail image of the Top Menu before using this function. (⇒ 43, Changing thumbnail)
- The following HD Videos (AVCHD) cannot be copied to the disc in high definition.
 - Exceeding 18 Mbps
 - 1080/50p or 1080/60p
 - Without the AVCHD information (video recorded with certain non-Panasonic equipment, video copied to the HDD after copying it to BD-R or BD-RE once, etc.)
- 3D video will become 2D.

Playing photos



※1 “For data files” only (JPEG, MPO)

※2 **BD-RE** only

※3 **RAM** **DVD-R** only

- In order to play back 3D photo (MPO), this unit should be connected to a Full HD 3D compatible TV.

1 **HDD**

- 1 Press **[FUNCTION MENU]**.
- 2 Select “Photo” in “Playback Contents”, then press **[OK]**.


USB HDD **BD-RE** **RAM** **DVD-R** **CD** **SD**

USB

- 1 Insert or connect the media.
The menu screen appears. (⇒ 36)
- 2 Select “View Photos”, then press **[OK]**.

2 Select the event, then press **[OK]**.

e.g., **HDD**



• To select the tab

Press **[◀, ▶]**.

• Start Slideshow

Refer to “Slideshow settings”. (⇒ 55)

• Switching to the Calendar screen (**HDD**)

Press **[PAUSE ■■]**.

3 Select the photo, then press **[OK]**.

- Press **[◀, ▶]** to display the previous or next photo.

To exit the Calendar screen

Press **[PAUSE ■■]**.




- When there are many files and/or folders, some files may not be displayed or not be playable. (⇒ 110)

DIRECT NAVIGATOR (PHOTO) screen

e.g., **HDD**

Album (⇒ below)



Event

It is displayed for each recording date.

- It is displayed for each folder for media other than HDD.

Screen icons

Album
Placing photos in albums of your choice makes it easier to find them. (⇒ 56)

3D (Tab)
3D photos (MPO) are automatically sorted. Select from this tab to play back in 3D. (It will play back in 2D when selected from other tabs.)

Photo protected

New photo which is stored and not viewed

Switching to the VIDEO or MUSIC screens

HDD:

- 1 On the DIRECT NAVIGATOR screen:
Press the red button.
- 2 Select "VIDEO" or "MUSIC", then press [OK].

BD-RE RAM:

On the DIRECT NAVIGATOR screen:
Press the red button.

Photo play option

- 1 While displaying a photo:
Press [OPTION].
- 2 Select the item, then press [OK].

Aspect

You can switch the screen mode. (⇒ 95)

Graphic Display Level

You can change the 3D position of the screen display, etc., during the 3D photo playback.


Photo Menu

• Start Slideshow

You can start a slideshow.

• Rotate RIGHT/Rotate LEFT

e.g.,




- The information of the rotated photos will not be stored depending on the media.
- This function is not available during the 3D photo playback.

• Information

Information (shooting date etc.) is shown.

Slideshow settings

- 1 On the DIRECT NAVIGATOR screen:
Press the green button.



- 2 Select the item, then press [OK].

Start Slideshow

You can start a slideshow.

Interval

You can set up the time until the next photo is to display.

Transition Effect*

Effect for the next photo to display can be set.

Repeat Play

You can set up to play back repeatedly.

Music Selection*

You can select background music on (either from HDD or USB) or off.

Background Music*

You can select background music from HDD (My Favourites or Playlists) or USB (Folder).

Random BGM*

You can play back the BGM (Background Music) in random order.

* This function is not available during the 3D photo playback.

To pause the Slideshow

Press [PAUSE ■■].

- Press [PAUSE ■■] again to restart.

To stop the Slideshow

Press [RETURN ☺].

Editing photos




*1 **BD-RE** only

*2 **RAM** only

1 On the DIRECT NAVIGATOR screen:

e.g., **HDD**



To edit the event:

Select the event.

To edit the photo:

1 Select the event, then press [OK].

2 Select the photo to edit.

• To select multiple events or photos

Press the yellow button when selecting the event or photo.

A check mark is displayed. Repeat this step.

- Press the yellow button again to cancel.

2 Press [OPTION].

- Selectable items will change depending on the media and the type of file.

3 Select the item, then press [OK].

Edit

• Add to Album

HDD

- 1 Select the destination album, then press [OK].
- 2 Press [OK].

• Combine Events

HDD

Select "Yes", then press [OK].

• Remove from Album

HDD

Select "Yes", then press [OK].

• Enter Album Name

HDD

Refer to "Entering text". (⇒ 95)

• Enter Event Name

Refer to "Entering text". (⇒ 95)

Delete Photos

Select "Yes", then press [OK].

Set up Protection

BD-RE **RAM** **SD**

Select "Yes", then press [OK].

appears when the protection is set.

- Even if the protection is set, the photo may be deleted by another unit.

Cancel Protection

BD-RE **RAM** **SD**

Select "Yes", then press [OK].

Copying photos



※1 “For data files” only (JPEG, MPO)

※2 **BD-RE** only

※3 **RAM** **DVD-R** only

Selecting and copying the photos



- On the DIRECT NAVIGATOR screen:
To copy the event:
Select the event, then press the blue button.

To copy the photo:

- Select the event, then press [OK].
- Select the photos to copy, then press the blue button.

• To select multiple events or photos


Press the yellow button when selecting the event or photo.

A check mark is displayed. Repeat this step.

- Press the yellow button again to cancel.

- Select the copying destination, then press [OK].

- When copying to HDD:
Select “Yes” or “No”, then press [OK].
• If you select “Yes”:
Select the album, then press [OK].
e.g., **SD**



- You can categorise and manage the events and photos on the HDD by copying to the album. (⇒ 54)

- Select “Yes”, then press [OK].
Copying starts.

To stop copying

Press and hold [RETURN Ⓢ] for 3 seconds.




- The name of the copied photos will be changed.
- If the number of files/folders to be copied exceeds the maximum (⇒ 110), copying will stop partway through.

Copying automatically



Newly added photos will automatically be copied to the HDD.

- Insert the media.
The menu screen appears. (⇒ 36)
- Select “Copy New Photos”, then press [OK].
e.g., **SD**



- Select “Yes”, then press [OK].
Copying starts.
- Once the copy is completed, select “Yes” or “No”, then press [OK].


To stop copying

Press and hold [RETURN Ⓢ] for 3 seconds.




- Photos without shooting date will be categorised using the creation date.
- If the space on the destination drive runs out or the number of files/folders to be copied exceeds the maximum (⇒ 110), copying will stop partway through.
- The name of the copied photos will be changed.


Playing music




#1



#2





#1 "For data files" only (MP3)

#2 **DVD-R** only

Music CD:

Insert the disc.

Playback will automatically start.

MP3:

- 1 Insert or connect the media.**
The menu screen appears. (⇒ 36)
 - **DVD-R** **CD** Playback will automatically start if only MP3 is recorded.
- 2 Select "Play / Copy Music (MP3)" or "Play Music (MP3)", then press [OK].**
Playback will start.
 - Using the tree screen to find a folder
 - 1 Press [OPTION].
 - 2 Select "Select Folder", then press [OK].
 - 3 Select the folder, then press [OK].

To play other music (track)

Select the item, then press [OK].

e.g., **CD** (MP3)

DIRECT NAVIGATOR		Track List
CD (MP3)		○○○○
No.	Track Name	
0001	○○○○	
0002	○○○○	
0003	○○○○	
0004	○○○○	
0005	○○○○	



- The track/artist name will be displayed if the information is contained in ID3 tag of the MP3 file.
- If there is a large amount of photo data etc. within a MP3 file, play may not be possible.

Copying music (MP3) to HDD

USB HDD **DVD-R** **CD** **USB** → **HDD**

After performing steps 1–2 (⇒ left)

- 1** Press the blue button.
- 2** Select "Copy", then press [OK].

To stop copying

Press and hold [RETURN ⊞] for 3 seconds.




- While copying, no other operations can be performed. Timer recordings will not proceed.
- All tracks in the folder will be copied.
- Tracks recorded to HDD in one operation will be regarded as one album.

Playing music recorded on HDD

HDD

- 1 Press [FUNCTION MENU].
- 2 Select "Music" in "Playback Contents", then press [OK].



- 3 Select the item, then press [OK].



Artists

- 1 Press [◀, ▶] to select the initial of the artist.
- 2 Select the name of the artist, then press [OK].
- 3 Select the album, then press [OK].
- 4 Select the track, then press [OK].



Albums

- 1 Press [◀, ▶] to select the initial of the album.
- 2 Select the album, then press [OK].
- 3 Select the track, then press [OK].



My Favourites

Tracks registered in "My Favourites".

Select the track, then press [OK].

- Registering a track to the "My Favourites".
(Up to 99 tracks)

While the track list screen is displayed:
Select the track, then press the green button.



Playlists

- 1 Select the playlist, then press [OK].
- 2 Select the track, then press [OK].



Frequently Played

Tracks most often played recently (up to 30 tracks).

Select the track, then press [OK].



Random Play

Random playback of all tracks.

Playback starts.

Switching to the VIDEO or PHOTO screens

- 1 On the DIRECT NAVIGATOR (Music Menu) screen:
Press the red button.
- 2 Select "VIDEO" or "PHOTO", then press [OK].

Showing Track Information

On the track list screen:

- 1 Select the track, then press [OPTION].
- 2 Select "Information", then press [OK].

Playing music

Operations during music play

HDD **USB HDD** **DVD-R** **CD** **USB**

Stop

Press [STOP ■].

Pause

Press [PAUSE ■■].

- Press [PLAY/× 1.3 ▶] to restart play.

Search

Press [SLOW/SEARCH ◀◀] or [SLOW/SEARCH ▶▶].

- Press [PLAY/× 1.3 ▶] to restart play.

Skip

Press [SKIP ◀◀] or [SKIP ▶▶].

Repeat Play/Random

Refer to “Repeat Play” or “Random” in Play menu (⇒ 75).

Sound Effects

Refer to “Sound Effects” in Sound menu (⇒ 76).


Displaying photos (Slideshow)

Photos stored on the “Album” of the HDD can be played back as slideshow during playback of the music.

While playing the music

Press the red button.

- To change the photos to display
 - 1 While slideshow playing
Press [OPTION].
 - 2 Select “Select Photo Album”, then press [OK].
 - 3 Select the album, then press [OK].
e.g.,



To end the slideshow

Press [RETURN ☺].

How to create the photo album

Refer to “Add to Album”. (⇒ 56)


To play music continuously even if the Power off link works

Refer to “Playing music continuously even after turning off power to the TV”. (⇒ 73)


Editing music/playlist



- 1 On the DIRECT NAVIGATOR screen:
Press [OPTION].
e.g.,



- 2 Select the item, then press [OK].
e.g., while selecting an Album



- Editing operations will change depending on the screen.

Delete All Tracks

- 1 If the confirmation screen appears:
Select "Yes", then press [OK].
- 2 Select "Delete", then press [OK].

Delete Album

Select "Delete", then press [OK].

Delete

Select "Delete", then press [OK].

Edit Album Name/Edit Track Name/Edit Artist Name/Edit Playlist Name

Refer to "Entering text" on page 95.

Remove All Tracks

- Select "Remove", then press [OK].
- Tracks themselves are not deleted from the HDD.

Clear My Favourites/Clear Frequently Played

- Select "Clear", then press [OK].
- Tracks themselves are not deleted from the HDD.

Remove

- Select "Remove", then press [OK].
- Tracks themselves are not deleted from the HDD.

Add to Playlist

You can register your favourite albums and tracks into 10 preset playlists.

Select the playlist, then press [OK].

- New playlist cannot be added.
- Up to 999 tracks can be registered to each playlist.

Recording from external equipment



Preparation


Connect the Set Top Box or video equipment
(⇒ 15)

Manual Recording

HDD

Recording mode: XP, SP, LP, EP

- 1** Press [INPUT SELECT] and select "AV", then press [OK].
- 2** Press [REC MODE] to select the recording mode.
- 3** Select the channel on the Set Top Box or start play on the video equipment.
- 4** Press [REC ●].
Recording starts.
- 5** Set the time to record. (⇒ 27)



To stop recording

Press [STOP ■].



- Following contents or media cannot be played back while recording from external equipment.
 - BD-Video
 - Xvid, MKV and AVCHD file
 - photo
 - SD card
 - USB HDD (For data files) and USB memory


Flexible Recording via AV input



* This function is not available with DVD-R DL and +R DL.

Recording mode: FR

- 1** Press [DRIVE SELECT] to select the recording drive.
- 2** Press [INPUT SELECT] and select "AV", then press [OK].
- 3** Press [FUNCTION MENU].
- 4** Select "Flexible Recording via AV input" in "Others", then press [OK].



- 5** Set the recording time.
- 6** Start play on the other equipment.
- 7** Select "Start", then press [OK].

To stop recording partway

Press [STOP ■].

To show the remaining time

Press [STATUS ⓘ].




- Simultaneous operation is not possible while Flexible Recording via AV input to the disc is working.

Copying the HD Video or the SD Video



* "For data files" only

e.g., Connecting to the Panasonic video camera



USB connection cable
(optional)



- If you connect a Panasonic product with a USB connection cable, setup screen may be displayed on the connected equipment. For details, refer to the instructions for the connected equipment.

Copying HD Video (AVCHD)

BD-RE BD-R RAM → HDD
DVD-R DVD-RW +R +RW

USB HDD SD USB, → HDD
video camera, etc. BD-RE BD-R

- The original file must be in the AVCHD standard.

- 1 Connect the video camera or insert the media.
 - Make the video camera ready for data transfer.

The menu screen appears. (⇒ 36)

- 2 Select "Copy Video (AVCHD)", then press [OK].

- 3 When copying from an SD card or video equipment:
Select "Copy to HDD" or "Copy to Blu-ray Disc", then press [OK].

- 4 Select the title, then press the yellow button. A check mark is displayed. Repeat this step.

e.g., **SD**

Copy Video (AVCHD)		Destination Capacity	
<input type="checkbox"/> SD	⇒ <input checked="" type="checkbox"/> HDD		Size
		No.	Channel
Time 9:00 AM		<input checked="" type="checkbox"/> 00	AVCHD
Rec time 0:30		<input type="checkbox"/> 02	AVCHD
Size 200 MB		<input type="checkbox"/> 003	AVCHD
		<input type="checkbox"/> 004	AVCHD
		—	—

- Press the yellow button again to cancel.
(All the recordings on the same date become a title.)

- 5 Press [OK].

- 6 Select "Start", then press [OK].
It will automatically format the unformatted disc, such as a new disc.
 - It may take time for the copying to start.

To stop copying

Press and hold [RETURN ☺] for 3 seconds.

To copy to the DVD-R in High Definition

Refer to "Copying HD Video (AVCHD) to the DVD-R in High Definition". (⇒ 53)



- An AVCHD title with 100 or more scenes will be divided into titles every 99th scene and copied.

Screen icons

- N (NTSC)** Title recorded using a different encoding system from that of the unit.
- P (PAL)**
 - Titles displaying these marks cannot be selected.

Copying the HD Video or the SD Video

Copying SD Video (MPEG2)

USB HDD **SD** **USB**,
video camera, etc.



HDD **RAM**

-
- The original file must be in the SD-Video standard.

1 Connect the video camera or insert the media.

- Make the video camera ready for data transfer.

The menu screen appears. (⇒ 36)

2 Select “Copy Video (MPEG2)”, then press [OK].

- To change the copy destination and the titles to copy (⇒ 48, Copying titles with copying list)

3 Select “Start Copying”, then press [OK].

4 Select “Yes”, then press [OK] to start copying.

To stop copying

Press and hold [RETURN ⊕] for 3 seconds.

Smart Home Networking (DLNA)

Smart Home Networking (DLNA) allows you to watch the contents and broadcasts on Server equipment connected on the same network from Client equipment.

This unit can be used both as Server and Client. Additionally, if used as Client, this unit can also be used as Media Renderer, which can be controlled by a Smartphone, etc.

Preparation

- Network connection (⇒ 17, 20)
- Perform Home Network settings of the DLNA compatible equipment.

For more details, refer to the following website and the operating instructions for each item of equipment.

<http://panasonic.jp/support/global/cs/>

(This site is in English only.)




- Some video or broadcasts cannot be enjoyed depending on the DLNA (Client) compatible equipment, the condition of this unit, or the file type.
- Ensure that the router for your home network has adequate security system to prevent unauthorized access.

Using this unit as Server

You can enjoy the video and photos saved on the HDD of this unit on DLNA (Client) compatible equipment connected via a network.

You can also watch broadcasts received by this unit on DLNA (Client) compatible equipment.

- The titles with access restriction (e.g., copy restriction) signals sent from broadcasters are not available for this function.
- You cannot play back music from the playback equipment (Client).



For details regarding the connection and operation of equipment connected via a network, refer to their respective operating instructions.

- * DLNA function compatible software should be installed. For more details, refer to the Panasonic website. (⇒ left)

Preparation

- When DLNA (Server) Function is deactivated, make the settings. (⇒ 77, 89, Home Network Settings)

- 1 Operate the playback equipment (Client) to display the list of contents on this unit.
 - Refer to their respective operating instructions.
- 2 Select the item, then press [OK].




- The DLNA compatible device that is to be connected to the unit should be connected to the same hub or broadband router as the unit.
- Files not on the HDD cannot be played back.
- Playing back 3D video recorded on this unit may not work properly.
- 3D photos copied to this unit cannot be played back in 3D.
- Editing is not possible.

Smart Home Networking (DLNA)

Using this unit as Client

You can share videos, photos and music stored in the DLNA Certified media server (such as a PC with Windows 7 installed etc.) connected via a network with this unit.



- 1** Press [FUNCTION MENU].
- 2** Select "Home Network (DLNA Client)" in "Network", then press [OK].
A list of equipment connected via the network is displayed.
 - This list can be updated by pressing the red button.
- 3** Select the equipment, then press [OK].
- 4** Select the item, then press [OK].
 - Menu structure will be different depending on the equipment. Select the contents by repeating the operation.
 - Convenient functions can be used by pressing [OPTION] depending on the contents.
- **Control Panel**
Control Panel is displayed once the playback starts.
Operation can be performed with [▲, ▼, ◀, ▶], [OK] and [EXIT ⊗].
 - Press [OK] if the Control Panel is not displayed.
 - (While paying video or photo) Press [RETURN ⊕] to hide the Control Panel.



- You may not be able to use the Control Panel even if you use the Panasonic DLNA compatible equipment.
- Depending on the contents and the connected equipment, playback may not be possible.
- Playlist of Windows Media® Player can play back only the contents that are stored in the libraries.
- While playing back the 3D programme, you cannot set "3D Settings". (⇒ 40)
- Items displayed in grey on the display cannot be played back by this unit.
- Depending on the performance of the connected PC, video frames may be dropped during playback, or video may not be played back at all. (⇒ 103)

Support format of DLNA client

Video

Container	Video codec	Audio codec	Example of file extension
AVCHD	H.264	Dolby® Digital	.mts
MP4	H.264	AAC	.mp4
Recorded programmes (XP/SP/LP/EP/FR)	MPEG2	Dolby® Digital Linear PCM	.mpg .mpeg
Recorded programmes (DR/HG/HX/HE/HL/HM)	MPEG2 H.264	MPEG Dolby® Digital	.m2ts .ts

Photo

Format	Example of file extension
JPEG	.jpg



Audio

Audio codec	Example of file extension
MP3	.mp3
FLAC	.flac
Linear PCM	—

Using this unit as Media Renderer

This unit will work as Media Renderer, which allows you to play back the contents on DLNA Server by operating a Digital Media Controller (a smartphone, etc.).

Possible applications:



* Digital Media Controller compatible software should be installed.

Following steps are necessary to use this unit as Media Renderer.

- 1** Press [FUNCTION MENU].
- 2** Select "Home Network (Media Renderer)" in "Network", then press [OK].
- 3** Operate the Digital Media Controller compatible equipment.

To exit from Home Network (Media Renderer) screen

Press [RETURN ⊖].




- Depending on the contents and the connected equipment, playback may not be possible.
- Items displayed in grey on the display cannot be played back by this unit.
- This unit can be played back via connected equipment only when controlled using Digital Media Controller.
- Depending on the performance of the connected PC, video frames may be dropped during playback, or video may not be played back at all.

VIERA Connect (Enjoying Internet Service)

VIERA Connect allows you to access some specific websites supported by Panasonic, and enjoy Internet contents such as photos, videos, etc. from VIERA Connect home screen. This unit has no full browser function and all features of websites may not be available.

e.g.,



VIERA Connect Home screen

- Images are for illustration purpose, contents may change without notice.

Preparation


- Network connection (⇒ 17, 20)

To enjoy video communication (e.g., Skype™)

- Connect this unit with optional Communication Camera (TY-CC20W or TY-CC10W). Depending on the area, this optional camera may not be available. Please consult your local Panasonic dealer for advice.

e.g.,

This unit's rear panel



Communication Camera
TY-CC20W or TY-CC10W

- For operating method refer to the following website.
<http://panasonic.jp/support/global/cs/>
(This site is in English only.)
- Cannot be used while recording, copying, or playing BD-Video.

1 Press [INTERNET].

The message is displayed. Please read it carefully and then press [OK].

- The video communication service can be accessed directly by pressing [G] button.

2 Select the item, then press [OK].

- Operable buttons:

[▲], [▼], [◀], [▶], [OK], [RETURN ⊕], colour buttons and number buttons.

To exit from VIERA Connect

Press [EXIT ⊗].



- When playing content from a disc, SD card or USB device VIERA Connect cannot be accessed.
- In the following cases, settings are possible using "Network Service Settings" (⇒ 77, 88)
 - When restricting the use of VIERA Connect.
 - When the audio is distorted.
- If using slow Internet connection, the video may not be displayed correctly. A high-speed Internet service with a speed of at least 6 Mbps is recommended.
- Be sure to update the software (firmware) when a software (firmware) update notice is displayed on the screen. If the software (firmware) is not updated, you will not be able to use the VIERA Connect function.
- The services through VIERA Connect are operated by their respective service providers, and service may be discontinued either temporarily or permanently without notice. Therefore, Panasonic will make no warranty for the content or the continuity of the services.
- All features of websites or content of the service may not be available.
- Some contents may be inappropriate for some viewers.
- Some contents of VIERA Connect may only be available for specific countries and may be presented in specific languages.
- If timer recording starts, VIERA Connect will stop.

Media management



- 1 Press [FUNCTION MENU].
- 2 Select "Others", then press [OK].
- 3 Select the item, then press [OK].
 - Selectable items will change depending on the selected drive.

Disc Name

BD-RE BD-R RAM DVD-R DVD-RW +R +RW

This function is to name a disc.

Refer to "Entering text". (⇒ 95)

- The disc name is displayed in the Blu-ray Disc Management/DVD Management window.
- **DVD-R DVD-RW +R** With a finalised disc, the name is displayed on the Top Menu.
- **+RW** The disc name is displayed only if you play the disc on other equipment after creating Top Menu.



- Do not perform this operation before copying HD Video (AVCHD) to DVD-R or DVD-R DL. (⇒ 53)

Disc Protection

BD-RE BD-R RAM

Select "Yes", then press [OK].

e.g.,



- To release the protection
Repeat the same steps.
- The screen icon will be switched to "Off".

Delete all titles

BD-RE BD-R RAM

- 1 Select "Yes", then press [OK].
- 2 Select "Start", then press [OK].
A message appears when finished.
- 3 Press [OK].



- Photo data (JPEG/MPO) or computer data cannot be deleted.

Format Disc/Format Card

BD-RE RAM DVD-RW +RW SD

BD-R +R (New disc only)

Formatting deletes all contents (including computer data), and they cannot be restored. Check carefully before proceeding.

- 1 Select "Yes", then press [OK].
- 2 Select "Start", then press [OK].
- 3 Press [OK].

RAM To stop formatting

Press [RETURN ⊕].

- You can cancel formatting if it takes more than 2 minutes. The disc must be reformatted if you do this.



- The contents are deleted when you format a disc or card even if you have set protection.
- **RAM** Formatting normally takes a few minutes; however, it may take up to a maximum of 70 minutes.
- **Do not disconnect the AC mains lead while formatting.** This can render the disc or the card unusable.
- When a disc or card has been formatted using this unit, it may not be possible to use it on any other equipment.
- It will become DVD Video format when a DVD-RW recorded in DVD Video Recording format is formatted with this unit.

Media management

Top Menu

DVD-R **DVD-RW** **+R** **+RW**

You can select the background for DVD-Video Top Menu.

Select the background, then press [OK].



- You can change thumbnails displayed in the Top Menu. (⇒ 43, Changing thumbnail)

Auto-Play Select

DVD-R **DVD-RW** **+R** **+RW**

You can select whether to show the Top Menu after finalising or creating Top Menu.

Select "Top Menu" or "Title 1", then press [OK].

Top Menu:

The Top Menu appears first.

Title 1:

The disc content is played without displaying the Top Menu.

Finalise

DVD-R **DVD-RW** **+R** (You can play the disc on compatible DVD players by finalising it on the unit.)

BD-R (Finalising BD-R prevents accidental recording or editing.)

- 1 Select "Yes", then press [OK].
- 2 Select "Start", then press [OK].
- 3 Press [OK].

After finalising

- **BD-R** **DVD-R** **+R** The disc becomes play-only and you can no longer record or edit.
- **DVD-RW** You can record and edit the disc after formatting.



- You cannot cancel finalising.
- Finalising takes up to 15 minutes (Up to 60 minutes in case of DVD-R DL and +R DL).
- **Do not disconnect the AC mains lead while finalising.** This can render the disc unusable.
- Depending on the disc, it may take longer than displayed on the confirmation screen (approximately four times longer).
- You cannot finalise discs recorded on other manufacturer's equipment.
- **DVD-R** **DVD-RW** **+R** If you finalise discs recorded on Panasonic equipment other than this unit, the background selected as "Top Menu" may not be displayed.
- Discs finalised on this unit may not be playable on other players due to the condition of the recording.

Create Top Menu

+RW

You can create Top Menu for displaying on other equipment.

Make selections from "Top Menu" and "Auto-Play Select" before creating Top Menu.

- 1 Select "Yes", then press [OK].
- 2 Select "Start", then press [OK].
- 3 Press [OK].



- You cannot use the Top Menu for playing on this unit.
- The created menu is deleted when you record or edit the disc.

Registering the external HDD (USB HDD)



* "For recorded titles" only

If you intend to move recorded titles to a USB HDD, the USB HDD must be registered to this unit first.

Limitation information

- A USB HDD with a capacity of less than 160 GB cannot be used.
- Registering of a USB HDD will format the USB HDD and all the content already recorded will be deleted.
- Up to eight USB HDDs can be registered on this unit.
- Registered USB HDDs cannot be used with devices other than this unit.

Regarding the external HDD (USB HDD)

Please use a recommended USB HDD.

For the latest information on recommended USB HDDs, please check the following website.

<http://panasonic.jp/support/global/cs/>



- Certain non-recommended USB HDDs cannot be used with this unit.
- If a problem occurs with the USB HDD, please contact the manufacturer of the device.

Connecting the USB HDD

Connect this unit with optional USB HDD.

e.g.,

This unit's rear panel



- Only one USB HDD (For recorded titles) can be connected at the same time.
- Do not connect additional HDDs using a USB hub.
- For details about connection method, refer to the instructions supplied with the USB HDD.

Disconnecting the USB HDD

Please use the following procedure to disconnect. Disconnecting without following this procedure may result in the loss of recorded content from the USB HDD or the internal HDD.

- 1 Press [FUNCTION MENU].
- 2 Select "Setup" in "Others", then press [OK].
- 3 Select "Settings for USB HDD" in "HDD / Disc / USB HDD", then press [OK].
- 4 Select "USB HDD Disconnection", then press [OK].
- 5 Select "Yes", then press [OK].
- 6 Disconnect the USB HDD from this unit.

Registering the external HDD (USB HDD)

Registering the USB HDD

- If the registering screen appears when connecting the USB HDD, go to step 5.

- 1** Press [FUNCTION MENU].
- 2** Select "Setup" in "Others", then press [OK].
- 3** Select "Settings for USB HDD" in "HDD / Disc / USB HDD", then press [OK].
- 4** Select "USB HDD Registration", then press [OK].
- 5** Select "Yes", then press [OK].
 - If you have already registered eight USB HDDs, it will be necessary to delete one or more of them before registering a new USB HDD.
The message screen appears:
 - 1 Select "Yes", then press [OK].
 - 2 Select the USB HDD to cancel, then press [OK].
The confirmation screen appears.
 - 3 Select "Yes", then press [OK].
- 6** When the registering is complete, message screen appears.
Press [OK].
- 7** The confirmation screen appears.
Press [OK].

To cancel all USB HDD registrations

Refer to "Cancellation of all USB HDD Registrations". (⇒ 83)



- If you register a USB HDD, all the content already recorded on the USB HDD will be deleted.
- It is not possible to play back the content on the USB HDD whose registration has been cancelled.
- You can check the registration number of the USB HDD on the DIRECT NAVIGATOR. (⇒ 33)

VIERA Link functions

What is VIERA Link "HDAVI Control"?

VIERA Link "HDAVI Control" is a convenient function which will link the operations of this unit and a Panasonic TV (VIERA) or an amplifier/receiver. You can use this function by connecting the equipment with the HDMI cable. See the operating instructions for connected equipment.

Download from TV

When you connect the unit to a TV for the first time, the setting information on the TV is acquired by this unit. (⇒ 19).

- This function is available with the TV that supports "HDAVI Control 3" or later.

Automatic input switching/ Power on link

When the following operations are performed, the input channel of the TV will be automatically switched and the screen of this unit will be displayed. Additionally when the TV is off, the TV will automatically turn on.

- When play starts on this unit
- When an action that uses DIRECT NAVIGATOR etc, is performed

Power off link

When you set the TV to standby mode, this unit is also automatically set to standby mode.

- Power off link function does not work when recording, copying etc.

Playing music continuously even after turning off power to the TV

The following operations make it possible to keep the power of the unit on and to play music continuously.

When the unit is directly connected to an amplifier/receiver.

- 1 While playing music
Press [OPTION].
 - 2 Select "TV Power Off", then press [OK].
- Sound may be discontinued for several seconds when the power to the TV is turned off.
 - This function is available with the TV that supports "HDAVI Control 2" or later.

PAUSE LIVE TV

You can operate this unit with the TV remote control.

Refer to "PAUSE LIVE TV". (⇒ 25)

- This function is available with the TV that supports "HDAVI Control 3" or later.

Direct TV Recording

This function allows you to immediately start recording the programme that you are viewing on the TV.

Refer to the TV operating instructions for operation.

- This function is available with the TV that supports "HDAVI Control 3" or later.

Easy control only with VIERA remote control

You can operate this unit using the TV remote control.

Refer to the operating instructions of the TV about the buttons that you can use.

- This function is available with the TV that supports "HDAVI Control 2" or later.



- This unit supports "HDAVI Control 5" function.
"HDAVI Control 5" is the standard for Panasonic's HDAVI Control compatible equipment. This standard is compatible with Panasonic's conventional HDAVI equipment. Please refer to individual manuals for other manufacturers' equipment supporting VIERA Link function.
- VIERA Link "HDAVI Control", based on the control functions provided by HDMI which is an industry standard known as HDMI CEC (Consumer Electronics Control), is a unique function that we have developed and added. As such, its operation with other manufacturers' equipment that supports HDMI CEC cannot be guaranteed.
- These functions may not work normally depending on the equipment condition.
- Use the remote control supplied with this unit if you cannot operate this unit using buttons on the TV remote control.
- The operation of this unit may be interrupted when you press certain buttons on the TV remote control.

Playback menu

A variety of operations and settings such as changing the subtitles and audio languages can be performed during playback of video or music. Also, picture and sound quality can be set to your personal taste.

- 1** Press [OPTION].
- 2** Select "Playback Settings" in "Playback Menu" or select "Playback Settings", then press [OK].

e.g.,

Disc	Soundtrack	1 ENG	<input checked="" type="checkbox"/> Digital 2/0 ch
Play	Subtitles	Off	1 ENG
Picture	Angle	1	
Sound			
Other			

Menu Item Setting

- 3** Select the menu, then press [▶] (right).
- 4** Select the item, then press [▶] (right).
- 5** Select the setting.
 - Some items can be changed by pressing [OK].

Depending on the condition of the unit (playing, stopped, etc.) and media contents, there may be some items which cannot be selected or for which the effects do not work properly.

To clear the Playback menu

Press [RETURN ⊕].

Disc

Video

The original video recording method (MPEG-4 AVC etc.) appears.

Signal Type

Primary Video

Video

The original video recording method appears.

Soundtrack

Select the type of audio or language.

Secondary Video

Video

Select on/off of images.

The original video recording method appears.

Soundtrack

Select on/off of audio and the language.

Soundtrack*

Show or change the soundtrack.

Subtitles*

Turn the subtitle on/off, and change the language depending on the media.

Audio Selection

Switch in the case of multiple audio.

Subtitle Style

Select the subtitle style recorded on the disc.

Angle*

Change the number to select an angle.

Audio Channel

Change audio (LR/L/R) during playback.

- * With some discs, you may only be able to make changes using the menus on the disc.

Play

Repeat Play

Select the item which you want to repeat.

Random

Select whether to play random or not.

Graphic Display Level

You can change the 3D position of the playback settings display, etc., during the 3D playback.

Picture

Mode

Select the picture quality mode during play.

- **Normal**

Default setting.

- **Soft**

Soft picture with fewer video artifacts.

- **Fine**

Details are sharper.

- **Cinema**

Mellows movies, enhances detail in dark scenes.

- **Cartoon**

A mode suitable for viewing animations.

Advanced Settings

HD optimizer

This will compensate the mosaic noise in the video and haze around the characters precisely.

Chroma Process

The high-resolution processing of HDMI chroma signals produces a high-resolution picture with rich picture quality.

Detail Clarity

The picture becomes sharp and detailed.

Super Resolution

Standard picture quality video is corrected to sharp and crisp picture quality when it is output as 1080i/1080p.

Progressive

Select the method of conversion for progressive output to suit the type of title being played.

- **Auto**

Automatically detects the film and video content, and appropriately converts it.

- **Video**

Select this setting when the content is distorted if "Auto" is selected.

- **Film**

Select this if the edges of the film content appear jagged or rough when "Auto" is

selected. However, if the

video content is distorted as shown in the illustration to the right, then select "Auto".



Playback menu

Sound

- Sound Effects
 - This function is effective when “Digital Audio Output” is set to “PCM”. (⇒ 84)
- Re-master 1/Re-master 2
 - Sound becomes more natural by adding higher frequency signals not recorded on the track.
- Dialogue Enhancer
 - The volume of the centre channel is raised to make dialogue easier to hear.

Other

- Position
 - Change the position where this menu screen appears on your TV.

Audio attribute

LPCM/ <input type="checkbox"/> Digital/ <input type="checkbox"/> Digital+/ <input type="checkbox"/> TrueHD/ DTS/DTS-HD/MPEG/ HE-AAC:	Signal type
k (kHz):	Sampling frequency
b (bit):	Number of bits
ch (channel):	Number of channels

Language					
ENG	English	JPN	Japanese	ARA	Arabic
FRA	French	CHI	Chinese	HIN	Hindi
DEU	German	KOR	Korean	PER	Persian
ITA	Italian	MAL	Malay	IND	Indonesian
ESP	Spanish	VIE	Vietnamese	MRI	Maori
NLD	Dutch	THA	Thai	BUL	Bulgarian
SVE	Swedish	POL	Polish	RUM	Romanian
NOR	Norwegian	CES	Czech	GRE	Greek
DAN	Danish	SLK	Slovak	TUR	Turkish
POR	Portuguese	HUN	Hungarian	*	Others
RUS	Russian	FIN	Finnish		




- The menu is not displayed when playing photos.

Changing the unit's settings

You can change the unit's settings of Digital TV Tuning, Sound, Display, Connection, Network etc. in the menu.

Common procedures

- 1** Press [FUNCTION MENU].
- 2** Select "Setup" in "Others", then press [OK].



- 3** Select the menu, then press [OK].
- 4** Select the item, then make the setting. (⇒ right)
 - Follow the instructions on the screen if further operations are necessary.
 - Depending on the connection or the status of this unit some items cannot be selected or changed.

To return to the previous screen

Press [RETURN ⊙].

Menu list

The locations of the setting items are as follows. For details on each setting item, please refer to the following pages.

Digital TV Tuning

- Favourites Edit (⇒ 79)
- Channel List (⇒ 80)
- Auto Setup (⇒ 80)
- Download from TV (⇒ 80)
- Manual Tuning (⇒ 80)
- Update Channel List (⇒ 80)
- Child Lock (Parental Rating) (⇒ 80)
- Signal Condition (⇒ 80)
- New Channel Message (⇒ 80)

HDD / Disc / USB HDD

- Settings for Playback (⇒ 81)
 - 3D BD-Video Playback (⇒ 81)
 - Soundtrack (⇒ 81)
 - Subtitles (⇒ 81)
 - Menu (⇒ 81)
 - Play Video (AVCHD) on BD-RE / BD-R (⇒ 81)
 - BD-Live (⇒ 81)
 - BD-Video Parental Control (⇒ 81)
 - DVD-Video Parental Control (⇒ 81)
 - Pure Sound mode (⇒ 81)
- Settings for Recording (⇒ 82)
 - Timer Record Start Buffer (⇒ 82)
 - Timer Record Stop Buffer (⇒ 82)
 - REWIND LIVE TV (⇒ 82)
 - Aspect for Recording (⇒ 82)
 - Chapter Creation (⇒ 82)
 - Rec for High Speed Copy (⇒ 82)
 - BD / DVD Speed for High Speed Copy (⇒ 82)
 - Recording time in EP mode (⇒ 82)
- HDD Management (⇒ 82)
 - Delete all titles (⇒ 82)
 - Delete all photos (⇒ 82)
 - Format HDD (⇒ 82)
- Settings for USB HDD (⇒ 83)
 - USB HDD Registration (⇒ 83)
 - USB HDD Disconnection (⇒ 83)
 - USB HDD Management (⇒ 83)
 - Delete all titles (⇒ 83)
 - Format USB HDD (⇒ 83)
 - Cancellation of all USB HDD Registrations (⇒ 83)

Changing the unit's settings

Picture

- Still Mode (⇒ 83)
- Seamless Play (⇒ 83)

Sound

- Dynamic Range Compression (⇒ 84)
- Downmix (⇒ 84)
- Bilingual Audio Selection (⇒ 84)
- Digital Audio Output (⇒ 84)
 - PCM Down Conversion (⇒ 84)
 - Dolby D / Dolby D + / Dolby TrueHD (⇒ 84)
 - DTS / DTS-HD (⇒ 84)
 - MPEG (⇒ 84)
 - BD-Video Secondary Audio (⇒ 84)
- Audio Delay (⇒ 85)
- Audio Type for Digital Broadcast (⇒ 85)
- Audio for HG / HX / HE / HL / HM Recording (⇒ 85)

Display

- On-Screen Information (⇒ 85)
- Unit's Display (⇒ 85)
- Screen Saver (⇒ 85)
- Teletext (⇒ 85)
- Blue LED (⇒ 85)

Connection

- 3D Settings (⇒ 85)
 - 3D Type (⇒ 85)
 - 3D AVCHD Output (⇒ 85)
 - 3D Playback Message (⇒ 85)
- TV Aspect (⇒ 86)
- Aspect for 4:3 Video (⇒ 86)
- TV System (⇒ 86)
- HDMI Connection (⇒ 86)
 - HDMI Video Format (⇒ 86)
 - 24p Output (⇒ 86)
 - Deep Colour Output (⇒ 86)
 - HDMI Audio Output (⇒ 87)
 - 7.1ch Audio Reformatting (⇒ 87)
 - Contents Type Flag (⇒ 87)
 - VIERA Link (⇒ 87)

Network

- Easy Network Setting (⇒ 87)
- Network Settings (⇒ 87)
 - LAN Connection Mode (⇒ 87)
 - Wireless Settings (⇒ 87)
 - Connection Setting (⇒ 87)
 - Double Speed Mode Setting (2.4GHz) (⇒ 87)
 - IP Address / DNS Settings (⇒ 88)
 - Proxy Server Settings (⇒ 88)
 - Network Service Settings (⇒ 88)
 - Lock (⇒ 88)
 - Automatic Volume Control (⇒ 88)
 - Remote Recording Function Settings (⇒ 88)
 - Remote Recording function (⇒ 88)
 - Device ID (⇒ 88)
 - Initialize Device Password (⇒ 88)
 - Home Network Settings (⇒ 89)
 - Home Network function (⇒ 89)
 - Setting device name (⇒ 89)
 - Conversion Setting for DLNA (⇒ 89)
 - Resolution Setting for DLNA (⇒ 89)
 - Registration type for remote devices (⇒ 89)
 - Remote device list (⇒ 89)

Others

- Standby Settings (⇒ 90)
 - Quick Start (⇒ 90)
 - Automatic Standby (⇒ 90)
 - Automatic Standby after OTR (⇒ 90)
 - Automatic Standby after Copy (⇒ 90)
 - RF OUT (Aerial Signal) (⇒ 90)
 - Power Save for Network Standby (⇒ 90)
- Remote Control (⇒ 91)
- Clock (⇒ 91)
- PIN Entry (⇒ 92)
- System Update (⇒ 92)
 - Software Update in Standby (⇒ 92)
 - Software Update Now (Broadcast) (⇒ 92)
 - Software Update Now (Internet) (⇒ 92)
 - Software Licence (⇒ 92)
- System Information (⇒ 92)
- Initialize (⇒ 93)
 - Shipping Condition (⇒ 93)
 - Default Settings (⇒ 93)

Digital TV Tuning

Favourites Edit

You can create four favourites of channels for making viewing and recording easier.

Digital TV Favourites Editor

All Digital Channels	Favourites 1
1 ○○○○	
2 ○○○○	
3 ○○○○	
4 ○○○○	
5 ○○○○	
6 ○○○○	
7 ○○○○	

Select channel
Add
RETURN
Select favourites
Add all
Page up [▲]
Page down [▼]

After editing as follows, save the Favourites.


Press [RETURN ⊞], then press [OK].

- To delete channels:
Select the channel in the “Favourites” column, then press [OK].
 - Yellow: Delete all channels.
- To change the name of the Favourites list:
 - 1 Press the red button in the “Favourites” column.
 - 2 Press [▲, ▼, ◀, ▶] to select a character, then press [OK].
Repeat this step to enter other characters.
 - Red: Delete a character.
 - Blue: Delete all characters.
 - 3 Press [RETURN ⊞].
- To select the other Favourites list:
Press the green button.
- To add channels to the Favourites list:
Select the channel in the “All Digital Channels” column, then press [OK]. Repeat this step.
 - Yellow: Add all the available channels to the Favourites. (This function is available only when there are no channels in the “Favourites”.)
- To change the order of the channels list:
 - 1 Select the channel in the “Favourites” column to move, then press the green button.
 - 2 Select the new position, then press the green button.

Changing the unit's settings

Channel List

You can edit the channel list.



- To hide unwanted channels
 - 1 Select the channel.
 - 2 Press [OK].
The check mark is removed.
 - Yellow: Reveal all channels.
- To change the channel number assignment
 - 1 Select the channel to change, then press the green button.
 - 2 Enter the channel number to reassign with the number buttons.
 - 3 Press [OK].
- To set the channel manually
 - 1 Press the red button.
 - 2 Refer to "Manual Tuning". (⇒ below)

Auto Setup

You can restart the Auto Setup. (⇒ 19)
Select "Yes", then press [OK].



- The timer recording programmes are cancelled.

Download from TV

Select "Download from TV" when you connect the unit to a VIERA Link (HDAVI Control 3 or later) compatible TV.

Select "Yes", then press [OK].

Manual Tuning

You can add new channels manually.

- 1 Press [▲, ▼] to select the physical channel.
 - Adjust the frequency by checking the signal strength and signal quality displays.
- 2 Press [OK] to start scan.
 - The set channel is displayed in the table.

Update Channel List

You can update the channel list to the latest one.

Child Lock (Parental Rating)

You can restrict the viewing of channels unsuitable to children.


Set a ratings level to limit broadcast viewing and playback.

- PIN is required to change. (⇒ 23)

Signal Condition

You can check the quality and strength of signals.

Press [CH ▲ ▼] to select the channel.



- Signal Quality:
 - Green bar: Good
 - Yellow bar: Poor
 - Red bar: Bad



- The channels you can receive are affected by weather conditions, seasons, time (day/night), region, length of the cable that is connected to the aerial, etc.
- When the signal is too strong (red bar), reduce the signal amplification at your aerial. (For details, consult your dealer.)

New Channel Message

Set whether to obtain the information automatically when a new DVB channel is added.

HDD / Disc / USB HDD

Settings for Playback

3D BD-Video Playback

Select the playback method of 3D compatible video software.

Soundtrack

Select the audio language.

- If "Original" is selected, the original language of each disc will be selected.
- Enter a code with the number buttons when you select "Other ****".
(⇒ 93, Language code list)

Subtitles

Select the language for subtitle.

- If "Automatic" is selected and the language selected for "Soundtrack" is not available, subtitles of that language will automatically appear if available on that disc.
- Enter a code with the number buttons when you select "Other ****".
(⇒ 93, Language code list)

Menu

Select the language for disc menus.

- Enter a code with the number buttons when you select "Other ****".
(⇒ 93, Language code list)

Play Video (AVCHD) on BD-RE / BD-R

When playing a disc which contains the following two video formats;

- High Definition video (AVCHD) recorded by the Panasonic video camera, etc.,
- High Definition quality video recorded on this unit,

select which video to play back.

- On:
Play the High Definition video (AVCHD)
- Off:
Play the High Definition quality title

BD-Live

You can restrict Internet access when BD-Live functions are used.

- If "On (Limit)" is selected, Internet access is permitted only for BD-Live contents which have content owner certificates.

BD-Video Parental Control

Set an age limit of BD-Video play.

- PIN is required to change. (⇒ 23)

DVD-Video Parental Control

Set a rating level to limit DVD-Video play.

- PIN is required to change. (⇒ 23)

Pure Sound mode

You can enjoy movies or music in an environment more suitable for viewing by stopping the rotation of the HDD when playing back commercial BD-Videos, DVD-Videos or music CDs.

- If "On" is selected, timer recording does not start during playback BD-Video, DVD-Video or music CD.

Changing the unit's settings

Settings for Recording

Timer Record Start Buffer

This function sets the timer recording to start earlier than the TV Guide time.

Timer Record Stop Buffer

This function sets the timer recording to stop later than the TV Guide time.

REWIND LIVE TV

Turn on/off the REWIND LIVE TV function.

- When "Automatic Standby" is set to "Off" (⇒ 90), "On" cannot be selected.

Aspect for Recording

Sets the aspect ratio when recording or copying except in DR mode.

- If "Automatic" is selected, the title will be recorded with the original aspect ratio at the time when recording started (including when recording started at a commercial, etc.).
- In the following cases, the programme will be recorded with the original aspect ratio.
 - **[BD-RE] [BD-R]** When the recording mode is set to "XP", "SP", "LP", "EP" or "FR"
 - **[HDD] [RAM]** When the recording mode is set to "XP", "SP", "LP", "EP" or "FR" with the "Rec for High Speed Copy" set to "Off"
- In the following cases, aspect is fixed to 4:3.
 - **[DVD-R] [DVD-RW]** When the recording mode is set to "EP" or "FR (recordings 5 hours or longer)" mode.
 - When recording to a +R, +R DL and +RW.

Chapter Creation

Set the Chapter Creation method.

- Even if "Automatic" is selected, depending on the programme to be recorded, the chapter may not be created correctly.

Rec for High Speed Copy

You can copy titles to DVD in high speed mode, if you set to "On" before recording a programme.

- This setting is valid for the following cases:
 - File Conversion (⇒ 44)
 - Recording from external equipment
 - Copying from a finalised DVD-Video disc
- If "On" is selected, the following restrictions are applied to recorded titles.
 - The settings in "Aspect for Recording" (⇒ left) and in "Bilingual Audio Selection" (⇒ 84) are applied to titles.
 - You cannot switch the audio when watching a programme via AV input.

BD / DVD Speed for High Speed Copy

Select the speed of high-speed copying.

If "Normal (Silent)" is selected, the time required for copying will be longer.

Recording time in EP mode

Select the maximum number of hours for recording in EP mode (⇒ 112, Recording modes and approximate recording times).

HDD Management

Press and hold [OK] for 3 seconds to show the following settings.

Delete all titles

Delete all titles (video) on the built-in HDD.

- Delete does not work if one or more titles are protected.

Delete all photos

Delete all photos on the built-in HDD.

Format HDD

Formatting deletes all contents on the built-in HDD, and they cannot be restored. Check carefully before proceeding.

Settings for USB HDD

USB HDD Registration

Register the USB HDD. (⇒ 71)

USB HDD Disconnection

This function puts the USB HDD in a state in which it can be safely disconnected. (⇒ 71)

USB HDD Management

Press and hold [OK] for 3 seconds to show the following settings.

Delete all titles

Delete all titles on the USB HDD.

- Delete does not work if one or more titles are protected.

Format USB HDD

Formatting deletes all contents, and they cannot be restored. Check carefully before proceeding.

Cancellation of all USB HDD Registrations

This function cancels the registrations of all the USB HDDs registered on this unit.

Only do this if you are going to dispose of this unit.



- Before operation, perform "USB HDD Disconnection" (⇒ above) and remove the USB HDD.
- It is not possible to play back the content from a USB HDD whose registration has been cancelled.

Picture

Still Mode

Select the type of picture shown when you pause play.

- Field:
Select if jittering occurs when "Automatic" is selected. (The picture is coarser.)
- Frame:
Select if small text or fine patterns cannot be seen clearly when "Automatic" is selected. (The picture is clearer and finer.)

Seamless Play

The segments can be played back seamlessly.

- When "Off" is selected, frame-dropping between the segments can be avoided, but the video may freeze for a moment between the segments.
- Seamless Play function does not work depending on the condition or the kind of programme.

Changing the unit's settings

Sound

Dynamic Range Compression

To lower the dynamic range for playback (e.g., at night).

- This does not work depending on broadcasts and recorded titles.

Downmix

Select the downmix system of multi-channel to 2-channels sound.

- Select "Surround encoded", when the connected equipment supports the virtual surround function.
- There is no effect on "Bitstream" via HDMI AV OUT and DIGITAL AUDIO OUT terminal.
- The audio will be output in "Stereo" in the following cases.
 - AVCHD playback
 - **BD-V** : Playback of clicking sound on the menu and audio with secondary video in picture-in-picture mode.

Bilingual Audio Selection

Select whether to record the audio type ("M1" or "M2") when:

- File Conversion (⇒ 44)
- Copying to a DVD-R, DVD-RW, +R and +RW.
- "Rec for High Speed Copy" is set to "On". (⇒ 82)

Digital Audio Output

PCM Down Conversion

Select how to output audio with a sampling frequency of 96 kHz.

- On:
 - Signals are converted to 48 kHz. (Choose when the connected equipment cannot process signals with a sampling frequency of 96 kHz.)
- Off:
 - Signals are output as 96 kHz.
 - The signals will be converted to 48 kHz regardless of the setting in the following cases.
 - The signals have a sampling frequency of over 96 kHz.
 - The disc has copy protection.
 - "BD-Video Secondary Audio" is set to "On". (**BD-V**) (⇒ below)

Dolby D / Dolby D + / Dolby TrueHD

DTS / DTS-HD

MPEG

Select the audio signal to output.

- Select "PCM" when the connected equipment cannot decode the respective audio format.
- Not making the proper settings may result in noise.

BD-Video Secondary Audio

Turn on/off the clicking sound on the menu and audio with secondary video.

Audio Delay

Mis-sync between the video and audio is corrected by delaying the audio output.

Audio Type for Digital Broadcast

If the programme has more than one track (Dolby Digital, MPEG, etc.), you can set priorities.

- This setting will give effect in the following conditions.
 - The default setting when watching broadcasts.
 - The default setting when playing back the title recorded in DR mode.
 - File Conversion (⇒ 44)
 - Normal speed copy from the title recorded in DR mode. (⇒ 46)

Audio for HG / HX / HE / HL / HM Recording

If the programme has multi channel audio, priority is given to what you select.

- This setting will give effect in the following cases.
 - Timer recording (⇒ 29)
 - File Conversion (⇒ 44)
 - Normal speed copy in HG, HX, HE, HL or HM mode from a title recorded in DR mode. (⇒ 46)

Display

On-Screen Information

Select the time until the channel information screen (⇒ 24) disappears automatically.

Unit's Display

Changes the brightness of the unit's display.

Screen Saver

This is to prevent burn-in on the screen.

Teletext

Select the Teletext (⇒ 25) display mode.

Blue LED

Set the lighting method for the lamp on the SD card slot.

- If "SD inserted" is selected, when this unit is turned on and SD card is inserted, the lamp is lighted.

Connection

3D Settings

3D Type

If 3D video cannot be played back in 3D, you may be able to play it in 3D by changing the setting.

- Change the settings for 3D on the TV also when "Side by side" is selected.

3D AVCHD Output

If 2D AVCHD video is recognised as 3D video and cannot be played back correctly, you may be able to play it by changing the setting.

3D Playback Message

Set to display or hide the 3D viewing warning screen.

Changing the unit's settings

TV Aspect

Set to match the type of TV connected.

- **Pan & Scan:**

Side picture is trimmed for 16:9 picture.

The pictures may be shown in the letterbox style depending on the content.



- **Letterbox:**

Black bands appear for 16:9 picture.



Aspect for 4:3 Video

To play a 4:3 title, set how to show pictures on a 16:9 TV.

TV System

Set in accordance with the TV System for the connected TV.

HDMI Connection

HDMI Video Format

You can only select items compatible with the connected equipment.

- If "Automatic" is selected, the output resolution best suited to the connected TV (1080p, 1080i, 720p or 576p/480p) is automatically selected.
- To enjoy High Quality Video up-converted to 1080p, you need to connect the unit to 1080p compatible HDTV. If this unit is connected to an HDTV through other equipment, it must also be 1080p compatible.

24p Output

When playing BD-Video recorded in 24 frames, this unit displays each frame at 1/24 second intervals—the same interval originally shot with the film movie.

- This item is effective only when this unit is connected to a TV supporting 1080/24p output and "HDMI Video Format" is set to "Automatic" or "1080p". (⇒ above)
- When BD-Video images other than 24p are played, images are output at 60p.

Deep Colour Output

This setting is for selecting whether to use Deep Colour output when a TV that supports Deep Colour is connected.

HDMI Audio Output

Select "Off" when connected to an amplifier/receiver with a DIGITAL AUDIO OUT terminal.

7.1ch Audio Reformatting

BD-V

Surround sound with 6.1 ch or less is automatically expanded and played back at 7.1 ch.

- If "Off" is selected, sound is played over the original number of channels. (Note that in the case of 6.1 ch audio, playback will be at 5.1 ch)

Audio reformatting is enabled in the following cases:

- When you have selected "PCM" in "Digital Audio Output".
- When the audio is Dolby Digital, Dolby Digital Plus, Dolby TrueHD or LPCM.

Contents Type Flag

If "Automatic" is selected, the optimal method of playback depending on the TV (e.g. cinema) will automatically be selected (only when the TV supports Contents Type Flag).

VIERA Link

Select "Off" when you do not want to use "HDAVI Control".

Network

Easy Network Setting

Press [OK] to start Easy Network Setting. (⇒ 20)


Network Settings

LAN Connection Mode

Select the LAN connection method.

Wireless Settings

This allows to set and check the connection settings of the Wireless router.



Connection Setting

The Wireless router connection wizard will be displayed.

Double Speed Mode Setting (2.4GHz)

When a 2.4 GHz wireless format is used, this setting sets the connection speed.

- If you connect using the "Double Speed Mode (40MHz)", 2 channels use the same frequency band, and there is consequently a greater risk of reception interference. This can cause the connection speed to drop or the connection to become unstable.

Changing the unit's settings

IP Address / DNS Settings

Check the connection of the network or set the IP address and DNS.

- To set the IP address and DNS
 - 1 Set "IP Address Auto-assignment" and "DNS-IP Auto-assignment" to "Off".
 - 2 Select the item, then press [OK] to show the respective setting.
- When the router's DHCP server function is not activated, check the numbers of other connected devices such as personal computers, then assign a number different from those of other devices for the "IP Address" and assign the same number for "Subnet Mask" and "Gateway Address".

Proxy Server Settings

Check and set the connection to the Proxy server.

- Press [OK] to show the respective setting.

Network Service Settings

Lock

You can restrict using VIERA Connect.

- PIN is required to change. (⇒ 23)

Automatic Volume Control

Volume is adjusted automatically to the standard volume while using VIERA Connect.

- Depending on contents, this function will not work.
- Select "Off" when the audio is warped.

Remote Recording Function Settings

You must register to a service to use this function.

For details please check the following website.

<http://panasonic.jp/support/global/cs/>

(This site is in English only.)

- However, as of February 2013, the service has not yet been launched.

Remote Recording function

When you set a recording from a mobile phone or a PC, etc. away from home, set this function to "On".

Device ID

This is the device ID and device password required for registering to and using a service.

Initialize Device Password

The device password for this unit is initialized.

- When you initialize the device password, you will not be able to use Remote Recording function. To use the Remote Recording function again, you must re-register to the service.

Home Network Settings

You can set the DLNA (Server) function.
(⇒ 65)

Home Network function

You can switch between enable/disable of the DLNA (Server) and DMR (Media Renderer) function.

- If "On" is selected, the setting for "Quick Start" is fixed to "On". (⇒ 90)
- If "Off" is selected, the setting for "Remote Recording function" is fixed to "Off". (⇒ 88)
- This cannot be set to "On" if the connection with the wireless broadband router is not encrypted in the wireless connection.

Setting device name

It is also possible to change the name of this unit on the network.

- Select from a preset list
Select the preset name, then press [OK].
- Create name
Enter the name.
Refer to "Entering text". (⇒ 95)

Conversion Setting for DLNA

- On:
When playing back on DLNA (Client) compatible equipment, this setting reduces the chance of break-ups and freezing of an image by lowering the image quality.



- When this is set to "On", switching the channel or starting playback will take longer.

Resolution Setting for DLNA

When "Conversion Setting for DLNA" is set to "On", select the image quality.

Registration type for remote devices

- Automatic:
All connected devices on the same network can access this unit.
- Manual:
Only registered devices can access this unit.

Remote device list

- To register equipment manually
 - 1 Select the device name or the MAC Address for the device you want to register, then press [OK].
 - 2 Select "Yes", then press [OK].
- To deregister equipment
 - 1 Select the registered equipment, then press [OK].
 - 2 Select "Yes", then press [OK].



- This function cannot be enabled when "Automatic" is selected in "Registration type for remote devices". (⇒ above)
- The maximum number of equipment that can be registered is 16.

Changing the unit's settings

Others

Standby Settings

Quick Start

- On:
It is possible to start quickly from standby mode.
- Off:
Power consumption in standby mode is minimized. (⇒ 108)
However, startup time from standby mode will be longer.
- Timer Setting for Quick Start:
"Quick Start" is activated when the set time comes. (If the clock has not been set, this function is not activated at all hours.)



- When "Home Network function" (⇒ 89) or "Remote Recording function" (⇒ 88) is set to "On", the setting for this function is fixed to "On".
- The setting may be changed to "On" automatically when the setting for video communication is changed. (⇒ 68)

Automatic Standby

Set the time to turn the unit to standby mode automatically.

When the unit is not operating, the unit will be turned to standby mode once the set time has passed.

- When "REWIND LIVE TV" is set to "On" (⇒ 82), "Off" cannot be selected.

Automatic Standby after OTR

- On:
This unit is turned to standby mode when it is not operated for approximately 5 minutes after completing "Automatic Stop" or "Recording Time" (⇒ 27).

Automatic Standby after Copy

- On:
This unit is turned to standby mode when it is not operated for approximately 5 minutes after completing copy (⇒ 48, Copying from media other than HDD with DIRECT NAVIGATOR, Copying titles with copying list).

RF OUT (Aerial Signal)

Set whether to output the broadcasting signal from RF OUT or not while in standby mode (When "Quick Start" is not activated).

- If "On" is selected, the aerial signal is output from this unit.

Power Save for Network Standby

You can minimize power consumption in standby mode even when the "Quick Start" function is activated. (⇒ 108)



- When this is set to "On", startup time when operating [GUIDE] and [DIRECT NAVIGATOR] from standby mode will be longer.

Remote Control

Change the remote control code on the main unit and the remote control if you place other Panasonic products close together.

- Use "BD 1", the factory set code, under normal circumstances.
- 1 Select the code, then press [OK].
 - 2 While pressing [OK], press and hold the number button ([1] to [6]) for more than 5 seconds.
 - 3 Press and hold [OK] for more than 5 seconds.
 - 4 Press [OK].

Clock

If the time is not set correctly, use the settings listed in the method below.

- Automatic
This unit usually obtains time and date information from digital broadcasts.
- Region Selection
Select the region where you live to adjust the standard time.
 - The time contained in the broadcast signal is UTC (Universal time, coordinated).
- Daylight Saving Time
Select time offset from the standard time for Summer Time.
 - If there is a gap between displayed time and actual time, set this function.
- Manual Setting
 - 1 Select "Off" of "Automatic", then press [OK].
 - 2 Select the item you want to change.
 - 3 Change the setting.
 - 4 Press [OK] when you have finished the settings.


Changing the unit's settings

PIN Entry

You can set/change the PIN for parental control.

- 1 Enter your 4-digit PIN with the number buttons.
 - 2 Enter the new 4-digit PIN with the number buttons.
- **Make a note of PIN in case you forget it.**

e.g.,



- 3 Press [OK].

System Update

Software Update in Standby

When you set this unit to standby mode, software (firmware) updates (⇒ 94) are downloaded automatically at the time you have specified.

Software Update Now (Broadcast)

Refer to "Software (Firmware) Update".
(⇒ 94)

Software Update Now (Internet)

Refer to "Software (Firmware) Update".
(⇒ 94)

Software Licence

Information about the software licence is displayed.

System Information

Display software (firmware), HDAVI Control version and Wireless Module version (When using wireless connection only) of this unit.

Initialize

Shipping Condition

All the settings except for basic settings return to the factory preset.

- The timer recording programmes are also cancelled.
- The device password is also initialized.
(⇒ 88)

Default Settings

All the settings other than the tuning settings, clock settings, disc language settings, rating PIN, remote control code, device password, etc. return to the factory presets.

Language code list

Abkhazian:	6566	Lingala:	7678
Afar:	6565	Lithuanian:	7684
Afrikaans:	6570	Macedonian:	7775
Albanian:	8381	Malagasy:	7771
Amharic:	6577	Malay:	7783
Arabic:	6582	Malayalam:	7776
Armenian:	7289	Maltese:	7784
Assamese:	6583	Maori:	7773
Aymara:	6589	Marathi:	7782
Azerbaijani:	6590	Moldavian:	7779
Bashkir:	6665	Mongolian:	7778
Basque:	6985	Nauru:	7865
Bengali; Bangla:	6678	Nepali:	7869
Bhutani:	6890	Norwegian:	7879
Bihari:	6672	Oriya:	7982
Breton:	6682	Pashto, Pushto:	8083
Bulgarian:	6671	Persian:	7065
Burmese:	7789	Polish:	8076
Byelorussian:	6669	Portuguese:	8084
Cambodian:	7577	Punjabi:	8065
Catalan:	6765	Quechua:	8185
Chinese:	9072	Rhaeto-Romance:	8277
Corsican:	6779	Romanian:	8279
Croatian:	7282	Russian:	8285
Czech:	6783	Samoan:	8377
Danish:	6865	Sanskrit:	8365
Dutch:	7876	Scots Gaelic:	7168
English:	6978	Serbian:	8382
Esperanto:	6979	Serbo-Croatian:	8372
Estonian:	6984	Shona:	8378
Faroese:	7079	Sindhi:	8368
Fiji:	7074	Singhalese:	8373
Finnish:	7073	Slovak:	8375
French:	7082	Slovenian:	8376
Frisian:	7089	Somali:	8379
Galician:	7176	Spanish:	6983
Georgian:	7565	Sundanese:	8385
German:	6869	Swahili:	8387
Greek:	6976	Swedish:	8386
Greenlandic:	7576	Tagalog:	8476
Guarani:	7178	Tajik:	8471
Gujarati:	7185	Tamil:	8465
Hausa:	7265	Tatar:	8484
Hebrew:	7387	Telugu:	8469
Hindi:	7273	Thai:	8472
Hungarian:	7285	Tibetan:	6679
Icelandic:	7383	Tigrinya:	8473
Indonesian:	7378	Tonga:	8479
Interlingua:	7365	Turkish:	8482
Irish:	7165	Turkmen:	8475
Italian:	7384	Twì:	8487
Japanese:	7465	Ukrainian:	8575
Javanese:	7487	Urdu:	8582
Kannada:	7578	Uzbek:	8590
Kashmiri:	7583	Vietnamese:	8673
Kazakh:	7575	Volapük:	8679
Kirghiz:	7589	Welsh:	6789
Korean:	7579	Wolof:	8779
Kurdish:	7585	Xhosa:	8872
Laotian:	7679	Yiddish:	7473
Latin:	7665	Yoruba:	8979
Latvian, Lettish:	7686	Zulu:	9085

Software (Firmware) Update

You cannot operate the unit until the update is complete. Don't remove the AC mains lead during the update. Removing the AC mains lead while the update is in progress may damage the unit.

If a software (firmware) update is available, a notification is displayed.

New software version has been found.
The software will be updated automatically after this unit is switched to standby.
Do not disconnect the AC mains lead.

Software of this unit can be updated automatically by the following methods at the specified time.
(Default setting is 3 a.m. ⇒ 92, Software Update in Standby)

- From broadcasts
- From Internet*

• To update the software (Firmware) immediately, use the following function:

- Software Update Now (Broadcast):
Software of this unit will be updated from broadcasts if update information is detected.
- Software Update Now (Internet)*:
Software of this unit will be updated from Internet if update information is detected.

* Network connection and setting are required.
(⇒ 17, 20)

- It is displayed on the channel information (⇒ 24) when the Software (Firmware) can be updated immediately.

e.g.,




To execute, press the red button while the channel information is displayed, and follow the instructions on the screen.

Update of the software (firmware) will start when the unit is turned to standby mode.

The unit's display during the update

e.g.,



- When "FINISH" is displayed, update of the software (firmware) has completed.



- It may take up to a few hours until the update is completed depending on the network or broadcast environment.
- The timer recording always takes preference over the software (Firmware) download; if the timer recording is scheduled to start, the downloading will be performed at the next opportunity.
- You can also download the latest software (firmware) from the following website.
<http://panasonic.jp/support/global/cs/>

Other operations


Entering text

Preparation

- Show the “Enter Title Name” screen, etc.


- 1 Select a character, then press [OK].
Repeat this step to enter other characters.

e.g.,



- To delete a character:
Select the character in the name field, then press [PAUSE ■].
- To enter characters with number buttons:
e.g., entering the letter “R”

- 1 Press [7] to move to the seventh row.
- 2 Press [7] twice to highlight “R”.
- 3 Press [OK].



- 2 Press [STOP ■] (Set).
“Writing...” appears then the screen returns to the previous screen and so on.

To end partway

Press [RETURN ⊕]. (Text is not added.)



- The maximum number of characters depends on the media.
- If a name is long, parts of it may not be shown in some screens.

Switching the aspect ratio of the screen

When the image does not match the screen size of the TV, you can enlarge the image to fill the screen.

- 1 Press [OPTION].
- 2 Select “Aspect”, then press [OK].
- 3 Select the item, then press [OK].

Normal:

Normal output

Side cut:

The black bars on the right and left sides of the 16:9 image disappear and the image is enlarged.

Zoom:

The black bars on the top and bottom sides of the 4:3 image disappear and the image is enlarged.



- This function does not work when watching 3D programme and playing back 3D title or 3D photo.
- It may also be adjusted using the screen mode of the TV etc.
- The screen mode is switched to “Normal” in the following situations:
 - when you change the channel
 - when you start or end the playback of a title
 - when you switch the unit on or to standby mode.
- [BD-V] [DVD-V] “Side cut” does not have any effect.
- When “TV Aspect” (↔ 86) is set to “Pan & Scan” or “Letterbox”, the “Zoom” effect is disabled.

HOLD function

The HOLD function deactivates all buttons on the unit and remote control.

Press and hold [OK] and [RETURN ⊕] simultaneously until “X HOLD” appears on the unit’s display.



Unit's display

To cancel the HOLD function

Press and hold [OK] and [RETURN ⊕] simultaneously until “X HOLD” disappears.

Troubleshooting guide

Before requesting service, make the following checks. If the problem still persists, consult your dealer for instructions.

Updating to the latest software (firmware) may solve the problem. (⇒ 94)

The followings do not indicate a problem with this unit:

- Regular disc rotating sounds or HDD rotating sounds.
- Poor reception due to atmospheric conditions.
- Image disturbance during search.
- Image disturbance when replacing 3D discs.
- Interruptions in reception due to periodic broadcasting breaks.
- When you switch the unit on or to standby mode, there may be an unexpected sound.

General operation

The unit does not work.

- Check the connections. (⇒ 14)
- One of the unit's safety devices may have been activated.

Reset the unit as follows:

- 1 Press [⏻] on the main unit to switch the unit to standby.
 - If the unit does not switch to standby, press [⏻] on the main unit for about 3 seconds. The unit is forcibly switched to standby. Alternatively, disconnect the AC mains lead, wait one minute, then reconnect it.
- 2 Press [⏻] on the main unit to switch it on. If the unit still cannot be operated, consult the dealer.

Cannot eject a disc.

- 1 While the unit is in standby mode, press and hold [OK], the yellow button and the blue button at the same time for more than 5 seconds.
 - "00 RET" is displayed on the unit's display.
- 2 Repeatedly press [▶] (right) until "06 FTO" is displayed on the unit's display.
- 3 Press [OK].

The unit is switched to standby mode automatically.

- VIERA Link has worked. (⇒ 73, Power off link)

The remote control does not work.

- The remote control and main unit are using different codes. Change the code on the remote control.



Unit's display

Press and hold [OK] and the indicated number button at the same time for more than 5 seconds. (⇒ 91)

- Software (firmware) is updating when "UPD □/□" is displaying on the unit's display. Wait until the update is completed. (⇒ 94)
- The HOLD function is activated. (⇒ 95)

Startup is slow.

- Startup takes time in the following situations:
 - A disc is inserted.
 - The clock is not set.
 - Immediately after a power failure or the AC mains lead is connected.
 - When a BD-J application is executing.
 - When the "Quick Start" is not activated. (⇒ 90)
- Startup of this unit may be slower depending on the TV settings.

Displays

"0:00" is flashing on the unit's display.

- Set the clock. (⇒ 77, 91)

The clock does not display on the unit when switched to standby.

- The clock does not display when "Quick Start" is not activated. (⇒ 90)

TV screen and video

Screen size is wrong.

- Check the "TV Aspect" or "Aspect for 4:3 Video". (⇒ 86)
- Adjust the aspect ratio setting on TV.
- If you connect to 4:3 TV, set "HDMI Video Format" to "576p/480p". (⇒ 77, 86)
- Check "Aspect for Recording" before recording or file conversion. (⇒ 77, 82)

The black screen appears on the TV.

- This phenomenon may occur, depending on the TV setting, when "Quick Start" is activated. Depending on the TV, this phenomenon may be prevented by reconnecting to a different HDMI input terminal.

TV reception is not displayed.

- Broadcast signals are not output from this unit's RF OUT terminal. Select "On" in "RF OUT (Aerial Signal)". (⇒ 77, 90)

Picture does not appear with the HD quality although HD setting was made.

- The pictures are output with 576p/480p depending on the title.

Troubleshooting guide

The screen changes automatically.

- If "Screen Saver" set to "On", the screen saver function will be activated when there is no operation for 5 minutes or more. (⇒ 85)

There is a lot of image lag when playing video.

- Set "HD optimizer" in the Picture menu to "Off". (⇒ 75)
- Set "Audio Delay". (⇒ 77, 85)

The images do not appear on the TV.

The picture is distorted during play, or video will not play correctly.

- Check the connections. (⇒ 14)
- Check the settings of the connected TV, etc.
- An incorrect resolution is selected in "HDMI Video Format". Reset the setting as follows:
 - 1 While the unit is on, press and hold [OK], the yellow button and the blue button at the same time for more than 5 seconds.
 - "00 RET" is displayed on the unit's display.
 - 2 Repeatedly press [▶] (right) until "04 PRG" is displayed on the unit's display.
 - 3 Press and hold [OK] for at least 3 seconds. Set the item again. (⇒ 77, 86)
 - When Dolby Digital Plus, Dolby TrueHD, and DTS-HD audio are not output properly, select "Yes" in "Default Settings" and make proper settings. (⇒ 77, 93)
- The unit's TV System is different from that of the disc. While stopped, keep pressing [■] (STOP) and [▲ OPEN/CLOSE] on the main unit for 5 or more seconds. The system switches from PAL to NTSC or vice versa.
- Picture may not be seen when more than 4 devices are connected with HDMI cables. Reduce the number of connected devices.
- The picture may be distorted or a black screen may appear between scenes recorded with different aspect ratios.
- Set "Deep Colour Output" (⇒ 77, 86) or "Contents Type Flag" (⇒ 77, 87) to "Off".

3D video is not output correctly.

- 3D video may be output correctly by changing the following settings:
 - "3D Type" of "3D Settings" (⇒ 77, 85)
 - "Signal Format" (⇒ 40, 3D settings during playback)
- Check the settings of the connected TV.
- When a non-3D compatible amplifier/receiver is connected between this unit and a TV, 3D video is not output. (⇒ 15)
- When the amplifier/receiver which is connected between this unit and a TV is off, 3D video is not output. (⇒ 15)
- 3D discs may not be played back correctly due to the settings of the TV.
- When "HDMI Audio Output" is set to "Off", 3D video may not be output correctly. (⇒ 87)

The same video is displayed in each left and right half of the screen.

- This is a 3D programme of the Side-by-Side type.
Change the setting as follows if connecting with a 3D compatible TV:
 - 1 Press [OPTION].
 - 2 Select "3D Settings", then press [OK].
 - 3 Select "Side by side" in "Signal Format", then press [OK].

Sound

No sound.

Distorted sound.

- Check the connections. (⇒ 14)
- Check the settings of the connected TV, etc.
- Press [AUDIO] to select the audio. (⇒ 25, 39)
- To output audio from a device connected with an HDMI cable, set "HDMI Audio Output" to "On". (⇒ 77, 87)

Cannot change audio channel.

- You cannot change the audio channel if "Digital Audio Output" is set to "Bitstream" (⇒ 84)


Recording, timer recording and copying

Cannot record.

Cannot copy.

- Some broadcasts are copyright protected.
- You cannot record to the disc by pressing the [REC ●] or timer recording.
- The disc is protected. (⇒ 69)
- **DVD-R** **DVD-RW** **+R** **+RW** Since it will copy to HDD temporarily, copying is not possible if there is insufficient available capacity on the HDD.
- **DVD-R** **DVD-RW** **+R** **+RW** Copying or editing may not be possible on these discs after ejecting and loading the disc or switching the unit on or to standby mode for approximately 30 times after being copied to.
- This unit cannot record/copy NTSC signals to discs that already have PAL signal recordings.

Timer recording does not work properly.

- Failed timer recordings are displayed in grey with  on the Timer Recording screen. (⇒ 32)
When you programme a timer recording, check the screen icons. If "!" is displayed, this timer programme may not be recorded because:
 - there is not enough space left.
 - the number of possible titles has reached its maximum.
 - programmes are deactivated, etc.

Auto Renewal Recording does not work properly.

- The programme will not be overwritten in the following cases:
 - the programme is protected
 - any programme is being played back or copied
 - a screen such as DIRECT NAVIGATOR is displayed
 Instead, the programme will be saved as a separate programme and that will be overwritten.

Troubleshooting guide

A part or whole of a recorded title has been lost.

- If there is a power failure or the AC mains lead is disconnected from the household mains socket while recording or editing, the title may be lost or the HDD may become unusable. We cannot offer any guarantee regarding lost programmes.

An unusually loud sound is coming from the rotating disc.

- If you want copy to perform more quietly, select "Normal (Silent)" in "BD / DVD Speed for High Speed Copy". (⇒ 77, 82)

The time recorded on the disc and the available time shown do not add up.

- **DVD-R** **+R** If you record or edit many times, the remaining capacity is reduced and then recording or editing may be disabled.
- Available disc space display may be different from actual.

Play

Cannot play back.

- The disc is dirty. (⇒ 10)
- The disc is scratched or marked.
- **BD-R** **BD-RE**
Set "Play Video (AVCHD)" on BD-RE / BD-R" to "On" and the playback may be possible (⇒ 77, 81).
- The disc may not be able to play back if it was not finalized or a Top Menu was not created on the equipment used for recording.

Audio and video momentarily pause.

- DVD-R DL and +R DL discs have two writable layers on one side. Video and audio may momentarily cut out when the unit is switching layers.

BD-Video or DVD-Video is not played.

- Ensure the disc is for the correct BD-Video region code or DVD-Video region number, and is not defective.

You have forgotten your rating PIN.

- The rating level returns to the factory preset.
 - 1 While the unit is on, press and hold [OK], the yellow button and the blue button at the same time for more than 5 seconds.
 - "00 RET" is displayed on the unit's display.
 - 2 Repeatedly press [▶] (right) until "03 VL" is displayed on the unit's display.
 - 3 Press [OK].
 - "INIT" is displayed on the unit's display.

Image for the Quick View is not smooth.

- Image may not be played back smoothly in case of DR, HG, HX, HE, HL, HM mode titles, AVCHD format titles or BD-Video.

Cannot play the disc on other players.

- **BD-RE** **BD-R** When these discs cannot be played back on other Blu-ray Disc players, etc. (e.g., title recorded with HE-AAC audio format), convert the recording mode to play them back. (⇒ 44, File Conversion)
- **DVD-R** **DVD-RW** **+R** **+RW** The disc must be finalised or have a Top Menu created (⇒ 70).
- **DVD-R** The disc created in AVCHD format can only be played back on AVCHD compatible equipment.

Edit

The available recording time does not increase even after deleting titles on the disc.

- **BD-R** **DVD-R** **+R** Available space on the disc does not increase even after deleting titles.
- **DVD-RW** **+RW** Available space on the disc increases when you delete the last title.

Cannot edit.

- You may not be able to edit on the HDD if there is no available space. Delete any unwanted titles to create empty space. (⇒ 41)

Cannot create a playlist.

- Creation or editing of playlists cannot be done on this unit.

Photo

The contents of the SD card cannot be read.

- Remove the card from the slot and then insert again. If this does not solve the problem, switch the unit to standby mode and turn it on again.

Copying, deleting and setting protection takes a long time.

- When there are a lot of folders and files, it may sometimes take a long time.

Photos do not play back normally.

- The images that were edited on the PC, such as Progressive JPEG, etc., may not play back. (⇒ 110)

Troubleshooting guide

Music

Tracks could not be copied to the HDD.

- Copyright protected tracks such as SCMS restrictions will not be copied.
- Recording from CDs that do not conform to CD-DA specifications (copy control CDs, etc.) cannot be guaranteed.

USB

This unit does not recognize the USB device correctly.

- If USB device is connected to this unit while using a video communication the USB device will not be recognized. Press [EXIT ⊗] and reconnect USB device.
- If inserted during playback the USB device may not be recognized by this unit. Disconnect and reconnect the USB device. If it still does not recognize the connection, switch the unit to standby mode and turn it on again.
- USB devices connected using a USB extension cable other than a dedicated one or a USB hub may not be recognized by this unit.
- This unit does not recognize USB HDDs other than those in which the size of one sector is 512-bytes. (For details, consult the dealer of your USB HDD.)

TV Guide

The TV Guide information is not displayed properly.

- Set the clock correctly. (⇒ 77, 91, Clock)
- Some broadcast may not send programme information.
- There was a programme change, or TV Guide information from a broadcast station was possibly not correctly transmitted.
- If signal quality is bad, the TV Guide system may not be able to receive any data.

Broadcast

Picture regularly breaks up on some channels.

- Adjust the reception with "Manual Tuning". (⇒ 77, 80)

Picture very infrequently breaks up on some or all channels.

- Electrical atmospheric interference caused by bad weather may cause pictures to break up and audio to mute or distort momentarily.

VIERA Link

VIERA Link does not work.

- Some functions may not work depending on the version of "HDAVI Control" of the connected TV, etc. This unit supports "HDAVI Control 5" functions.
- Check the settings of the connected TV, etc.
- If the connection for the equipment connected with HDMI was changed, or if there was a power failure or the plug was removed from the household mains socket, "HDAVI Control" may not work.
In this case, change TV (VIERA) setting for "HDAVI Control" again.
- This unit does not support "ONE TOUCH PLAY" function of the Panasonic AV Control Receiver.

Network

You cannot access this unit from DLNA compatible equipment on the network.

- Check the network connection and the network settings. (⇒ 17, 20)
- It may not be possible to connect depending on the types of the equipment or the status of the equipment.

When using this unit as a server, video frames are dropped.

- Change the following settings:
 - Conversion Setting for DLNA (⇒ 77, 89)
 - Resolution Setting for DLNA (⇒ 77, 89)

You cannot play contents properly from DLNA compatible equipment on the network.

- There may be some video that cannot be played back on DLNA compatible equipment depending on the equipment.
- Following titles cannot be played back:
 - A title with access restriction
 - A title with incompatible format
- Playback via DLNA compatible equipment may not be performed when this unit is in the following conditions:
 - While playing back a BD-Video
 - While simultaneously performing High speed copy and recording
 - While displaying the Setup menu
 - While executing functions using a network, such as "VIERA Connect"
- You cannot play back simultaneously from two or more items of DLNA compatible equipment.

When using Wireless LAN connection, video from the DLNA Certified media server is not played back or video frames are dropped during playback.

- Use 802.11n (2.4 GHz) Wireless router.
Simultaneous use with a microwave, cordless telephone etc. at 2.4 GHz may result in connection interruptions or other problems.
- On the "Wireless Settings" screen (⇒ 87), the continuous lighting of at least four "Reception" indicators is the target for a stable connection. If three or fewer indicators are lit or the connection is being interrupted, change the position or angle of your Wireless router. If there is no improvement, connect to a wired network and perform the "Easy Network Setting" (⇒ 20) again.

Troubleshooting guide

Reset

To return all the settings to the factory preset

Perform "Shipping Condition" or "Default Settings". (⇒ 77, 93)

Messages on the unit's display

The following messages or service numbers appear on the unit's display when something unusual is detected.

BD □

("□" stands for a number.)

The remote control and main unit are using different codes. Change the code on the remote control. (⇒ 97)

CONV

Selected titles in the USB HDD are being converted.

Do not disconnect the USB HDD from this unit.

GUIDE

TV Guide data is being downloaded.

HARD ERR

If there is no change after switching the unit to standby mode and turning it on, consult the dealer.

NoERAS

You cannot delete items on this disc.
The disc may be damaged.

NoREAD

- The disc is dirty. (⇒ 10) The unit cannot record, play, or edit.
- The lens cleaner has finished cleaning.
Press [**▲** OPEN/CLOSE] on the main unit to eject the disc.

NoWRIT

You cannot write to this disc.
The disc may be damaged. Use a new disc.

PLEASE WAIT

- Displayed when the unit is started and is switched to standby mode.
- There was a power failure or the AC plug was disconnected while the unit was on. The unit is carrying out its recovery process. Wait until the message disappears.

PROG FULL

There are already 32 timer programmes. Delete unnecessary timer programmes. (⇒ 32)

REMOVE

The USB device is drawing too much power.
Remove the USB device.

START

Update of the software (firmware) is started.
You cannot operate the unit until the update is complete. (⇒ 94)

SW-DL

Software (firmware) is downloading.
Download will stop when the unit is turned on, or the timer recording starts. (⇒ 94)

UNSUPPORT

The media is not supported.

UPD □/□

("□" stands for a number.)

The software (firmware) is being updated.
You cannot operate the unit until the update is complete. (⇒ 94)

U59

The unit is hot.
The unit switches to standby for safety reasons.
Wait for about 30 minutes until the message disappears.
Do not block the cooling fan on the rear of the unit.

U61

(When a disc is not inserted) A malfunction has occurred. The unit is trying to restore to the normal operation. Once the message disappears you can use the unit again.
If it remains displayed, consult the dealer.

U76

HDMI cannot be output because it is connected to a model that does not support copyright protection.

U77

Due to the current disc not having authorised copyright information, video output is not performed.

Troubleshooting guide

U88

(When a disc is inserted) There was something unusual detected with the disc or the unit. The unit is trying to restore to the normal operation. Once the message disappears you can use the unit again.

If it remains displayed, consult the dealer.

U99

The unit fails to operate properly. Press [⏻/I] on the main unit to switch the unit to standby mode. Now press [⏻/I] on the main unit again to turn the unit on.

X HOLD

The HOLD function is activated. (⇒ 95)

H□□ or F□□

("□" stands for a number.)

There is something unusual. (The service number displayed after H and F depends on the unit's condition.)

Reset the unit as follows:

- 1 Disconnect the plug from the household mains socket, wait a few seconds, then reconnect it.
- 2 Press [⏻/I] to turn the power on. (The unit may be fixed.)

Request service from the dealer. Inform the dealer of the service number when requesting service.

When you experience problems with Easy Network Setting

If there is any problem, the following message is displayed on the screen.

Wireless Settings

Display	Check the following
A conflict with other devices occurred.	<ul style="list-style-type: none"> • Please wait a few moments, and then try again.
A time out error occurred.	<ul style="list-style-type: none"> • Setting of the Wireless router for MAC Address etc. • The signal may be weak. • The SSID and the encryption key of the Wireless router.
An authentication error or a time out error occurred.	<ul style="list-style-type: none"> • Please wait a few moments, and then try again.
A device error occurred.	<ul style="list-style-type: none"> • If the problem is not solved, consult your dealer.

Easy Network Setting (Home Network Connection Check)

Display	Check the following
1. LAN cable connection or Wireless setting: "Fail"	<ul style="list-style-type: none"> • Connection of the LAN cables (⇒ 17) • Settings of the hub and router
2. IP address setting: "Fail"	
3. Connection to gateway: "Fail"	
1. LAN cable connection or Wireless setting: "Pass"	<ul style="list-style-type: none"> • Connection and settings of the hub and router • Settings of "IP Address / DNS Settings" (⇒ 77, 88)
2. IP address setting: "Fail"	
3. Connection to gateway: "Fail"	
1. LAN cable connection or Wireless setting: "Pass"	
2. IP address setting: "Pass"	
3. Connection to gateway: "Fail"	
1. LAN cable connection or Wireless setting: "Pass"	
2. IP address setting: "Home network available"	
3. Connection to gateway: "Fail"	

Easy Network Setting (Internet Connection Test)

Display	Check the following
Cannot find the server. (B019)	<ul style="list-style-type: none"> • "Primary DNS" and "Secondary DNS" settings of "IP Address / DNS Settings" (⇒ 77, 88)
No connection could be made to the server. (B020)	<ul style="list-style-type: none"> • The server may be busy or the service may have been suspended. Please wait a few moments, and then try again. • Settings of "Proxy Server Settings" (⇒ 77, 88) and the router.

Specifications

Specifications are subject to change without notice.

■ General

Dimensions: 430 mm (W)
66 mm (H)

(excluding the projecting parts)
238 mm (D)

(including the projecting parts)
249 mm (D)

Mass: Approx. 3.2 kg

Power supply: AC 220 V to 240 V, 50 Hz

Power consumption: Approx. 32 W

Power consumption in standby mode:

"Quick Start" is activated and "Power Save
for Network Standby" is set to "Off"

Approx. 6 W

"Quick Start" is activated and "Power Save
for Network Standby" is set to "On"

Approx. 5 W

"Quick Start" is not activated and
"RF OUT (Aerial Signal)" is set to "Off"

Approx. 0.2 W

Operating temperature: 5 °C to 40 °C

Operating humidity range: 10 % to 80 % RH
(no condensation)

■ TV system

Tuner System: DVB-T

Country: Australia

Channel Coverage: VHF 6~12
UHF 27~69

■ Recording system

Video: MPEG-2 (Hybrid VBR),
MPEG-4 AVC/H.264

Audio:

Dolby Digital (XP, SP, LP, EP mode: 2ch)

Dolby Digital

(DR mode, HG, HX, HE, HL, HM mode:

Max 5.1ch (DVB-T))

HE-AAC (DR mode: 2ch (DVB-T))

MPEG (DR mode: 2ch)

■ Video

Video system: PAL/NTSC

Analog video in (pin jack): 1 pc.

Input level: 1 Vp-p (75 Ω)

■ Audio

Analog audio L/R in (pin jack): 1 pc.

Input level:

Full scale 2.0 Vrms at 1 kHz (> 10 kΩ)

Analog audio L/R out (pin jack): 1 pc.

Output level:

Full scale 2.0 Vrms at 1 kHz (< 1 kΩ)

Digital audio out (optical): 1 pc.

PCM, Dolby Digital, DTS, MPEG

Digital audio out (coaxial): 1 pc.

PCM, Dolby Digital, DTS, MPEG

■ HDMI terminal

HDMI output (19 pin type A): 1 pc.

PCM, Dolby Digital, DTS, MPEG,

Dolby Digital Plus, Dolby TrueHD,

DTS-HD Master Audio,

DTS-HD High Resolution Audio

• This unit supports "HDAVI Control 5"
function.

■ Internal HDD capacity

1 TB

■ Other terminals

USB Port (Type A): 2 pcs.

SD Card Slot: 1 pc.

LAN (Ethernet) Port: 1 pc.

10BASE-T/100BASE-TX

■ Wireless LAN

Standard compliance: IEEE802.11b/g/n

Frequency range: 2.4 GHz band

Security*: WPA™/WPA2™

(Encryption type: TKIP/AES,

Authentication type: PSK)

WEP (64 bit/128 bit)

* This unit supports WPA and WPA2
encryption.

■ Recordable discs

BD-RE (SL/DL):	1-2X SPEED (Ver. 2.1)
BD-R (SL/DL):	1-2X SPEED (Ver. 1.1), 1-4X SPEED (Ver. 1.2), 1-6X SPEED (Ver. 1.3), 1-2X SPEED LTH type (Ver. 1.2), 1-6X SPEED LTH type (Ver. 1.3)
DVD-RAM:	2X SPEED (Ver. 2.0), 2-3X SPEED (Ver. 2.1), 2-5X SPEED (Ver. 2.2)
DVD-R (SL):	1X SPEED (Ver. 2.0), 1-4X SPEED (Ver. 2.0), 1-8X SPEED (Ver. 2.0), 1-16X SPEED (Ver. 2.1)
DVD-R (DL):	2-4X SPEED (Ver. 3.0), 2-8X SPEED (Ver. 3.0)
DVD-RW:	1X SPEED (Ver. 1.1), 1-2X SPEED (Ver. 1.1), 2-4X SPEED (Ver. 1.2), 2-6X SPEED (Ver. 1.2)
+R (SL):	2.4X SPEED (Ver. 1.0), 2.4-4X SPEED (Ver. 1.1), 2.4-8X SPEED (Ver. 1.2), 2.4-16X SPEED (Ver. 1.3)
+R (DL):	2.4X SPEED (Ver. 1.0), 2.4-8X SPEED (Ver. 1.1)
+RW:	2.4X SPEED (Ver. 1.1), 2.4-4X SPEED (Ver. 1.2)

■ Optical pick-up

System with 2 lenses, 3 integration units
(405 nm wavelength for BDs,
661 nm wavelength for DVDs,
783 nm wavelength for CDs)

■ LASER specification

Class 1 LASER Product	
Wave length:	405 nm (BDs) 661 nm (DVDs) 783 nm (CDs)

Laser power:

No hazardous radiation is emitted with
the safety protection

■ Recording system

BD-RE (SL/DL):	Blu-ray Disc Rewritable Format
BD-R (SL/DL):	Blu-ray Disc Recordable Format
DVD-RAM:	DVD Video Recording format
DVD-R (SL/DL):	DVD-Video format
DVD-RW:	DVD-Video format
+R (SL/DL), +RW	

■ Copying speed from HDD to BD-R in High Speed Copy

HDD (HM, 1 hour) → 6X Speed BD-R

Copying speed: 60x
Required time: Approx. 1 min.

- The above rate in the list indicates the shortest time and fastest speed required for copying one-hour title from HDD to the disc by High-Speed copying.
- The required amount of time and speed may vary depending on the conditions such as the area where information is written or unique feature on the disc.

■ Region code

DVD:	#4
BD:	Region B

■ Playable discs

BD-Video (Blu-ray 3D, BD-Live)	
BD-ROM Version 2.4	
DVD-Video:	DVD-Video format
CD-DA (Audio CD)	
BD-RE:	Ver. 2.1, JPEG ^{*1} , MPO ^{*1}
BD-RE DL:	Ver. 2.1, JPEG ^{*1} , MPO ^{*1}
BD-R:	Ver. 1.3, LTH type Ver. 1.3, Xvid ^{*1} , MKV ^{*1}
BD-R DL:	Ver. 1.3, Xvid ^{*1} , MKV ^{*1}
DVD-RAM:	DVD Video Recording format, AVCHD format, JPEG ^{*2} , MPO ^{*2}
DVD-R:	DVD-Video format ^{*3} , AVCHD format ^{*3} , JPEG ^{*2} , MPO ^{*2} , MP3 ^{*2} , Xvid ^{*2} , MKV ^{*2}
DVD-R DL:	DVD-Video format ^{*3} , AVCHD format ^{*3} , JPEG ^{*2} , MPO ^{*2} , MP3 ^{*2} , Xvid ^{*2} , MKV ^{*2}
DVD-RW:	DVD-Video format ^{*3} , DVD Video Recording format, AVCHD format ^{*3}
+R:	Video ^{*3} , AVCHD format ^{*3}
+R DL:	Video ^{*3} , AVCHD format ^{*3}
+RW:	Video ^{*3} , AVCHD format ^{*3}
CD-R/CD-RW:	CD-DA, JPEG ^{*2} , MPO ^{*2} , MP3 ^{*2} , Xvid ^{*2} , MKV ^{*2}

^{*1} BD disc needs to be based on UDF format.

^{*2} DVD/CD discs need to be based on UDF
or ISO9660 format.

^{*3} Finalising is necessary.

Specifications

■ SD Card

Compatible media:	SD Memory Card*
Format:	
SD Card:	only FAT12, FAT16
SDHC Card:	only FAT32
SDXC Card:	only exFAT
Data that can be played:	JPEG, MPO, AVCHD format, MPEG-2, MP4

- * Includes SDHC/SDXC cards.
Includes mini type cards (need a miniSD™ adaptor).
Includes micro type cards (need a microSD™ adaptor).

■ USB device

USB standard:	USB2.0 High Speed
Format:	FAT12, FAT16, FAT32, NTFS
Data that can be played:	MP3, JPEG, MPO, Xvid, MKV, MP4, MPEG-2

Audio information

The audio output differs depending on which terminals are connected to the amplifier/receiver, and the setting on this unit. (⇒ 84, Digital Audio Output)

- The number of channels listed is the maximum possible number of output channels when connected to amplifier/receiver compatible with the respective audio format.

Terminal	Digital Audio Output	
	Bitstream	PCM
HDMI AV OUT	Output using original audio*1	BD-Video: 7.1ch PCM*1, 2 DVD-Video: 5.1ch PCM
DIGITAL AUDIO OUT	Dolby Digital/ DTS Digital Surround	Down-mixed 2ch PCM

*1 When "BD-Video Secondary Audio" is set to "On", the audio will be output as Dolby Digital, DTS Digital Surround or 5.1ch PCM.

*2 The audio output is amplified from 5.1ch or 6.1ch to 7.1ch depending on the DTS, Inc. specifications.

Maximum numbers of titles that can be recorded

HDD	999 titles (When continuously recording for long durations, titles are automatically divided every 8 hours.)
BD-RE, BD-R	200 titles on one disc.
DVD-RAM, DVD-R, DVD-RW	99 titles on one disc.
+R, +RW	49 titles on one disc.

Information for the files other than recorded programmes

■ JPEG/MPO

Playable media: HDD, BD-RE (SL/DL), DVD-RAM, DVD-R, DVD-R DL, CD-R, CD-RW, SD Card, USB device

Compatible pixels:
Between 34×34 and 8192×8192 pixels
(Sub sampling is 4:2:2 or 4:2:0)
Files:
JPEG conforming DCF
(Design rule for Camera File system)
MPO conforming MPF
(Multi Picture Format)

Maximum numbers of folders and files:

Media	Maximum folders	Maximum files
HDD	—	20000
BD-RE	500	10000
DVD-RAM	500	10000
DVD-R	500	10000
CD-R, CD-RW	500	10000
SD Card	500	10000
USB device	500	10000

- This unit is not compatible with MOTION JPEG or Progressive JPEG.

■ MP3

Playable media: HDD, DVD-R, DVD-R DL,
CD-R, CD-RW, USB device

Compression rate: 32 kbps to 320 kbps

Sampling rate: 16 kHz, 22.05 kHz, 24 kHz,
32 kHz, 44.1 kHz, 48 kHz

Maximum numbers of folders and files:

Media	Maximum folders	Maximum files
HDD	—	40000
DVD-R	300	3000
CD-R, CD-RW	300	3000
USB device	300	3000

■ MP4

Playable media: SD Card, USB device

MPEG-4 AVC/H.264:
Up to High Profile, Level 4.2

Video resolution: Up to 1920×1080

MPEG-4 AAC-LC

Sampling rate: 8 kHz to 48 kHz

Number of audio channel: 1 or 2

■ MKV

Playable media: BD-R (SL/DL), DVD-R,
DVD-R DL, CD-R, CD-RW, USB device

MPEG-4 AVC (H.264) profile is up to High
Profile, Level 4.

AAC-LC, MP3, Dolby Digital audio, DTS,
PCM, Vorbis and FLAC can be decoded.

Maximum number of folders: 300 folders
(including the root folder)

Maximum number of files: 200 files

■ SD-Video (Standard Definition)

Playable media: SD Card, USB device

Codec: MPEG-2

File Format: SD-Video format*

used on Standard Definition Camera
(Panasonic and some other's)

* SD-Video Entertainment Video Profile

■ HD-Video (High Definition)

Playable media: SD Card, USB device

Codec: MPEG-4 AVC/H.264

File Format: AVCHD format conforming

Specifications

Recording modes and approximate recording times

Depending on the content being recorded, the recording time may become shorter than indicated.

■ DR mode

Recording Mode	HDD	BD-RE, BD-R	
	(1 TB)	Single Layer (25 GB)	Dual Layer (50 GB)
DR (HD quality)	140 hours	3 hours 20 min.	6 hours 40 min.
DR (SD quality)	264 hours	6 hours 30 min.	13 hours

• Recording time of DR mode may vary depending on the bit rate of broadcasting:

- High Definition (HD) quality: estimated bit rate is 15 Mbps
- Standard Definition (SD) quality: estimated bit rate is 8 Mbps

• Regarding recording time remaining:

Remaining time in the DR mode is calculated with a bit rate of 15 Mbps. But the bit rate differs depending on the broadcast, so the displayed remaining time might be different from the actual remaining time.

■ HG, HX, HE, HL, HM modes

Recording Mode	HDD (1 TB)	BD-RE, BD-R	
		Single Layer (25 GB)	Dual Layer (50 GB)
HG	157 hours	4 hours	8 hours
HX	235 hours	6 hours	12 hours
HE	353 hours	9 hours	18 hours
HL	472 hours	12 hours	24 hours
HM	684 hours	17 hours 30 min.	35 hours

■ XP, SP, LP, EP modes

Recording Mode	HDD (1 TB)	BD-RE, BD-R	
		Single Layer (25 GB)	Dual Layer (50 GB)
XP	215 hours	5 hours 15 min.	10 hours 30 min.
SP	431 hours	10 hours 30 min.	21 hours
LP	862 hours	21 hours	42 hours
EP (6 hours)*	1293 hours	31 hours 30 min.	63 hours
EP (8 hours)	1724 hours	42 hours	84 hours

Recording Mode	DVD-RAM		DVD-R, DVD-RW, +R, +RW (4.7 GB)	DVD-R DL, +R DL (8.5 GB)
	Single-sided (4.7 GB)	Double-sided (9.4 GB)		
XP	1 hour	2 hours	1 hour	1 hour 45 min.
SP	2 hours	4 hours	2 hours	3 hours 35 min.
LP	4 hours	8 hours	4 hours	7 hours 10 min.
EP (6 hours)*	6 hours	12 hours	6 hours	10 hours 45 min.
EP (8 hours)	8 hours	16 hours	8 hours	14 hours 20 min.

* When "Recording time in EP mode" is set to "6 hours" (⇒ 82)

• Regarding recording time remaining:

This unit records using a VBR (Variable bit rate) data compression system to vary recorded data segments to match video data segments which may cause differences in the displayed amount of time and space remaining for recording.

Licenses

"AVCHD", "AVCHD 3D", "AVCHD Progressive" and "AVCHD 3D/Progressive" are trademarks of Panasonic Corporation and Sony Corporation.

Copyright 2004-2010 Verance Corporation. Cinavia™ is a Verance Corporation trademark. Protected by U.S. Patent 7,369,677 and worldwide patents issued and pending under license from Verance Corporation. All rights reserved.

DLNA, the DLNA Logo and DLNA CERTIFIED are trademarks, service marks, or certification marks of the Digital Living Network Alliance.

DVB and the DVB logos are trademarks of the DVB Project.

Manufactured under license from Dolby Laboratories.
Dolby and the double-D symbol are trademarks of Dolby Laboratories.

Manufactured under license under U.S. Patent Nos: 5,956,674; 5,974,380; 6,226,616; 6,487,535; 7,392,195; 7,272,567; 7,333,929; 7,212,872 & other U.S. and worldwide patents issued & pending. DTS-HD, the Symbol, & DTS-HD and the Symbol together are registered trademarks & DTS-HD Master Audio | Essential is a trademark of DTS, Inc. Product includes software. © DTS, Inc. All Rights Reserved.

"DVD Logo" is a trademark of DVD Format/Logo Licensing Corporation.

MPEG Layer-3 audio coding technology licensed from Fraunhofer IIS and Thomson.

This product is licensed under the AVC patent portfolio license and VC-1 patent portfolio license for the personal and non-commercial use of a consumer to (i) encode video in compliance with the AVC Standard and VC-1 Standard ("AVC/VC-1 Video") and/or (ii) decode AVC/VC-1 Video that was encoded by a consumer engaged in a personal and non-commercial activity and/or was obtained from a video provider licensed to provide AVC/VC-1 Video. No license is granted or shall be implied for any other use. Additional information may be obtained from MPEG LA, LLC.
See <http://www.mpegla.com>.

SDXC Logo is a trademark of SD-3C, LLC.

The Skype name, associated trade marks and logos and the "S" logo are trade marks of Skype.

VIERA Connect is a trademark of Panasonic Corporation.

The Wi-Fi CERTIFIED Logo is a certification mark of the Wi-Fi Alliance.
The Wi-Fi Protected Setup Mark is a mark of the Wi-Fi Alliance.



"Wi-Fi", "Wi-Fi Protected Setup", "WPA" and "WPA2" are marks or registered marks of the Wi-Fi Alliance.

HDAVI Control™ is a trademark of Panasonic Corporation.

HDMI, the HDMI Logo, and High-Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing LLC in the United States and other countries.

Java is a registered trademark of Oracle and/or its affiliates.



Windows is a trademark or a registered trademark of Microsoft Corporation in the United States and other countries.

This product incorporates the following software or technology:

- (1) the software developed independently by or for Panasonic Corporation,
- (2) the software owned by third party and licensed to Panasonic Corporation,
- (3) the software developed by the Independent JPEG Group,
- (4) the software developed by the Freetype Project,
- (5) the software licensed under the GNU LESSER General Public License (LGPL) and/or,
- (6) open sourced software other than the software licensed under the LGPL,
- (7) Windows Media digital right management technology (WM-DRM) licensed by Microsoft Corporation or its affiliates.

For the software categorized as (5), please refer to the terms and conditions of LGPL, as the case may be at

<http://www.gnu.org/licenses/old-licenses/lgpl-2.1.html>

In addition, the software categorized as (5) are copyrighted by several individuals. Please refer to the copyright notice of those individuals at

<http://panasonic.net/avc/oss/diga/FCRCP13A.html>

The LGPL software is distributed in the hope that it will be useful, but WITHOUT ANY WARRANTY, without even the implied warranty of MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE.

At least three (3) years from delivery of products, Panasonic will give to any third party who contacts us at the contact information provided below, for a charge no more than our cost of physically performing source code distribution, a complete machine-readable copy of the corresponding source code covered under LGPL.

Contact Information

oss-cd-request@gg.jp.panasonic.com

Source code covered under LGPL is also freely available to you and any other member of the public via our website below.

<http://panasonic.net/avc/oss/diga/FCRCP13A.html>

For the software categorized as (5) and (6), please refer to the applicable license terms included in the "Software Licence" menu on product.

Further, for WM-DRM categorized as (7), please be aware of the following.

(a) This product is protected by certain intellectual property rights of Microsoft Corporation and third parties. Use or distribution of such technology outside of this product is prohibited without a license from Microsoft or an authorized Microsoft subsidiary and third parties.

(b) Content providers are using the digital rights management technology for Windows Media contained in this device ("WM-DRM") to protect the integrity of their content ("Secure Content") so that their intellectual property, including copyright, in such content is not misappropriated. This device uses WM-DRM software to play Secure Content ("WM-DRM Software"). If the security of the WM-DRM Software in this device has been compromised, owners of Secure Content ("Secure Content Owners") may request that Microsoft revoke the WM-DRM Software's right to acquire new licenses to copy, display and/or play Secure Content.

Revocation does not alter the WM-DRM Software's ability to play unprotected content. A list of revoked WM-DRM Software is sent to your device whenever you download a license for Secure Content from the Internet or from a PC. Microsoft may, in conjunction with such license, also download revocation lists onto your device on behalf of Secure Content Owners.

Vorbis, FLAC, WPA Supplicant

The software licenses are displayed when "Software Licence" in the Setup menu is selected. (⇒ 92)

Limited Warranty

Panasonic Warranty

1. The product is warranted for 12 months from the date of purchase. Subject to the conditions of this warranty Panasonic or its Authorised Service Centre will perform necessary service on the product without charge for parts or labour, if in the opinion of Panasonic, the product is found to be faulty within the warranty period.
2. This warranty only applies to Panasonic products purchased in Australia and sold by Panasonic Australia or its Authorised Distributors or Dealers and only where the products are used and serviced within Australia or its territories. Warranty cover only applies to service carried out by a Panasonic Authorised Service Centre and only if valid proof of purchase is presented when warranty service is requested.
3. This warranty only applies if the product has been installed and used in accordance with the manufacturer's recommendations (as noted in the operating instructions) under normal use and reasonable care (in the opinion of Panasonic). The warranty covers normal domestic use only and does not cover damage, malfunction or failure resulting from use of incorrect voltages, incorrect installation, accident, misuse, neglect, build-up of dirt or dust, abuse, maladjustment of customer controls, mains supply problems, thunderstorm activity, infestation by insects or vermin, tampering or repair by unauthorised persons (including unauthorised alterations), introduction of sand, humidity or liquids, commercial use such as hotel, office, restaurant, or other business or rental use of the product, exposure to abnormally corrosive conditions or any foreign object or matter having entered the product.
4. This warranty does not cover the following items unless the fault or defect existed at the time of purchase:

(a) Cabinet Part(s)	(e) DVD, Blu-ray or Recordable Discs
(b) Video or Audio Tapes	(f) Video / Audio Heads from wear and tear in normal use
(c) SD cards or USB devices	(g) Information stored on Hard Disk Drive, USB stick or SD card
(d) User replaceable Batteries	(h) DTV reception issues caused by TV Aerial / Cabling / Wall socket(s)

 etc
5. Some products may be supplied with Ethernet connection hardware. The warranty is limited on such products and will not cover
 - (a) Internet and or DLNA connection / setup related problems
 - (b) Access fees and or charges incurred for internet connection
 - (c) The use of incompatible software or software not specifically stipulated in the product operations manual; and
 - (d) Any indirect or consequential costs associated with the incorrect use or misuse of the hardware, its connection to the internet or any other device.
6. To claim warranty service, when required, you should:
 - Telephone Panasonic's Customer Care Centre on 132600 or visit our website referred to below and use the Service Centre Locator for the name/address of the nearest Authorised Service Centre.
 - Send or take the product to a Panasonic Authorised Service Centre together with your proof of purchase receipt as a proof of purchase date. Please note that freight and insurance to and / or from your nearest Authorised Service Centre must be arranged by you.
 - Note that home or pick-up/delivery service is available for the following products in the major metropolitan areas of Australia or the normal operating areas of the nearest Authorised Service Centres:
 - Plasma/LCD televisions / displays (screen size greater than 103 cm)
7. The warranties hereby conferred do not extend to, and exclude, any costs associated with the installation, de-installation or re-installation of a product, including costs related to the mounting, de-mounting or remounting of any screen, (and any other ancillary activities), delivery, handling, freighting, transportation or insurance of the product or any part thereof or replacement of and do not extend to, and exclude, any damage or loss occurring by reason of, during, associated with, or related to such installation, de-installation, re-installation or transit.

Panasonic Authorised Service Centres are located in major metropolitan areas and most regional centres of Australia, however, coverage will vary dependant on product. For advice on exact Authorised Service Centre locations for your product, please telephone our Customer Care Centre on 132600 or visit our website and use the Service Centre Locator.

In addition to your rights under this warranty, Panasonic products come with consumer guarantees that cannot be excluded under the Australian Consumer Law. If there is a major failure with the product, you can reject the product and elect to have a refund or to have the product replaced or if you wish you may elect to keep the goods and be compensated for the drop in value of the goods. You are also entitled to have the product repaired or replaced if the product fails to be of acceptable quality and the failure does not amount to a major failure.

If there is a major failure in regard to the product which cannot be remedied then you must notify us within a reasonable period by contacting the Panasonic Customer Care Centre. If the failure in the product is not a major failure then Panasonic may choose to repair or replace the product and will do so in a reasonable period of time from receiving notice from you.

**THIS WARRANTY CARD AND THE PURCHASE DOCKET (OR SIMILAR PROOF OF PURCHASE)
SHOULD BE RETAINED BY THE CUSTOMER AT ALL TIMES**

If you require assistance regarding warranty conditions or any other enquiries, please visit the **Panasonic Australia** website www.panasonic.com.au or contact by phone on **132 600**
If phoning in, please ensure you have your operating instructions available.

Panasonic Australia Pty. Limited

ACN 001 592 187 ABN 83 001 592 187

1 Innovation Road, Macquarie Park NSW 2113

PRO-031-F11 Issue: 4.0

01-01-2011

Index

A

Aspect	86, 95
Audio	
Broadcasts	25
Digital Audio	110
Playback	39
Auto Setup	19, 80
AVCHD	
Copy	53, 63
Playback	33, 36

B

BD-Live	37
BD-Video	
BD-Live	37, 81
Playback	36
3D	40
BD-Video Parental Control	81

C

Channel information	24
Channel List	23
Edit	80
Chapter	35, 39, 45
Chapter Creation	82
Child Lock (Parental Rating)	80
Clock	91
Connection	
Amplifier/receiver	15
AUDIO OUT terminal	16
Basic connections	14
DIGITAL AUDIO OUT terminal	16
HDMI cable	14, 15
Network	17
Set Top Box	15
Video equipment	15
Copy (Music)	58
Copy (Photo)	57
Copy (Video)	46
Copy title playing	53
Finalised disc	52
HD Video (AVCHD)	53, 63
SD Video (MPEG2)	64

D

Delete	
Delete BD-Video data	37
Music	61
Photo	56
Video	41
Delete all photos	
HDD	82
Delete all titles	
Disc	69
HDD	82
USB HDD	83
Delete BD-Video data	37
DIRECT NAVIGATOR	
Music	59
Photo	54
Video	33
Disc	
Delete all titles	69
Finalise	70
Format	69
Media information	6
Protection	69
DLNA	
Client	66
Media Renderer	67
Server	65, 89
DVD-Video	
Playback	36
DVD-Video Parental Control	81
E	
Easy Network Setting	20, 87
Easy setting	19
Edit (Music)	61
Edit (Photo)	56
Edit (Video)	42
Chapter	39, 45
Delete	41, 42
File Conversion	44
Protection	42
Entering text	95

Index

F

Favourites	79
File Conversion	44
Finalise	70
Format	
Disc	69
HDD	82
SD Card	69
USB HDD	83
FUNCTION MENU	22

H

HD Video (AVCHD)	
Copy	53, 63
Play	33, 36
HDAVI Control	73, 87
HDD	
Delete all photos	82
Delete all titles	82
Format	82
Media information	6
HDMI cable	14
HOLD function	95

J

JPEG	54
-------------------	----

L

Language code list	93
---------------------------------	----

M

Manual Tuning	80
Media	
Disc	6
HDD	6
SD Card	6, 10
USB HDD	6
USB memories	6, 10
Media Renderer	67
Menu screen	36
MKV	
Playback	36
MPEG2	64
MPO	54
MP3	58
Music	
Copy	58
Delete	61
Edit	61
Playback	58

N**Network**

BD-Live	37
Connection	17
DLNA (Client)	66
DLNA (Server)	65, 89
Setting	87
Software (Firmware) Update	94
VIERA Connect	68

P

PAUSE LIVE TV	25
----------------------------	----

Photo

Copy	57
Delete	56
Edit	56
Playback	54
Protection	56
Slideshow	54, 60

PIN	23
------------------	----

Playback menu	74
----------------------------	----

Playback (Music)

Audio CD	58
MP3	58
Recorded on HDD	59

Playback (Photo)	54
-------------------------------	----

Slideshow	54, 60
-----------------	--------

Playback (Video)

AVCHD	33, 36
BD-Video	36
BD-Video Parental Control	81
Changing audio	39
Chapter	35
DVD-Video	36
DVD-Video Parental Control	81
MKV	36
Playlist created on other equipment	36
Recorded video contents	33
Status message	38
Subtitles	39
Xvid	36
3D	40

Protection

Disc	69
HOLD function	95
Photo	56
Video	42

Pure Sound Mode	81
------------------------------	----

Q		
Quick Start	90	
R		
Recording	27	
Aspect	82	
From external equipment	62	
High speed copy	82	
Recording mode	8, 112	
Recording time	112	
Timer recording	29	
Recording mode	8, 112	
Remote control	12	
HOLD function	95	
Manufacturer and Code No.	18	
Remote control code	91	
TV operation	18	
Reset	93, 100, 104	
REWIND LIVE TV	25, 82	
S		
SD Card		
Format	69	
Media information	6, 10	
miniSD / microSD	10	
SD Video (MPEG2)		
Copy	64	
Setting		
Auto Setup	19, 80	
Easy Network Setting	20, 87	
Easy setting	19	
Setup menu	77	
Connection	85	
Digital TV Tuning	79	
Display	85	
HDD / Disc / USB HDD	81	
Network	87	
Others	90	
Picture	83	
Sound	84	
Skype™	68	
Slideshow	54, 60	
Software (Firmware) Update	94	
Subtitles		
Broadcasts	25	
Playback	39	
T		
Teletext	25, 85	
Timer recording	29	
Auto Renewal Recording	30	
Manually programming timer recording	30	
Top Menu		
Create Top Menu	70	
Tuning		
Channel List	80	
Manual Tuning	80	
Parental Rating	80	
Signal condition	80	
TV Guide		
Operation	24	
Timer recording	29	
TV System	86	
U		
Unit's display		
Messages	104	
USB HDD		
Cancellation of all USB HDD Registrations	83	
Delete all titles	83	
Disconnection	71, 83	
Format	83	
Media information	6	
Registration	71, 83	
USB memories		
Media information	6, 10	
V		
Video		
Copy	46	
Delete	41	
DIRECT NAVIGATOR	33	
Edit	42	
Playback	33, 36	
Protection	42	
Recording	27	
VIERA Connect	68	
VIERA Link	73, 87	
X		
Xvid		
Playback	36	
3D	40	

Information on Disposal in other Countries outside the European Union



This symbol is only valid in the European Union.

If you wish to discard this product, please contact your local authorities or dealer and ask for the correct method of disposal.

The recording and playback of content on this or any other device may require permission from the owner of the copyright or other such rights in that content. Panasonic has no authority to and does not grant you that permission and explicitly disclaims any right, ability or intention to obtain such permission on your behalf. It is your responsibility to ensure that your use of this or any other device complies with applicable copyright legislation in your country. Please refer to that legislation for more information on the relevant laws and regulations involved or contact the owner of the rights in the content you wish to record or playback.

Personal information handling

To provide functions and services of this unit, a device ID, device password and usage history information are stored and managed securely in an appropriate security environment of Panasonic. Please note that usage history and other information may be collected for purposes such as improving products and services in such a way that individuals cannot be identified.

Panasonic Corporation
Web Site: <http://panasonic.net>

En

VQT4W66

F0213MD0